PATENT SPECIFICATION

(11) 1 454 266

1 454 266

(21) Application No. 50372/73 (22) Filed 30 Oct. 1973
(31) Convention Application No. 302 371
(32) Filed 30 Oct. 1972 in
(33) United States of America (US)
(44) Complete Specification published 3 Nov. 1976
(51) INT CL² G06F 15/02
(52) Index at acceptance
G4A 10EX 15A1 16D 17P 1D 2F5 2HX 3W10W2 5A 9E CX
DT

(19)



(54) IMPROVED BUSINESS CALCULATOR

(71) We, HEWLETT-PACKARD COMPANY a corporation organized and existing under the laws of the State of California, United States of America of 1501 Page Mill Road, Palo Alto, California, United States of America, do hereby declare the invention, for which we pray that a patent may be granted to us, and the method by which it is to be performed, to be particularly described in and by the following statement:—

This invention is concerned with improvements in or relating to calculators and is more particularly concerned with non-programmable business calculators.

Conventional business calculators generally have less capability and flexibility than is required to meet the needs of the business user. They are usually designed to solve the most elementary calculation of one business discipline (i.e. banking or real estate, or finance, etc) and lack the capability and flexibility for inter-disciplinary business calculations. For example, there are special calculators for financiers to solve bond yield and bond price problems, and calculators for realtors to solve mortgage amortization and depreciation problems. However, a financier who wishes to quickly compare the rate of return between bonds and real estate will either need two expensive calculators or will have to compromise the degree of accuracy of the calculation with gross mathematical approximations performed on a single purpose calculator. This limitation of single purpose calculators can lead to critical errors in decision making. Because conventional single purpose business calculators are designed for special applications by specialists in that area, the keyboards are generally not self-explanatory and appear as a befuddling collection of buttons and switches with special symbols. This requires a longer user orientation period before productive usage begins.

Due to the high cost and the limited capabilities of the available business calculators, and sometimes, simply because there is no calculator available to perform certain calculations, the majority of the everyday business calculations are still made with the aid of published tables. Published tables are the only convenient means available for solving certain financial problems, such as calculations for the discount amount in discounted notes and the equivalent interest rate between accrued interest notes and discounted notes. The main disadvantage of using tables is the inherent restriction to the discrete values given in the table. The accuracy of the calculation is limited to the accuracy of the tables and the need for interpolation further compromises the calculation. For example, a widely used bond value table has discrete values for bond yield to two decimal places and the interest rate is given in one-eighth of one percent increments. The use of tables with this limited accuracy could lead to errors of several thousands of dollers in a fifty million dollar bond issue.

Another disadvantage of using tables is the requirement that the user must have a working knowledge of both the problem area and the mathematical formulas to set up the problem in a specific manner before the tables are applicable. Even then, it is often necessary to take a reciprocal or multiply by a constant before the answer is usable. This limits the user of the table to only those with a certain level of expertise in the problem area. Thus, one who performs a great variety of business calculations, from asset depreciation to sale forecasting must have: (1) an expensive collection of special purpose calculators; or (2) a library of tables close at hand; or (3) the mathematical and financial expertise to set up and solve the problem correctly.

In the complete specification of our copending United Kingdom patent

application No. 23162/76 (Serial No. 1,454,268) there is disclosed an electronic calculator comprising

keyboard input means for entering information into the calculator;

storage means, coupled to said keyboard input means, for storing information entered into the calculator;

processing means, coupled to said keyboard input means and said storage means, for processing information entered into the calculator and stored in said storage means to perform selected calculations; and

output means, coupled to said processing means, for displaying the results of selected calculations performed by said processing means;

said keyboard input means including a plurality of input keys manually operable for causing said processing means to perform a first plurality of operations designated by a first plurality of legends positioned on said keyboard input means and associated with said plurality of input keys;

said keyboard input means further including a command key manually operable with said plurality of input keys for causing said processing means to perform a second plurality of operations designated by a second plurality of legends positioned on said keyboard input means and associated with said plurality of input keys;

said command key and said second plurality of legends being coded to associate said command key with each of said second plurality of operations designated by said second plurality of legends.

In the complete specification of our copending United Kingdom patent application No. 23163/76 (Serial No. 1,454,267), there is disclosed an electronic calculator for calculating the yield to maturity of a bond having a bond price and a coupon rate, said calculator comprising:

a first register for initially storing a first number representing the coupon rate divided by the bond price multiplied by a first selected value;

a second register initially storing a second number representing the inverse of the bond price multiplied by a second selected value;

a third register storing a third number having a magnitude greater than one and representing the normalized value of uncompensated days for a selected period of time;

a fourth register initially storing the contents of the first register;

a fifth register storing the result of a calculation;

first means coupled to the first, second, third, and fourth registers to combine the contents thereof in accordance with the relation

$$F=R\frac{(1+R)^N-P}{(1+R)^N-1}-K,$$

where R is the contents of the fourth register (excluding the initial contents thereof), N is the contents of the third register, P is the contents of the second register, and K is the contents of the first register, said first means being coupled to the fifth register for storing the result of this combination therein;

second means coupled to the fourth and fifth registers to substract the contents of the fifth register from the contents of the fourth register and to store the difference in the fourth register; accruing means coupled to the first means and the first, second, third, and fourth registers to calculate an accrued interest portion of the bond price, to adjust the contents of the first and second registers to account for the accrued interest portion of the bond price, and thereafter to cause the first means to combine the contents of the third register and the last-stored contents of the first, second, and fourth registers in accordance with said relation and store the result of this combination in the fifth register;

third means responsive to the contents of the fifth register, when those contents are less than a third selected value, to initiate operation of the accruing means; and

output means coupled to the fourth register and the third means to provide a visual output indication of the calculated yield to maturity of the bond, said third means being operable after operation of the accruing means, for initiating operation of the output means to provide a visual indication of the calculated yield to maturity of the bond.

A principal object of this invention is to provide a general purpose business calculator that has vastly greater capability and flexibility than conventional

business calculators and that is small, inexpensive and easier to use than conventional business calculators.

The present invention provides an electronic calculator comprising; keyboard input means having a plurality of numeric keys manually operable for entering numerical data into the calculator and having a plurality of non-numeric control keys manually operable for controlling the calculator, said non-numeric control keys including a plurality of function keys associated with a plurality of functionally related financial variables and manually operable for designating selected numerical data as said financial variables and for conditioning the calculator to perform mathematical operations involving said variables; storage means coupled to said keyboard input means for storing numerical data entered into or calculated by the calculator; processing means coupled to said keyboard input means and to said storage means and responsive to successive actuation of one or more of said numeric keys and one or more of said non-numeric control keys in a sequence, including one of said function keys followed by one of said function keys without interruption by any of said numeric keys, for automatically performing a methametical operation employing selected numerical data, stored in said storage means and designated as one or more of said financial variables by actuation of one or more of said function keys, to determine the value of a financial variable associated with the last of said function keys in said sequence; and output means coupled to said processing means for indicating the value of the financial variable associated with the last of said function keys in said sequence.

In a calculator as set forth in the last preceding paragraph said plurality of function keys may comprise five financial function keys associated with five functionally related financial variables; and said processing means is preferably responsive to successive actuation of one or more of said numeric keys and one or more of said non-numeric control keys in a sequence, including one of said financial function keys followed by one of said financial function keys without interruption by any of said numeric keys, for automatically performing a mathematical operation employing selected numerical data, stored in said storage means and designated as one or more of said financial variables by actuation of one or more of said financial function keys, to determine the value of a financial variable associated with the last of said financial function keys in said sequence.

In a calculator as set forth in the last preceding paragraph said five financial function keys may include:

a first financial function key associated with a financial variable representing a number of periods;

a second financial function key associated with a financial variable representing an interest rate per period;

a third financial function key associated with a financial variable representing a periodic payment amount;

a fourth financial function key associated with a financial variable representing a present value of principal;

and a fifth financial function key associated with a financial variable representing a future value of principal after one or more periods have elapsed.

In a calculator as set forth in the last preceding paragraph or the last preceding paragraph but one said non-numeric control keys may include a command key for associating one of said five financial function keys with an alternative financial variable representing a yield to maturity of a bond, for associating another of said five financial function keys with an alternative financial variable representing an accrued interest amount, and for associating still another of said five financial function keys with an alternative financial variable representing a bond price; and each of three last-mentioned financial keys may be manually operable, when actuated successively following actuation of said command key, for designating selected numerical data as the corresponding one of said alternative financial variables and for conditioning the calculator to perform a mathematical operation involving that alternative financial variable.

In a calculator as set forth in the last preceding paragraph but one said first, second, third, fourth, and fifth financial function keys can be positioned on said keyboard input means in a lineal sequence and in the order mentioned. Preferably said three financial function keys associable with said alternative financial variables are positioned on said keyboard input means in a lineal sequence and in the order mentioned.

In a calculator as set forth in the last preceding paragraph but one each of said

five financial function keys may be provided with an indicium indicating the financial variable with which it is associated; and said keyboard input means may be further provided with indicia indicating the alternative financial variables with which said three financial function keys are associable. Preferably said command key and said indicia indicating the alternative financial variables are color coded.

In a calculator as set forth in the last preceding paragraph but five said processing means may include: first means responsive to actuation of a first one of said non-numeric control keys for generating the arithmetic average of numerical data stored in said storage means, for causing said output means to display said arithmetic average in decimal digit form, and for generating an end-of-operation signal; and second means coupled to said first means and responsive to said end-of-operation signal for generating the standard deviation of numerical data stored in said storage means, said processing means being responsive to actuation of a second one of said non-numeric keys for causing said output means to indicate said standard deviation in decimal digit form.

In a calculator as set forth in the last preceding paragraph said non-numeric control keys may include a command key manually operable with said first and second non-numeric control keys, when said second non-numeric control key, said commond key, and said first non-numeric control key are successively actuated in the order mentioned following generation of said arithmetic average and said end-of-operation signal, for causing said first and second means to generate the arithmetic average and the standard deviation for different numerical data entered into said storage means by said numeric keys.

In a calculator as set forth in the last preceding paragraph but seven a first one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing equally-spaced and chronologically-sequenced numerical data in said storage means; said processing means may be operable for generating the least-squares linear regression of the numerical data stored in said storage means; and said non-numeric control keys may include a command key manually operable with said first non-numeric control key, when said command key and said first non-numeric control key are successively actuated in the order mentioned, for causing said processing means to generate a first value of the least-squares linear regression of the numerical data stored in said storage means and for causing said output means to indicate said first value in decimal digit form.

In a calculator as set forth in the last preceding paragraph said first value may be the value at the y-intercept in rectangular coordinate notation; and said processing means may be responsive to further successive actuations of said first non-numeric control key for generating succeeding values of the least-squares linear regression of the numerica data stored in said storage means.

In a calculator as set forth in the last preceding paragraph but one a second one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing the sequence number of a chronological numerical datum in said storage means; and said processing means may be responsive to actuation of said first non-numeric control key, when successively preceded by actuation of said second non-numeric control key, for generating the value of the least-squares linear regression for the chronological numerical datum designated by the sequence number stored in said storage means by actuation of said second non-numeric control key.

In a calculator as set forth in the last preceding paragraph but ten said processing means may be responsive to actuation of one of said non-numeric control keys for determining the percentage difference between two numerical values stored in said storage means and for thereupon causing said output means to display that percentage difference in decimal digit form.

In a calculator as set forth in the last preceding paragraph but eleven said processing means may be operable for generating the percentage difference between two numerical values stored in said storage means; and said non-numeric control keys may include a command key manually operable with another of said non-numeric control keys, when said command key and said other non-numeric control key are successively actuated in the order mentioned, for causing said processing means to generate the percentage difference between two numerical values stored in said storage means and for thereupon causing said output means to display that percentage difference in decimal digit form.

In a calculator as set forth in the last preceding paragraph but twelve said numeric and non-numeric control keys may be manually operable for storing numerical data representing any two calendar dates in said storage means in a

predetermined decimal digit format; and said processing means may include first means responsive to actuation of one of said non-numeric control keys for determining the number of days between any two calendar dates and represented by numerical data stored in said storage means in said predetermined decimal digit format, and for causing said output means to display the determined number of days in said pre-determined decimal digit format.

In a calculator as set forth in the last preceding paragraph but thirteen said numeric and non-numeric control keys may be manually operable for storing numerical data representing an initial calendar data in said storage means in a predetermined decimal digit format and for storing numerical data representing a number of days from said initial calendar date; and said processing means may include first means responsive to actuation of one of said non-numeric control keys for generating the calendar date of the day corresponding to said number of days from said initial calendar date, when said initial and generated calendar dates are included within a predetermined range of calendar dates, and for causing said output means to display the generated calendar date in said predetermined decimal digit format.

In a calculator as set forth in the last preceding paragraph or the last preceding paragraph but one said processing means preferably includes: second means responsive to actuation of said one non-numeric control key for causing said output means to indicate when numerical data stored in said storage means represents an erroneous calendar date, represents a calendar data outside said predetermined range of calendar dates, or is incompatible with said predetermined decimal digit format, and third means for compensating for the extra day in leap-years occurring within said predetermined range of calendar dates.

In a calculator as set forth in the last preceding paragraph but one said non-numeric control keys may include a command key manually operable with said one non-numeric control key, when said command key and said one non-numeric control key are successively actuated in the order mentioned, for causing said first means to generate the calendar date of the day corresponding to said number of days from said initial calendar date and to cause said output means to display the generated calendar date in said predetermined decimal digit format.

In a calculator as set forth in the last preceding paragraph but two said first means may be responsive to actuation of said one non-numeric control key for generating the calendar date of the day corresponding to said number of days forward from said initial calendar date, when the numerical data representing said number of days from said initial calendar date is positive, and for generating the calendar date of the day corresponding to said number of days backward from said initial calendar date, when the numerical data representing said number of days from said initial calendar date is negative.

In a calculator as set forth in the last preceding paragraph but seventeen a first one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing a first numerical datum designating a particular period within the depreciable life of an asset in said storage means and is manually operable with one or more of said numeric keys for storing a second numerical datum representing the total number of such periods in the depreciable life of the asset in said storage means; a second one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing a third numerical datum representing an initial value of the asset in said storage means; said processing means may be operable for generating the value of the sum-of-the-digits depreciation and the depreciated value of the initial value of the asset represented by said third numerical datum for the period designated by said first numerical datum; and said non-numeric control keys may include a command key manually operable with a third one of said non-numeric control keys, when said command key and said third non-numeric control key are successively actuated in the order mentioned, for causing said processing means to generate said value of the sum-of-the-digits depreciation and said depreciated value and for causing said output means to display said generated value of the sum-of-the-digits depreciation in decimal digit form.

In a calculator as set forth in the last preceding paragraph said processing means may be responsive to further successive actuations of said third non-numeric control key for generating the value of the sum-of-the-digits depreciation of the initial value of the asset represented by said third numerical datum for each period included within the total number of periods represented by said second numerical datum subsequent to the period designated by said first numerical

datum and for causing said output means to display each generated value of the sum-of-the-digits depreciation in decimal digit form.

In a calculator as set forth in the last preceding paragraph but one a fourth one of said non-numeric control keys may be manually operable for thereafter causing said output means to display said generated depreciated value in decimal digit form.

In a calculator as set forth in the last preceding paragraph but twenty a first one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing a first numerical datum representing the number of successive payments; a second one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a second numerical datum representing the interest rate per payment; a third one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a third numerical datum representing the amount of each payment; and said processing means is responsive to actuation of a fourth one of said non-numeric control keys for generating the present value of the number of successive payments represented by said first numerical datum in the amount per payment represented by said third numerical datum and at the interest rate per payment represented by said second numerical datum and for causing said output means to display the generated present value in decimal digit form. Preferably each of said first, second, third, and fourth non-numeric control keys comprises a different one of said function keys.

In a calculator as set forth in the last preceding paragraph but twenty-one a first one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing a first numerical datum representing the number of days within an interest accruing period in said storage means; a second one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing a second numerical datum representing an annual interest rate in said storage means; a third one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing a third numerical datum representing a principal amount in said storage means; and said processing means may be responsive to actuation of a fourth one of said non-numeric control keys for generating the values of the amount of interest on a 360-day basis and on a 365-day basis of the principal amount represented by said third numerical datum for the number of days represented by said first numerical datum and at the annual interest rate represented by said second numerical datum and for causing said output means to display the value of the amount of interest generated on one of said bases in decimal digit form. Preferably said non-numeric control keys include a command key manually operable with said fourth non-numeric control key, when said command key and said fourth non-numeric control key are successively actuated in the order mentioned, for causing said processing means to generate said values of the amount of interest and to cause said output means to display the value of the amount of interest generated on said one of said bases in decimal digit form.

In a calculator as set forth in the last preceding paragraph said processing means is preferably responsive to actuation of a fifth one of said non-numeric control keys for causing said output means to display the value of the amount of interest generated on the other of said bases in decimal digit form.

In a calculator as set forth the last preceding paragraph but twenty-three a first one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing a first numerical datum representing the number of payments within an interest accruing period in said storage means; a second one of said non-numeric control keys may be manually operable with one or more of said numeric keys for storing a second numerical datum representing the annual add-on interest rate in said storage means; and said processing means may be responsive to reactuation of said second non-numeric control key, following storage of said second numerical datum in said storage means, for generating the value of an annual percentage interest rate and the value of a monthly payment factor for the number of payments represented by said first numerical datum at the annual add-on interest rate represented by said second numerical datum and for causing said output means to display the generated value of the annual percentage interest rate in decimal digit form.

In a calculator as set forth in the last preceding paragraph each of said first and second non-numeric control keys may comprise a different one of said function keys.

In a calculator as set forth in the last preceding paragraph said processing means is preferably responsive to actuation of a third one of said non-numeric control keys for causing said output means to display the generated value of the monthly payment factor in decimal digit form.

In a calculator as set forth in the last preceding paragraph said processing means is preferably further responsive to actuation of one or more of said numeric keys for storing a third numerical datum representing the principal amount in said storage means and is thereupon responsive to actuation of a fourth one of said non-numeric control keys for generating the value of the monthly payment and for causing said output means to display the generated value of the monthly payment in decimal digit form.

Each calculator according to the present invention is designed to incorporate into one small unit the capability of performing the majority of the calculations used in the many disciplines of business and performing these calculations with up to ten-digit accuracy. It replaces the special calculators designed for banking, or accounting, or finance, or real estate and other businesses and eliminates the need for all commonly used financial tables. It also allows the user to make inter-disciplinary analysis, for example, between real estate or bond investment programs, quickly and with one calculator. Furthermore, with a calculator according to the present invention, a sophisticated user can incorporate the mathematical formulae of several business disciplines to solve a complex problem involving several disciplines.

A business calculator according to the present invention is small and does not require a high level of user expertise or a working knowledge of the problem area and the necessary mathematical formulas before the problem can be set up and solved. Keys relating to a general class of problems are grouped together and designated in accordance with the generally accepted business symbols (e.g., "i" for interest per period, "PMT" for payment per period, etc.). The key layout and the keying sequence are such that they suggest to the non-expert user the information necessary to solve a given problem. For example, in solving the general class of compound interest and annuity problems with this calculator, the five possible variables, number of time periods, interest rate per period, payment per period, the present value and the future value are all located on the top row. A user can key in any of the three variables in the prescribed left to right sequence and the calculator will solve either of the remaining unknowns as requested. This procedure does not require any previous knowledge of compound interest or annuity mathematics, and any of the five variables can be solved without any intermediate steps. Hence, all that is required of the user is that he be able to define the variables of the problem, and the unique keying sequence of the invention will carry out the necessary mathematical manipulation.

A calculator constructed according to the preferred embodiment of this invention is small enough to hold in one hand, is capable of displaying data as it is entered and a numerical result as it is calculated, and incorporates many complex functions in order to perform the number and kind of calculations and mathematical operations required for different business disciplines. The limits of miniaturization and sophistication are realized, however, if the keyboard of such a calculator becomes so small and so crowded with keys that the human hand can no longer physically or conveniently manipulate them. One solution to this problem is to reduce the number of functions the calculator can perform. A better solution is to assign more than one function to each key, thus reducing the number of keys necessary to incorporate all the functional capabilities of the calculator.

As more functions are assigned to each key, however, the clarity of labelling a key's various functions becomes important. Moreover, not only must the labelling clearly refer to the particular key, but the functions each key causes the machine to perform should be easily understood and learned by the user from scanning the keyboard labels. After learning the total capability of the particular machine from a reading of the manual, the user should be able to know the relationship between keys, the function(s) each key initiates and, therefore, the operation of the machine, from his knowledge of the keyboard itself.

The limitations of miniature calculators have been overcome by the preferred embodiment of the present invention by incorporating easily interpreted, coded legends to the keyboard surface immediately above certain keys to which more than one function is assigned. The coding not only designates the separate function of each of these keys, but also refers to the prefix key which activates the second function of the key when it is depressed.

Some conventional business calculators have a day between date function, but do not check for improper date entries (e.g., 32nd of June) or compensate for the extra day in a leap year, whereas a calculator according to present invention automatically checks for improper date entries and compensates for the extra days in leap years in all number-of-days calculations between 1900 A.D. and 2100 A.D. Furthermore, the present invention has the unique capability of determining a future or past date with compensation for leap years given the number of days away.

Conventional business calculators have very complicated procedures for establishing a trend line from a set of periodic data points. In the existing prior art, the user enters the data points and is given the value of the y intercept and the slope of the straight line that best fits the data points (hereinafter referred to as the best fit line). In order to forecast future values, the user had to multiply the slope by the future time period and add the result to the value of the y intercept to get the desired future value. A calculator according to the present invention is, in contrast, capable of determining a best fit line from a set of data points and, without any intermediate steps or interpolation, of providing ordinal values on the best fit line at any point on the time axis. This calculator can also extrapolate either single or multiple time periods into the past or the future. Hence, the user can either request the ordinal value at any time period up to ten digits long (e.g., −2.5, 0, 7.53452) or utilize the feature which automatically calculates the ordinal value for single time period increments.

Conventional business calculators for bond price and bond yield calculations have a manual switch to initiate different bond price and bond yield algorithms for bonds maturing in less than 181 days (these are considered as notes rather than bonds), whereas a calculator according to the present invention has an automatic feature to check the maturity period and initiate the proper algorithm. The algorithms traditionally used in conventional business calculators to solve bond price and bond yield are very complex and require extensive hardware capability. This has made these calculators large, complicated, and expensive. However, in a present calculator according to the present invention, two new algorithms requiring significantly less hardware for bond price and bond yield calculations are used to allow the incorporation of these two bond calculations in a small, general purpose calculator at a fraction of the special bond calculator price.

Conventional business calculators designed to calculate accumulated mortgage interest and remaining principal on a mortgage can give the cumulative totals up to a given time period. However, it is often necessary to determine the accumulated mortgage interest and the cumulative principal paid during a specific fime period. This is not possible with prior art calculators without making two separate calculations and then taking the difference. In contrast a calculator according to the present invention permits the user to find the amount of mortgage interest paid during any specified time period, as well as the remaining principal in one step. Thus, this calculator can for example automatically calculate either the interest paid during the past year or the interest paid during the sixth through the tenth years.

Conventional business calculators with discount cash flow capability discount the entire stream of expected cash flow and solve for the rate of return of the investment. This provides for a summary analysis of the cash producing life span of an asset, but does not provide any interim information on the repayment of the original investment. A calculator according to the present invention has, on the other hand, a discount cash flow capability that discounts each cash flow and maintains a running total of the outstanding amount of the original investment. Hence, when the outstanding balance becomes zero, or greater, the user will know the number of periods before the investment is recouped.

In the past discounted note calculations were made by employing discount note tables where the discounted interest rate is given at .05% increments, the discounted amount is given to six decimal places, and the equivalent annual interest rate is given only to four decimal places. Thus, one who wished to find the discounted amount or to convert the discounted interest rate to an equivalent annual interest rate is faced with two limitations: (1) the discrete interest value and, hence, the need for interpolation to obtain the discounted interest rate; and (2) the four decimal place accuracy of the equivalent annual interest rates. Both of these aforementioned limitations can have a sizable effect on large sum calculations.

In some money markets outside the United States, a 365 day year is used for

interest bearing transactions. This makes it necessary for an international investor to make extra calculations to convert a given interest rate from a 360 day basis to a 365 day basis or vice versa. Thus, it would be very helpful for an international investor to have the capability of finding the equivalent interest for either interest bearing period.

A calculator according to the present invention can replace the discount note tables and perform the calculations related to discounted notes without being limited to discrete discounted interest rates and is accurate to ten digits. It automatically calculates the discounted amount and the equivalent annual interest rate to ten digit accuracy for both the 360 day year and the 365 day year which enables prompt evaluation of interest bearing instruments in different money markets.

Conventional business calculators with arithmetic mean and standard deviation capability are very restricted in their performance. In most cases, to find the standard deviation, the user must first find the variance from the sum of the squares of the input data and then take the square root of the variance to find the standard deviation. Also, once the data is entered and the arithmetic mean calculation is made, it is not possible to add or remove a data point to evaluate the effect on the arithmetic mean and the standard deviation without entering all the data points and performing the calculations over again.

A calculator according to the present invention can compute both the arithmetic mean and the standard deviation automatically from the input data. Furthermore, once the arithmetic mean and the standard deviation are calculated, a calculator according to the present invention permits the user to add or remove input data values from the original set of data and calculate a new arithmetic mean and standard deviation without re-entering all the input values. Hence, this calculator is highly interactive and permits the user to measure the influence of hypothetical inputs on the existing data.

A calculator according to the present invention also has the capability for determining a depreciation schedule based on the sum-of-the-digit depreciation method. Given the life of an asset and the depreciable amount, this calculator computes the depreciation for any requested period and the remaining book value to be depreciated. Furthermore, the user can find the same information for all subsequent periods to set up a depreciation schedule.

In order to implement the extended capability and flexibility provided by this calculator, new algorithms were developed requiring less hardware to solve complex problems. A new algorithm using internal transformations was developed to solve for the interest in the present value of an annuity and in the future value of an annuity. This same algorithm also solves for the effective annual percentage rate from the so-called "add-on" rate. Thus, this one algorithm has made it possible for a user to solve any of these three inherently different interest problems without having to identify the problem. A calculator according to the present invention can automatically identify the type of interest problem from the prescribed left to right keying sequence of the relevant data, and the input data is then converted to a form acceptable to the new algorithm.

Another new algorithm was also developed to reduce the complexity of the bond price and bond yield problem (and the solution thereof) so as to make this problem solvable using only five registers. This new algorithm uses an explicit term that eliminates the need for a series of summations, which would otherwise require substantially more hardware.

The algorithms for performing the functions of this calculator are stored in a read-only memory circuit including seven serial-address in, serial-instruction out read-only memories regulated by a control and timing circuit. This control and timing circuit includes a microprogrammed controller, which receives status conditions from throughout the calculator and sequentially outputs signals to control the flow of data. The control and timing circuit also scans the keyboard to obtain a six-bit read-only memory address, which is generated at the keyboard each time a key is actuated as required to initiate one or more algorithms for performing the functions associated with the actuated key.

Information from the addressed read-only memory is transmitted serially to an arithmetic and register circuit where a serial, binary-coded decimal (BCD) adder/subtractor performs the basic computations. The results of the computations are transmitted to registers in this circuit where they are either stored temporarily or outputted via a seven-segment, 15-digit, LED display.

There now follows a detailed description which is to be read with reference to

the accompanying drawings of a business calculator according to the present invention; it is to be clearly understood that this calculator has been selected for description to illustrate the invention by way of example and not by way of limitation.

In the drawings:—

Fig. 1 is a top view of a business calculator according to the preferred embodiment of the invention;

Fig. 2 is a block diagram of the calculator of Fig. 1;

Fig. 3 is a waveform diagram illustrating the timing sequence of the interconnecting busses and lines of Fig. 2;

Fig. 4 is a block diagram of the control and timing circuit of Fig. 2;

Fig. 5 is a more detailed block diagram of the keyboard scanning circuitry of Fig. 4;

Fig. 6 is a block diagram of one of ROM's Ø—6 of Fig. 2;

Fig. 7 is a waveform diagram illustrating a typical address signal and a typical instruction signal;

Fig. 8 is a timing diagram illustrating the important timing points for a typical addressing sequence;

Fig. 9 is a waveform diagram illustrating the word select signals generated in the control and timing circuit of Figs. 2 and 4 and in the ROM's Ø—6 of Figs. 2 and 6;

Fig. 10 is a block diagram of the arithmetic and register circuit of Fig. 2;

Fig. 11 is a path diagram of the actual data paths for the registers A—F and M of Fig. 10;

Fig. 12 is a waveform diagram illustrating the output signals for the display decoder outputs A—E of Figs. 2, 10, and 11;

Fig. 13 is a waveform diagram illustrating the actual signals on the display decoder outputs A—E of Figs. 2, 10, and 11 when the digit 9 is decoded;

Fig. 14 is a waveform diagram illustrating the timing of the START signal generated by the display decoder of Fig. 10;

Fig. 15 is a schematic diagram of the clock driver of Fig. 2;

Fig. 16 is a waveform diagram illustrating the timing relationship between the input and output signals of the clock driver of Fig. 15;

Fig. 17 is a logic diagram of the anode driver of Fig. 2;

Fig. 18 is a waveform diagram illustrating the timing relationship between the input, output, and other signals of the anode driver of Fig. 17;

Fig. 19 is a schematic diagram of the basic inductive drive circuit for one of the LED's employed in the LED display of Fig. 2;

Fig. 20 is a waveform diagram illustrating the timing relationship between the decimal point drive signals for the LED display of Fig. 2;

Fig. 21 is a schematic diagram of the inductive drive circuit for one digit in the LED display of Fig. 2;

Fig. 22 is a logic diagram of the cathode driver of Fig. 2;

Fig. 23 is a top view of a metal strip employed in the keyboard input unit of Figs. 1 and 2;

Fig. 24 is a side view of the metal strip of Fig. 23;

Fig. 25 is a force-deflection curve for a typical key in the keyboard input unit of Figs. 1 and 2;

Fig. 26 is a schematic diagram of the LED display of Figs. 1 and 2 and the inductive drive circuits therefor;

Fig. 27 is a schematic diagram of one segment of the LED display of Fig. 26;

Fig. 28 is an equivalent piecewise-linear model for the circuitry of Fig. 27;

Fig. 29 is a waveform diagram illustrating the inductor current and LED anode voltages in the circuitry of Fig. 27;

Fig. 30 is a path diagram illustrating the possible transfer paths between the ROM's Ø—6 of Fig. 2;

Fig. 31 is a flow diagram of the display wait loop employed in the calculator of Figs. 1 and 2;

Fig. 32 is a flow diagram of an interest algorithm employed in the calculator of Figs. 1 and 2;

Fig. 33 is a flow diagram of a price of a bond algorithm employed in the calculator of Figs. 1 and 2;

Fig. 34 is a flow diagram of a yield to maturity of a bond algorithm employed in the calculator of Figs. 1 and 2; and

Figs. 35A and B comprise a flow diagram of a date algorithm employed in the calculator of Figs. 1 and 2.

SYSTEM ARCHITECTURE

Referring to Figures 1 and 2, there is shown a pocket-size electronic calculator 10 including a keyboard input unit 12 for entering data and instructions into the calculator and a seven-segment LED output display unit 14 for displaying each data entry and the results of calculations performed by the calculator. As shown in Figure 2, the calculator 10 also includes a metal-oxide-semiconductor (MOS) control and timing circuit 16, an MOS read-only memory circuit 18 (including read-only-memories (ROM's) Ø—6), an MOS arithmetic and register circuit 20, a bipolar clock driver 22, and a solid state power supply unit 24.

The three MOS circuits are two-phase dynamic MOS/large scale integration (LSI) circuits with low thresholds allowing compatibility with transistor-transistor logic (TTL) bipolar circuits and allowing extremely low-power operation (less than one hundred milliwatts for all three circuits). They are organized to process fourteen-digit binary-coded decimal (BCD) words in a digit-serial, bit-serial manner. The maximum bit rate or clock frequency is two-hundred kilohertz, which gives a word time of two hundred and eighty microseconds (permitting a floating point addition to be completed in sixty milliseconds).

The control and timing circuit 16, the read-only memory circuit 18, and the arithmetic and register circuit 20 are tied together by a synchronization (SYNC) buss 26, an instruction (I_s) buss 28, a word select (WS) buss 30, an instruction address (I_a) line 32, and a carry line 34. All operations occur on a fifty-six bit (b_0—b_{55}) word cycle (fourteen four-bit BCD digits). The timing sequence for the interconnecting busses and lines 26—34 is shown in Figure 3.

The SYNC buss 26 carries synchronization signals from the control and timing circuit 16 to the ROM's Ø—6 in the read-only memory circuit 18 and to the arithmetic and register circuit 20 to synchronize the calculator system. It provides one output each word time. This output also functions as a ten-bit wide window (b_{45}—b_{54}) during which the I_s buss 28 is active.

The I_s buss 28 carries ten-bit instructions from the active ROM in the read-only memory circuit 18 to the other ROM's, the control and timing circuit 16, and the arithmetic and register circuit 20, each of which decodes the instructions locally and responds to or acts upon them if they pertain thereto and ignores them if they do not. For instance, the ADD instruction affects the arithmetic and register circuit 20 but is ignored by the control and timing circuit 16. Similarly, the SET STATUS BIT 5 instruction sets a status flip-flop 5 in the control and timing circuit 16 but is ignored by the arithmetic and register circuit 20.

The actual implementation of an instruction is delayed one word time from its receipt. For example, an instruction may require the addition of the digit 2 in two of the registers in the arithmetic and register circuit 20. The ADD instruction would be received by the arithmetic and register circuit 20 during bit times b_{45}—b_{54} of a word time N and the addition would actually occur during bit times b_8—b_{11} of a word time N + 1. Thus, while one instruction is being executed the next instruction is being fetched.

The WS buss 30 carries an enable signal from the control and timing circuit 16 or one of the ROM's in the read-only memory circuit 18 to the arithmetic and register circuit 20 to enable the instruction being executed thereby. Thus, in the example of the previous paragraph, addition occurs only during the digit 2 since the adder in the arithmetic and register circuit 20 is enabled by the WS buss 30 only during this portion of the word. When the WS buss 30 is low, the contents of the registers in the arithmetic and register circuit 20 are recirculated unchanged. Three examples of WS timing signals are shown in Figure 3. In the first example, the digit 2 is selected out of the entire word. In the second example, the last eleven digits are selected. This corresponds to the mantissa portion of a floating point word format. In the third example, the entire word is selected. Use of the word select feature allows selective addition, transfer, shifting or comparison of portions of the registers within the arithmetic and register circuit 20 with only one basic ADD, TRANSFER, SHIFT, or COMPARE instruction. Some customization in the ROM word select fields is available via masking options.

The I_a line 32 serially carries the addresses of the instructions to be read from the ROM's Ø—6. These addresses originate from the control and timing circuit 16, which contains an instruction address register that is incremented each word time unless a JUMP SUBROUTINE or a BRANCH instruction is being executed. Each

address is transferred to the ROM's Ø—6 during bit times b_{19}—b_{26} and is stored in an address register of each ROM. However, only one ROM is active at a time, and only the active ROM responds to an address by outputting an instruction on the I_0 line 28. Control is transferred between the ROM's by a ROM SELECT instruction. This technique allows a single eight-bit address, plus eight special instructions, to address up to eight ROM's of two hundred and fifty-six words each.

The carry line 34 transmits the status of the carry output of the adder in the arithmetic and register circuit 20 to the control and timing circuit 16. The control and timing circuit 16 uses this information to make conditional branches, dependent upon the numerical value of the contents of the registers in the arithmetic and register circuit 20.

The control and timing circuit 16 is organized to scan a five-by-eight matrix of switches in search of an interconnection that designates actuation of a key. Any type of metal-to-metal contact may be used as a key. Bounce problems are overcome by programmed lockouts in the key entry routine. Each key has an associated six-bit code.

A power-on circuit 36 in the power supply unit 24 supplies a signal forcing the calculator to start up in a known condition when power is supplied thereto. Power is supplied to the calculator when the on-off switch of the keyboard input unit 12 (see Fig. 1) is moved to the 'on' position.

The primary outputs of the calculator are five output lines 38 connected between a display decoder of the arithmetic and register circuit 20 and an anode driver of the output display unit 14. Data for a seven-segment display plus a decimal point is time-multiplexed onto these five output lines. A start line 40 connected between the display decoder of the arithmetic and register circuit 20 and a cathode driver of the output display unit 14 indicates when the digit 0 occurs.

CONTROL AND TIMING CIRCUIT

Referring now to Fig. 4, the control and timing circuit 16 contains a master system counter 42, scans the keyboard input circuit 12, retains status information about the system or the condition of an algorithm, and generates the next ROM address. It also originates the subclass of Word Select signals which involve a pointer 44, a four-bit counter that points to one of the register digit positions.

The control unit of the control and timing circuit 16 is a microprogrammed controller 46 comprising a fifty-eight word (twenty-five bits per word) control ROM, which receives qualifier or status conditions from throughout the calculator and sequentially outputs signals to control the flow of data. Each bit in this control ROM either corresponds to a single control line or is part of a group of N bits encoded into 2^N mutually exclusive control lines and decoded externally to the control ROM. At each phase 2 clock, a word is read from the control ROM as determined by its present address. Part of the output is fed back to become the next address.

Several types of qualifiers are checked. Since most commands are issued only at certain bit times during the word cycle, timing qualifiers are necessary. This means the control ROM may sit in a wait loop until the appropriate timing qualifier comes true, then move to the next address to issue a command. Other qualifiers are the state of the pointer register, the PWO (power-on) line, the CARRY flip-flop, and the state of each of the 12 status bits.

Since the calculator is a serial system based on a fifty-six bit word, the, six-bit, system counter 42 is employed for counting to fifty-six. Several decoders from the system counter 42 are necessary. The SYNC signal is generated during bit times b_{45}—b_{54} and transmitted to all circuits in the system (see Fig. 3). Other timing qualifiers are sent to the micro-programmed controller 46 as mentioned in the previous paragraph.

The system counter 42 is also employed as a keyboard scanner as shown in Fig. 5. The most significant three bits of the system counter 42 go to a one-of-eight decoder 48, which sequentially selects one of a plurality of keyboard row lines 50. The least significant three bits of the system counter count modulo seven and go to a one-of-eight multiplexer 52, which sequentially selects one of a plurality of keyboard column lines 54 (during sixteen clock times no key is scanned). The multiplexer output is called the key down signal. If a contact is made at any intersection point in the five-by-eight matrix (by depressing a key), the key down signal will become high for one state of the system counter 42 (i.e., when the appropriate row and column lines are selected). The key down signal will cause

that state of the system counter to be saved in a key code buffer 56. This six-bit code is then transferred to a ROM address register 58 and becomes a starting address for the program which services the key that was down (two leading 0 bits are added by hardware so an eight-bit address exists). Thus, during each state of the system counter 42, the decoder-multiplexer combination 48 and 52 is looking to see if a specific key is down. If it is, the state of the system counter becomes a starting address for execution of that key function (note that sixteen of the fifty-six states are not used for key codes). By sharing the function of the system counter and using a keyboard scanning technique directly interfaced to the MOS circuitry, circuit complexity is reduced significantly.

A twenty-eight bit shift register which circulates twice each fifty-six bit word time, is employed in the control and timing circuit 16. These twenty-eight bits are divided into three functional groups: a main ROM address register 58 (eight bits), a subroutine return address register 60 (eight bits), and a status register 62 (twelve bits).

The main ROM's Ø—6 each contain two hundred and fifty-six (ten bit) words, thereby requiring an eight-bit address. This address circulates through a serial adder/subtractor 64 and is incremented during bit times b_{47}—b_{54} (except in the case of branch and jump-subroutine instructions for which the eight bit address field of the ten-bit instruction is substituted for the current address). The next address is transmitted over the I_a line 32 to each of the main ROM's Ø—6 during bit times b_{19}—b_{26}.

The status register 62 contains twelve bits or flags which are used to keep track of the state of the calculator. Such information as whether the decimal point has been hit, the minus sign set, etc. must be retained in the status bits. In each case the calculator remembers past events by setting an appropriate status bit and asking later if it is set. A 'yes' answer to a status interrogation will set a carry flip-flop 66 as indicated by the control signal IST in Fig. 4. Any status bit can be set, reset, or interrogated while circulating through the adder 64 in response to the appropriate instruction.

The instruction set allows one level of subroutine call. The return address is stored in the eight-bit return address register 60. Execution of a JUMP subroutine stores the incremented present address into the return address register 60. Execution of the RETURN instruction retrieves this address for transmission over the I_a line 32. Gating is employed to interrupt the twenty-eight bits circulating in the shift register 58—62 for insertion of addresses at the proper time as indicated by the JSB control signal in Fig. 4.

An important preferred feature of the calculator system is the capability to select and operate upon a single digit or a group of digits (such as the exponent field) from the fourteen digit registers. This feature is implemented through the use of the, four-bit, pointer 44 which points at the digit of interest. Instructions are available to set, increment, decrement, and interrogate the pointer 44. The pointer is incremented or decremented by the same serial adder/subtracter 64 used for addresses. A 'yes' answer to the instruction "is pointer≠N" will set the carry flip-flop 66 via a control signal IPT in Fig. 4.

The word select feature was discussed above in connection with Figs. 2 and 3. Some of the word select signals are generated in the control and timing circuit 16, namely those dependent on the pointer 44, and the remainder in the main ROM's Ø—6. The pointer word select options are (1) pointer position only and (2) pointer position and all less significant digits. For instance, assume the mantissa signs of the numbers in the A and C registers of the arithmetic and register circuit 20 were to be exchanged. The pointer would be set to position 13 (last position) and the A EXCHANGE C instruction with a "pointer position" word select field would be given. If all of the word except the mantissa signs were to be exchanged, the A EXCHANGE C instruction would be given with the pointer set at 12 and the word select field set to pointer and less significant digits. The control and timing circuit word-select output is or-tied on the WS buss 30 with the ROM word-select output and transmitted to the arithmetic and register circuit 20.

Any carry signal out of the adder in the arithmetic and register circuit 20, with word select also high, will set the carry flip-flop 66. This flip-flop is interrogated during the BRANCH instruction to determine if the existing address should be incremented (yes carry) or replaced by the branch address (no carry). The branch address is retained in an eight-bit address buffer 68 and gated to the I_a line 32 by the BRH control signal.

The power-on signal is used to synchronize and preset the starting conditions

of the calculator. It has two functions, one of which is to get the address of the control ROM 46 set to a proper starting state and the other of which is to get the system counter 42 in the control and timing circuit 16 synchronized with the counter in each main ROM Ø—6. As the system power comes on, the PWO signal is held at logic 1 (0 volts in this system) for at least twenty milliseconds. This allows the system counter 42 to make at least one pass through bit times b_{45}—b_{54} when SYNC is high thereby setting main ROM Ø active and the rest of the ROM's inactive. When the PWO signal goes to logic 0 (+6 volts), the address of control ROM 46 is set to 000000 where proper operation can begin.

READ-ONLY MEMORY CIRCUIT

The ROM's Ø—6 in the read-only memory circuit 18 store the programs for executing the functions required of the system. Since each ROM contains 256 ten-bit words, there are 1,536 words or 15,360 bits of ROM. A block diagram of each of the ROM's Ø—6 is shown in Fig. 6.

The basic operation of each ROM is a serial-address in, a serial-instruction out. During every fifty-six bit word time the address comes in, least significant bit first from bit b_{19} through bit b_{26}. Every ROM Ø—6 in the system receives this same eight-bit address and from bit time b_{45} through b_{54} tries to output onto the I_8 line 28. However, a ROM enable (ROE) flip-flop 70 in each ROM insures that no more than one ROM actually sends an instruction on the I_8 line 28 at the same time.

All output signals are inverted so that the steady-state power dissipation is reduced. The calculator circuits are P-channel MOS. Thus, the active signals that turn on a gate are the more negative. This is referred to as negative logic, since the more negative logic level is the logic 1. As mentioned above, logic 0 is +6 volts and logic 1 is 0 volts. The signals on I_8 and I_9 are normally at logic 0. However, when the output buffer circuits are left at logic 0 they consume more power. A decision was therefore made to invert the signals on the I_8 and I_9 outputs and re-invert the signals at all inputs. Thus, signals appear at the I_8 and I_9 outputs as positive logic. The oscilloscope pattern that would be seen for instruction 1101 110 011 from state 11 010 101 is shown in Fig. 8.

The serial nature of the calculator circuits requires careful synchronization. This synchronization is provided by the SYNC pulse, generated in the control and timing circuit 16 and lasting for bit times b_{45}—b_{54}. Each ROM has its own fifty-six state counter 72, synchronized to the system counter 42 in the control and timing circuit 16. Decoded signals from this state counter 72 open the input to an address register 74 at bit time b_{19}, clock I_8 out at bit time b_{45} and provide other timing control signals.

As the system power comes on, the PWO signal is held at 0 volts (logic 1) for at least twenty milliseconds. The PWO signal is wired (via a masking option) to set the ROM Output Enable (ROE) flip-flop 70 on main ROM 0 and reset it on all other ROM's. Thus when operation begins, ROM 0 will be the only active ROM. In addition, the control and timing circuit 16 inhibits the address output during start-up so that the first ROM address will be zero. The first instruction must be a JUMP SUBROUTINE to get the address register 58 in the control and timing circuit 16 loaded properly.

Fig. 7 shows the important timing points for a typical addressing sequence. During bit times b_{19}—b_{26} the address is received serially from the control and timing circuit 16 and loaded into the address register 74 via the I_8 line 32. This address is decoded and at bit time b_{44} the selected instruction is gated in parallel into an I_8 register 76. During bit times b_{45}—b_{54} the instruction is read serially onto the I_8 buss 28 from the active ROM (i.e., the ROM with the ROM enable flip-flop set).

Control is transferred between ROM's by a ROM SELECT instruction. Effectively this instruction will turn off the ROE flip-flop 70 on the active ROM and turn on the ROE flip-flop 70 on the selected ROM. Implementation is dependent upon the ROE flip-flop being a master-slave flip-flop. In the active ROM, the ROM SELECT instruction is decoded by a ROM select decoder 78 at bit time b_{44}, and the master portion of the ROE flip-flop 70 is set. The slave portion of the ROE flip-flop 70 is not set until the end of the bit time (b_{55}). In the inactive ROM's the instruction is read serially into the I_8 register 76 during bit times b_{45}—b_{54} and then decoded, and the ROE flip-flop 70 is set at bit time b_{55} in the selected ROM. A masking option on the decoding from the least significant three bits of the I_8 register 76 allows each ROM to respond only to its own code.

The six secondary word-select signals are generated in the main ROM's Ø—6.

Only the two word-select signals dependent upon the POINTER come from the control and timing circuit 16. The word select of the instruction is retained in a word select register 80 (also a master-slave). If the first two bits are 01, the instruction is of the arithmetic type for which the ROM must generate a word select gating signal. At bit time b_{55} the next three bits are gated to the slave and retained for the next word time to be decoded into one of six signals. The synchronization counter 72 provides timing information to a word select decoder 82. The output WS signal is gated by the ROE flip-flop 70 so that only the active ROM can output on the WS line 30, which is OR-tied with all the other ROM's and also with the control and timing circuit 16. As discussed above, the WS signal goes to the arithmetic and register circuit 20 to control the portion of a word time an instruction is active.

The six ROM generated word select signals used in the calculator are shown in Fig. 9. The ROM's Ø—6 output a one bit-time pulse on the I_8 buss 28 at bit time b_{11} to denote the exponent minus sign time. This pulse is used in the display decoder of the arithmetic and register circuit 20 to convert a 9 into a displayed minus sign. The time location of this pulse is a mask option on the ROM.

ARITHMETIC AND REGISTER CIRCUIT

The arithmetic and register circuit 20 shown in Fig. 10 provides the arithmetic and data storage function for the calculator. It is controlled by the WS, I_8, and SYNC lines 30, 28, and 26, respectively; receives instructions from the ROM's Ø—6 over the I_8 line 28; sends information back to the control and timing circuit 16 via the CARRY line 34; partially decodes the display information before transmitting it via the output lines 38 to the anode driver of the output display unit 14; and provides a START pulse to the cathode driver of the output display unit 14 to synchronize the display.

The arithmetic and register circuit 16 contains seven, fourteen-digit (fifty-six bit) dynamic registers A—F and M and a serial BCD adder/subtractor 84. Actual data paths, not shown in Fig. 10 due to their complexity, are discussed below and shown in Fig. 11. The power and flexibility of an instruction set is determined to a great extent by the variety of data paths available. One of the advantages of a serial structure is that additional data paths are not very costly (only one additional gate per path). The structure of the arithmetic and register circuit 20 is optimized from the type of algorithms required by the calculator.

The seven registers A—F and M can be divided into three groups: the working registers A, B, and C with C also being the bottom register of a four-register stack; the next three registers D, E, and F in the stack; and a separate storage register M communicating with the other registers through the register C only. In Fig. 11, which shows the data paths connecting all the registers A—F and M, each circle represents the fifty-six bit register designated by the letter in the circle. In the idle state (when no instruction is being executed in the arithmetic and register circuit 20) each register continually circulates since with dynamic MOS registers information is represented by a charge on a parasitic capacitance and must be continually refreshed or lost. This is represented by the loop re-entering each register.

The registers A, B, and C can all be interchanged. Either the register A or C is connected to one adder input, and either the register B or C to the other. The adder output can be directed to either the register A or C. Certain instructions can generate a carry via the carry flip-flop 85 which is transmitted to the control and timing circuit 16 to determine conditional branching. The register C always holds a normalized version of the displayed data.

In the stack formed by the registers C, D, E and F a ROLL DOWN instruction is executed by the following transfers: F→E→D→C→F. A STACK UP instruction is executed by the following transfers: GC→D→E→F. Thus, it is possible to transfer a register and also let it recirculate so that in the last example the contents of C are not lost. The structure and operation of a stack such as this are further described in U.S. Patent Specification No. 3781820.

In the serial decimal adder/subtractor 84, a correction (addition of 6) to a BCD sum must be made if the sum exceeds nine (a similar correction for subtraction is necessary). It is not known if a correction is needed until the first three bits of the sum have been generated. This is accomplished by adding a four-bit holding register 86 (A_{60}—A_{57}) and inserting the corrected sum into a portion 88 (A_{56}—A_{53}) of the register A if a carry is generated. This holding register 86 is also required for the SHIFT A LEFT instruction. One of the characteristics of a

decimal adder is that non-BCD codes (i.e. 1101) are not allowed. They will be modified if circulated through the adder. The adder logic is minimized to save circuit area. If four bit codes other than 0000—1001 are processed, they will be modified. This is no constraint for applications involving only numeric data (however, if ASC11 codes, for instance, are operated upon, incorrect results will be obtained).

The arithmetic and register circuit 20 receives the instruction during bit times b_{45}—b_{54}. Of the ten types of instructions hereinafter described, the arithmetic and register circuit 20 must respond to only two types (namely, ARITHMETIC & REGISTER instructions and DATA ENTRY/DISPLAY instructions). ARITHMETIC & REGISTER instructions are coded by a 10 in the least significant two bits of an I_s register 90. When this combination is detected, the most significant five bits are saved in the I_s register 90 and decoded by an instruction decoder 92 into one of thirty-two instructions.

The ARITHMETIC & REGISTER instructions are active or operative only when the Word Select signal (WS) generated in one of the ROM's Ø—6 or in the control and timing circuit 16 is at logic one. For instance, suppose the instruction "A+C→C, mantissa with sign only" is called. The arithmetic and register circuit 20 decodes only A+C→C. It sets up the registers A and C at the inputs to the adder 84 and, when WS is high, directs the adder output to the register C. Actual addition takes place only during bit times b_{12} to b_{55} (digits 3—13) since for the first three digit times the exponent and exponent sign are circulating and are directed unchanged back to their original registers. Thus, the word select signal is an "instruction enable" in the arithmetic and register circuit 20 (when it is at logic 1, instruction execution takes place, and when it is at logic 0, recirculation of all registers continues).

The DATA ENTRY/DISPLAY instructions, except for digit entry, affect an entire register (the word select signal generated in the active ROM is at logic 1 for the entire word cycle). Some of these instructions are: up stack, down stack, memory exchange M←→C, and display on or toggle. A detailed description of their execution is given hereinafter.

For increased power savings a display decoder 94 is partitioned to partially decode the BCD data into seven segments and a decimal point in the arithmetic and register circuit 20 by using only five output lines (A—E) 38 with time as the other parameter. Information for seven segments (*a*—*g*) and a decimal point (dp) are time shared on the five output lines A—E. The output wave forms for the output lines A—E are shown in Figure 12. For example, the output line D carries the segment *e* information during T_1 (the first bit time of each digit time) and the segment D information during T_2 (the second bit time of each digit time); and the output E carries the segment G information during T_1, the segment F information during T_2, and the decimal point (dp) during T_4. The actual signals which would appear if a digit 9 were decoded are shown in Fig. 13. The decoding is completed in the anode driver of the output display unit 14 as explained hereinafter.

The registers in the arithmetic and register circuit 20 hold fourteen digits comprising ten mantissa digits, the mantissa sign, two exponent digits, and the exponent sign. Although the decimal point is not allocated a register position, it is given a full digit position in the output display. This apparent inconsistency is achieved by using both the A and B registers to hold display information. The A register is set up to hold the displayed number with the digits in the proper order. The B register is used as a masking register with digits 9 inserted for each display position that is to be blanked and a digit 2 at the decimal point location. When the anode driver of the output display unit 14 detects a decimal point code during T_4, it provides a signal to the cathode driver of the output display unit to move to the next digit position. One digit and the decimal point share one of the fourteen digit times. The digit 9 mask in the register B allows both trailing and leading zeros to be blanked (i.e., by programming 9's into the B register). Use of all three working registers for display (i.e., the C register to retain the number in normalized form, the A register to hold the number in the displayed form, and the B register as a mask) allows the calculator to have both a floating point and a scientific display format at the expense of only a few more ROM states.

The display blanking is handled as follows. At time T_4 the BCD digit is gated from the register A into a display buffer 96. If this digit is to be blanked, the register B will contain a nine (1001) so that at T_4 the end bit (B_{01}) of the B register will be a one (an eight would therefore also work). The input to the display buffer 96 or OR—ED with B_{01} and will be set to 1111 if the digit is to be blanked. The

decimal point is handled in a similar way. A two (0010) is placed in the register B at the decimal point location. At time T_2 the decimal point buffer flip-flop is set by B_{01}. Any digit with a one in the second position will set the decimal point (i.e., 2, 3, 6, or 7).

The display decoder 94 also applies a START signal to the line 40. This signal is a word synchronization pulse, which resets the digit scanner in the cathode driver of the output display unit 14 to assure that the cathode driver will select digit 1 when the digit 1 information is on the outputs A, B, C, D, and E. The timing for this signal is shown in Fig. 14.

One other special decoding feature is required. A minus sign is represented in tens complement notation or sign and magnitude notation by the digit 9 in the sign location. However, the display must shown only a minus sign (i.e., segment *g*). The digit 9 in the register A in digit position 2 (exponent sign) or position 13 (mantissa sign) must be displayed as minus. The decoding circuitry uses the pulse on the I_8 buss 28 at bit time b_{11} (see Fig. 3) to know that the digit 9 in digit position 2 of the register A should be a minus and uses the SYNC pulse to know that the digit 9 in digit position 13 of the register A should also be a minus. The pulse on the I_8 buss 28 at bit time b_{11} can be set by a mask option, which allows the minus sign of the exponent to appear in other locations for other uses of the calculator circuits.

CLOCK DRIVER

The bipolar clock driver 22, one phase of which is shown in Fig. 15, requires less than 25 milliwatts and can drive loads up to three hundred picofarads with a voltage swing of +7 to −14 volts. An ENABLE input 98 allows both outputs Q_1 and Q_2 to be held to V_{CC}, the MOS Logic 0 state. This is an effective means of strobing the clock. During dc operation, the transistor pair Q_1—Q_2 allows only one of the output transistor pairs Q_5—Q_6 or Q_7—Q_8 to conduct. A diode D_3 prohibits conduction from transistor Q_6 to transistor Q_8 during transient operation. Thus, the only possible transient short circuit current must flow from transistor Q_5 to transistor Q_7. However, the limited current handling capability of the transistor Q_5 (a lateral PNP) limits this current to less than five milliamps peak. The input signals for the clock driver 22 are generated on the anode driver of the output display unit 14, and the outputs of the clock driver go to each of the MOS circuits in the system. The timing relationships are shown in Fig. 16.

ANODE DRIVER

As discussed above, the display information is partially decoded in the arithmetic and register circuit 20 and completely decoded into seven segment plus decimal point signals in the bipolar anode driver of the output display unit 14. The anode driver also includes the basic clock generator for the system and a circuit for detecting low battery voltage to turn on all the decimal points. A detecting circuit of this type is disclosed in the complete specification of our U.K. patent Specification No. 1363175. A logic diagram of the anode driver is shown in Fig. 17.

The clock generator uses an external LC series circuit to set the oscillator frequency. The advantages of an LC series circuit to set the frequency are: (1) the components can be specified to up to 2% tolerance; and (2) a crystal can be connected to the same external pin to set the frequency to .001% for timing applications.

The square-wave oscillator frequency (all times in this section will be referred to an 800 KHz oscillator frequency, which translates to a 200 KHz clock for the calculator, the actual frequency being somewhat less) is divided by a flip-flop BL to 400 KHz. Flip-flops B1 and B2 are clocked off alternate phases of flip-flop B1 to provide two 200 KHz square waves as shown in Fig. 18. A flip-flop B3 is clocked from the flip-flop B2 and in turn clocks a flip-flop B4 to provide further count-down of the basic clock frequency. The two-phase clock signals Q_1 and Q_2 are generated from the flip-flop BL and B1 and an 800 KHz oscillator 100. They are on for 625 nsec and separated by 625 μsec as shown in Fig. 18. One other periodic signal is derived in the anode driver. Once each digit time a signal (counter-clock) is sent to the cathode driver of the output display unit 14 (the trailing edge of this signal will step the display to the next digit).

The display consists of fifteen characters while the basic calculator word cycle consists of fourteen digits. The extra character is the decimal point. As explained above, a BCD two is placed in the register B at the digit position of the decimal point. The display decoder 94 in the arithmetic and register circuit 20 indicates this by a signal on outputs B and E during bit time T_4 (see Fig. 12). When this condition

is decoded by the anode driver, the decimal point is excited and an extra counter clock signal is given to step the display to the next position (see Figs. 18, 19, and 20). Therefore all remaining digits in the register A are displaced one digit in the display.

Figs. 19 and 20 show the simplified circuit and the timing relationship for the decimal point. The timing is critical since all the inductor current in segment *b* (the last to be excited) must be decayed before the counter clock signal is given to step to the next digit or the remaining current would be discharged through the wrong digit and a faint lighting of the segment *b* on the same digit with the decimal point would occur. The decimal point insertion technique is the reason all other seven segments are excited during the first half of the digit time. The decimal point charging time is one-half that of the other segments. The decimal point segment gets the same current in one-half the time and is one-half as bright as the other segments.

An inductive circuit method of driving the light-emitting diodes is employed. Basically the method involves using the time it takes current to build up in an inductor to limit current, rather than using a resistor as is normally done with LED read-outs. This saves power since the only lossy components in the drive system are the parasitic inductor and transistor resistances. The drive circuit for one digit is shown in Fig. 21. Assuming the cathode transistor switch T_c is closed, an anode switch T_a is closed for 2.5 μsec allowing the current to build up to a value I_p along a nearly triangular waveform (the early part of an exponential buildup). When anode switch T_a is opened, the current is dumped through the LED, decaying in about 5 μsec. The anodes are strobed according to the sequence in Fig. 18. The primary reason for sequentially exciting the anodes is to reduce the peak cathode transistor current. Since the decay time is approximately twice the buildup time, it works out that the peak cathode current is about 2.5 times the peak current in any segment. The LED's are more efficient when excited at a low duty cycle. This means high currents for short periods (80 ma. anode current, 250 ma. cathode current). Fig. 18 also shows the relationship between the anode strobing sequence and the display output signals (A—E) from the arithmetic and register circuit 20.

Since the anode driver operates from the battery voltage directly and drives the decimal point segment, a circuit is provided that senses when the voltage drops below a certain limit and thereupon turns on all decimal points. An external pin is provided to connect a trimming resistor to set the voltage where the indication is to occur.

CATHODE DRIVER

The cathode driver of the output display unit 14 comprises a fifteen position shift register for scanning the fifteen digit display once each word time. This scanning operation moves from digit to digit in response to counter clock signals from the anode driver. Once each word time a START signal arrives from the arithmetic and register circuit 20 to restart the procedure. A block diagram is shown in Fig. 22.

KEYBOARD

The calculator employs a reliable, low-profile, low cost keyboard with tactile feedback such as that shown in United States Patent Specification No. 3941953. The keyboard employs metal strips 102 with slots 104 etched or punched out as shown in Fig. 23, leaving an area which can be stretched to form small humps as shown in Fig. 24. The strips are spot welded to a printed circuit board such that orthogonal traces run under each hump. Pressing a key makes electrical contact between one of the horizontal strips and the corresponding vertical trace. The bounce is less than one millisecond (the calculator contains a wait loop to prevent double entries). Extensive life testing of the keyboard indicates more than a million cycles can be expected. Tolerances must be maintained carefully to prevent the possibility that a key is depressed but no contact is made and to insure uniformity.

One of the main advantages of the keyboard is the "over-center" or "fall away" feel. Fig. 25 shows a force-deflection curve for a typical key. As can be seen a force of about 100 grams must be exceeded before the metal hump "breaks" through. After this critical value the operator cannot prevent contact from being made. Similarly when the key is released, contact is maintained until a critical value when the hump bounces back. Again, past a critical point the operator cannot prevent the key from releasing. This type of action prevents a condition

known as "teasing" in which a key is nearly depressed and slight movement causes multiple entries. The point on the force deflection curve at which contact is made or released is most desirably on the negative slope portion. In the calculator it is either there or exactly at the bottom (point A in Fig. 25), but never on the final positive slope portion.

Figure 1 shows the layout of the keyboard input unit 12 which includes a plurality of function and numeric keys. Several of the function keys are capable of performing more than one function when used in conjunction with a prefix key 15. For example, a function key 17 carries one legend "y^x" which refers to its direct function. Immediately above the key location, a legend 19 indicates a second function "$\sqrt{x}$". The legend 19 is color-coded to designate not only the second function "$\sqrt{x}$", but also to refer the user to the prefix key 15 which activates that function when depressed prior to pressing the key 17. The coloration of the body of the prefix key 15 corresponds to the coloration of all legends such as the legend 19 for association with the functions it initializes. The additional functions of the present invention initialized by the prefix key 15 are "YTM", "INTR", "BOND", "Δ%", "COMPUTE", "DATE", "—Σ", "CLEAR" and "Σ—".

LED DISPLAY

As mentioned above, the inductive drive technique employed for the LED display is inherently efficient because there are no dissipative components other than parasitic resistances and the forward voltage drop across saturated transistor switches. An inductive driver similar to that used in the calculator is disclosed in our U.K. Patent Specification No. 1355150.

The display circuitry used in the calculator is shown in Fig. 26. It comprises an 8 x 15 array of LED's in which the eight rows are scanned by the anode driver and the fifteen columns by the cathode driver. The timing for this scanning was discussed above. A simplified circuit diagram for one segment is shown in Fig. 27. The equivalent piecewise-linear circuit model is shown in Fig. 28. An analysis of this model shows the inductor current buildup and discharge to be nearly linear for the parameters used in the calculator. The discharge-time to charge-time ratios is approximately:

$$\frac{t_{discharge}}{t_{charge}} \quad \frac{V_s - V_{sat}}{V_d + V_{sat}} = \frac{3.8 - 0.1}{1.6 + 0.2} = \frac{3.7}{1.8} = 2.06$$

Fig. 29 shows the inductor current for a basic calculator clock frequency of 175 KHz. The average LED current can be calculated from the formula

$$\text{Ave } I_{LED} = \text{pulse current} \times \text{duty cycle}$$

$$= (\tfrac{1}{2} \times 80\text{ ma}) \frac{5.88\text{ sec}}{\frac{1}{175\text{ KHz}}} \times 56$$

$$= \frac{(80)(5.88)(.175)}{(2)(56)} = .735\text{ ma}$$

The worst case display power (i.e., thirteen 8's and two minus signs) is about 110 milliwatts. Fig. 29 also shows the ringing inherent with inductive drive.

INSTRUCTION SET

Every function performed by the calculator is implemented by a sequence of one or more ten-bit instructions stored in the ROM's Ø—6 of the read-only memory circuit 18. The serial nature of the MOS calculator circuits allows the instruction bits to be decoded from LSB to MSB (right to left) serially. If the first bit is a one, the instruction is either a subroutine jump or a conditional branch as selected by the second bit, with eight bits left for an address. The next largest set of instructions, the arithmetic set, starts with a zero followed by a one (right to left), leaving eight bits for encoded instructions. The ten different types of instructions, employed by the calculator are shown in the table below.

TABLE OF INSTRUCTION TYPES (X = DON'T CARE)

TYPE	AVAILABLE INSTRUCTIONS	NAME	FIELDS
1	256 (ADDRESSES)	JUMP SUBROUTINE	8: SUBROUTINE ADDRESS | 0 1
	256 (ADDRESSES)	CONDITIONAL BRANCH	BRANCH ADDRESS (I_9) | 1 1 (I_0)
2	32 × 8 = 256	ARITHMETIC/REGISTER	5: OPERATION CODE | 3: WORD SELECT | 1 0
3	64 (37 used)	STATUS OPERATIONS	4: N | 2: F (I_5I_4) | 0 (I_3) | 1 (I_2) | 0 (I_1) | 0 (I_0)
		SET BIT N	F = 00
		INTERROGATE N	F = 01
		RESET N	F = 10
		CLEAR ALL	F = 11 (N = 0000)
4	64 (30 used)	POINTER OPERATIONS	4: P | 2: F | 1 | 1 | 0 | 0
		SET POINTER TO P	F = 00
		INTERROGATE P	F = 10
		DECREMENT P	F = 01
		INCREMENT P	F = 11 P = XXXX
5	64 (20 used)	DATA ENTRY/DISPLAY	4: N | 2: F | 1 0 0 0
		LOAD CONSTANT	F = 01
		IS → A	F = 1X (N = XX01)
		BCD INPUT TO C REG	F = 1X (N = XX11)
		STACK INSTRUCTIONS	F = 10 N = (– – –0)
		AVAILABLE	F = 00
6	32 (11 used)	ROM SELECT, MISC.	3: N | 2: F | 1 0 0 0 0
		SELECT ROM "N"	F = 00
		KEYBOARD ENTRY	F = 10 (N = XX1)
		EXTERNAL ENTRY	(N = XX0)
		SUBROUTINE RETURN	F = 01 (N = XXX)
7	16	RESERVED FOR PROGRAM STORAGE	4: X X X X | 1 0 0 0 0 0
8	8	MOS CIRCUIT	3: X X X | 1 0 0 0 0 0 0 0
9	7	AVAILABLE	X X X | 0 0 0 0 0 0 0 0
10	1	NO OPERATION (NOP)	0 0 0 0 0 0 0 0 0 0 0 0

There are two type 1 instructions, namely jump subroutine and conditional branch. They are decoded only by the control and timing circuit 16. No word select is generated and all registers in the arithmetic and register circuit 20 merely recirculate. The object of the jump subroutine instruction is to move to a new address in ROM and to save the existing address (plus one) as a return address. The last instruction in a subroutine must be a RETURN to continue the program where it was left previously.

As discussed above, the control and timing circuit 16 contains a twenty eight-bit shift register 58—62 which holds the current eight-bit ROM address and also has eight bits of storage for one return address (see Fig. 4). During bit times b_{47}—b_{54} the current ROM address flows through the adder 64 and is incremented by one. Normally, this address is updated each word time. However, if the first two bits of the instruction, which arrive at bit times b_{45}—b_{46} are 10, the incremented current address is routed to the return address register 60 of the twenty eight-bit shift register and the remaining eight bits of the instruction, which are the subroutine address, are inserted into the address register 58. These data paths with the JSB control line are shown in Fig. 4. In this way the return address has been saved and the jump address is ready to be transmitted to the ROM at bit times b_{19}—b_{26} of the next word time.

The most frequently used instruction is the conditional branch, which based upon data or system status implements the decision-making capability of the calculator. In the calculator system described here this instruction also functions as an unconditional branch.

The format of the branch instruction, as shown in the instruction table above, is two ones followed by an eight-bit branch address. The instruction is received at bit times b_{45}—b_{54}. The last eight bits of the instruction are stored in the address buffer register 68 (see Fig. 4). During the next word time the carry flip-flop 66 is checked at bit time b_{19}. If the carry flip-flop was set during the previous word time, the current ROM address is transmitted to the ROM's Ø—6. If the carry flip-flop was not set, the branch address is read from the address buffer 68 onto the I_a buss 32 and loaded into the ROM address register 74 (see Fig. 6). Thus, the instruction is a BRANCH IF NO CARRY. There are three ways the carry flip-flop 66 can be set: (1) by a carry generated in the arithmetic and register circuit 20; (2) by a successful interrogation of the pointer position; and (3) by a successful interrogation of one of the twelve status bits. An example is given in the table below.

Example Conditional Branch Execution

WORD	ADDRESS RECEIVED AT ROM	INSTRUCTION SENT BY ROM	INSTRUCTION EXECUTED	RESULT
N–1	P	INCREMENT SIGN DIGIT	—	—
N	P+1	CONDITIONAL BRANCH TO ADDRESS Q	INCREMENT SIGN DIGIT	CARRY GENERATED IF "A" REG. NEGATIVE
N+1	P+2	CONTENTS OF P+2	CONDITIONAL BRANCH	SEND P+2 or
	or	or		
	Q	CONTENTS OF Q		SEND Q

A typical test condition is to determine the sign of a number. Suppose at address P in the program a branch to the location Q is desired if the sign of A is positive, while program execution is to continue if the sign is negative. In the example given in the table above, the instruction "increment the A register, word select of sign digit only" is given at the location P. During word time N—1 the instruction is received by the arithmetic and register circuit 20 and is executed at word time N (the same word time when the CONDITIONAL BRANCH instruction is received by the control and timing circuit 16). If the sign of A is negative, there will be a nine in the sign digit. Incrementing this position will generate a carry and set the carry flip-flop 66 in the control and timing circuit 16. Since the instruction is a branch if no carry is generated, the program execution will jump to location Q only if the sign is positive (i.e., was a zero), otherwise execution continues at P+2.

Note that during word time N+1 the calculator did nothing more than to select which of two addresses to send next (all registers merely recirculate). To perform a branch actually takes two word cycles to execute, one to ask a question and set the carry flip-flop 66 if the answer is YES, and the other to test if the CARRY flip-flop was set and transmit the proper address. In many cases the

asking of the question is an arithmetic operation (i.e. A+B→A) which must be performed anyway. Then the branch takes only one extra instruction.

Contrary to most instruction sets, this set has no unconditional branch instruction. However, since an ordinary "jump" is one of the most used instructions, the conditional branch is also used as an unconditional branch or jump by insuring that the carry flip-flop 66 is reset when an unconditional branch is desired. This is the reason the sense of the conditional branch is BRANCH ON NO CARRY. The carry flip-flop 66 is reset during execution of every instruction except arithmetic (type 2) and interrogation of pointer or status (types 3 and 4). Since only arithmetic and interrogation instructions can set the carry flip-flop 66, the constraint is not severe. The jump subroutine instruction can also be used as an unconditional branch if the previous return address does not have to be saved. In summary, conditional branch can be used as an unconditional branch provided the state of the carry flip-flop 66 is known to be reset (i.e., provided the conditional branch does not follow an arithmetic or an interrogation of pointer or status instruction).

Arithmetic and register (Type 2) instructions apply to the arithmetic and register circuit 20 only. There are thirty-two arithmetic and register instructions divided into eight classes encoded by the left-hand five bits of the instruction. Each of these instructions can be combined with any of eight word select signals to give a total capability of two hundred and fifty-six instructions. The thirty-two arithmetic and register instructions are listed in the table below.

TABLE OF TYPE TWO INSTRUCTIONS
(in order of binary code)

CODE	INST	CODE	INST
0 0000	0−B	1 0000	A−B
0 0001	0→B	1 0001	B←→C
0 0010	A−C	1 0010	SHIFT C RIGHT
0 0011	C−1	1 0011	A−1
0 0100	B→C	1 0100	SHIFT B RIGHT
0 0101	0−C→C	1 0101	C+C→C
0 0110	0→C	1 0110	SHIFT A RIGHT
0 0111	0−C−1→C	1 0111	0→A
0 1000	SHIFT A LEFT	1 1000	A−B→A
0 1001	A→B	1 1001	A←→B
0 1010	A−C→C	1 1010	A−C→A
0 1011	C−1→C	1 1011	A−1→A
0 1100	C→A	1 1100	A+B→A
0 1101	0−C	1 1101	A←→C
0 1110	A+C→C	1 1110	A+C→A
0 1111	C+1→C	1 1111	A+1→A

KEY: A, B, C are registers; → means goes into, ←→ means interchange.

The eight classes of arithmetic and register instructions are:
(1) Clear (3);
(2) Transfer/Exchange (6);
(3) Add/Subtract (7);
(4) Compare (6);
(5) Complement (2);
(6) Increment (2);
(7) Decrement (2); and
(8) Shift (4).

There are three clear instructions. These instructions are 0→A, 0→B, and 0→C. They are implemented by simply disabling all the gates entering the designated register. Since these instructions can be combined with any of the eight word select options, it is possible to clear a portion of a register or a single digit.

There are six transfer/exchange instructions. These instructions are A→B, B→C, C→A, A←→B, B←→C, and C←→A. This variety permits data in the registers A, B, and C to be manipulated in many ways. Again, the power of the instruction

must be viewed in conjunction with the word select option. Single digits can be exchanged or transferred.

There are seven add/subtract instructions which use the adder/subtractor circuitry 84. They are A±C→C, A±B→A, A±C→A, and C+C→C. The last instruction can be used to divide by five. This is accomplished by first adding the number to itself via C+C→C, multiplying by two, then shifting right one digit, and dividing by ten. The result is a divide by five. This is used in the square root routine.

There are six compare instructions. These instructions are always followed by a conditional branch. They are used to check the value of a register or a single digit in a register and still not modify or transfer the contents. These instructions may easily be found in the type two instruction table above since there is no transfer arrow present. They are:

(1) 0–B (Compare B to zero);
(2) A–C (Compare A and C);
(3) C–1 (Compare C to one);
(4) 0–C (Compare C to zero);
(5) A–B (Compare A and B); and
(6) A–1 (Compare A to one).

If, for example, it is desired to branch if B is zero (or any digit or group of digits is zero as determined by WS), the 0–B instruction is followed by a conditional branch. If B was zero, no carry (or borrow) would be generated and the branch would occur. The instruction can be read: IF U≥V THEN BRANCH. Again it is easy to compare single digits or a portion of a register by appropriate word select options.

There are two complement instructions. The number representation system in the calculator is sign and magnitude notation for the mantissa, and tens complement notation in the exponent field. Before numbers can be subtracted, the subtrahend must be tens-complemented (i.e., 0–C→C). Other algorithms require the nines complement (i.e., 0–C–1→C).

There are four increment/decrement instructions (two of each). They are A±1→A and C±1→C.

There are four shift instructions. All three registers A, B, and C can be shifted right, while only the register A has a shift left capability. The arithmetic and register instruction set is summarized by class in the table below.

TABLE OF TYPE TWO INSTRUCTIONS
(divided by class)

Class	Instruction	Code
1) Clear	0→A	10111
	0→B	00001
	0→C	00110
2) Transfer/ Exchange	A→B	01001
	B→C	00100
	C→A	01100
	A←→B	11001
	B←→C	10001
	C←→A	11101
3) Add/ Subtract	A+C→C	01110
	A−C→C	01010
	A+B→A	11100
	A−B→A	11000
	A+C→A	11110
	A−C→A	11010
	C+C→A	10101
4) Compare	0−B	00000
	0−C	01101
	A−C	00010
	A−B	10000
	A−1	10011
	C−1	00011
5) Complement	0−C→C	00101
	0−C−1→C	00111
6) Increment	A+1→A	11111
	C+1→C	01111
7) Decrement	A−1→A	11011
	C−1→C	01011
8) Shift	Sh A Right	10110
	Sh B Right	10100
	Sh C Right	10010
	Sh A Left	01000

The twenty-eight bit shift register 58—62 in the control and timing circuit 16 contains twelve status bits or flags used to remember conditions of an algorithm or some past event (e.g., the decimal point key has already been depressed). These flags can be individdually set, reset, or interrogated or all bits can be cleared (reset simultaneously). The format for the status operation (type 3) instructions given in the instruction types table above is repeated below.

TABLE OF STATUS INSTRUCTION DECODING

Bit #	I_9 I_8 I_7 I_6	I_5 I_4	I_3	I_2 I_1 I_0
FIELD	N	F	0	1 0 0

F	INSTRUCTION
0 0	SET FLAG N
0 1	INTERROGATE FLAG N
1 0	RESET FLAG N
1 1	CLEAR ALL FLAGS (N=0000)

If the status bit N is one when the instruction "interrogate N" is executed, the CARRY flip-flop 66 in the control and timing circuit 16 will be set. The status bit will remain set. Interrogate is always followed by a conditional branch instruction. The form of the interrogation is: "If status bit N=0, then branch", or "If status bit N≠1, then branch. "The reason for this negative orientation is that all branches occur if the test is false (i.e., CARRY flip-flop=0), a result derived from using the conditional and unconditional branches as the same instruction.

Status bit 0 is set when a key is depressed. If cleared it will be set every word time as long as the key is down.

A four-bit counter in the control and timing circuit 16 acts as the pointer or marker 44 to allow arithmetic instructions to operate on a portion of a register. Instructions are available to set and interrogate the pointer at one of fourteen locations or to increment or decrement the present position. The pointer instruction decoding is given in the table below.

TABLE OF POINTER INSTRUCTION DECODING

BIT #	9 8 7 6	5 4	3	2 1 0
FIELD	P	F	1	1 0 0

F	INSTRUCTION	
00	Set pointer to P	
10	Interrogate if pointer at P	
01	Decrement pointer	P = XXXX i.e. don't care
11	Increment pointer	

As with the status interrogate instruction, the CARRY flip-flop 66 is set if the pointer is at P when the "pointer at P?" instruction is executed (as with status interrogation, the actual question is in the negative form: "IF P≠N, THEN BRANCH" or "IF P = OTHER THAN N, THEN BRANCH"). This instruction would be followed by a conditional branch. In a math routine the pointer allows progressive operation on a larger and larger portion of a word. After each iteration (cycle) through a loop, the pointer is decremented (or incremented) and then tested for completion to force another interation or a jump out of the loop.

The data entry and display (type 5) instructions are used to enter data into the arithmetic and register circuit 20, to manipulate the stack and memory registers, and to blank the display (sixteen instructions in this set are not recognized by any of the existing circuits and are therefore available for other external circuits that might be employed with other embodiments of the calculator). The table below contains a detailed decoding of the data entry and display (type 5) instructions.

TABLE OF TYPE 5 INSTRUCTION DECODING

(X = don't care, which in this context means the instruction does not depend on this bit; either a 1 or a 0 here will cause the same execution.)

I_9 I_8 I_7 I_6 I_5 I_4	1 0 0 0

I_9 I_8 I_7 I_6	I_5 I_4	INSTRUCTION
0000→1111	0 0	16 Available instructions
N 0000→1001	0 1	Enters 4 bit code N into C Register at pointer position (LOAD CONSTANT)
0 0 0	0 1 X	Display Toggle
0 0 1	0 1 X	Exchange Memory, C→M→C
0 1 0	0 1 X	Up Stack, C→C→D→E→F
0 1 1	0 1 X	Down Stack, F→F→E→D→A
1 0 0	0 1 X	Display OFF
1 0 1	0 1 X	Recall Memory, M→M→C
1 1 0	0 1 X	Rotate Down, C→F→E→D→C
1 1 1	0 1 X	Clear all registers 0→A,B,C,D,E,F,M
X X	0 1 1 X	I_s → A register (56 bits)
X X	1 1 1 X	BCD → C register (56 bits)

The first set of sixteen instructions ($I_5I_4 = 00$) in this table are not used by any of the main MOS circuits. They may be used by additional circuits or external circuitry listening to the I_s line such as may be employed with other embodiments of the calculator.

The next instruction ($I_5I_4 = 01$) in this table is called the LOAD CONSTANT (LDC) or DIGIT ENTRY instruction. The four bits in I_9—I_6 will be inserted into the C register at the location of the pointer, and the pointer will be decremented. This allows a constant, such as π (pi), to be stored in ROM and transferred to the arithmetic and register circuit 20. To transfer a ten-digit constant requires only eleven instructions (one to preset the pointer). Several exclusions exist in the use of this instruction. When used with the pointer in position 13, it cannot be followed by an arithmetic and register instruction (i.e., by Type 2 or 5 instructions as there are problems in common use of a five-bit I_s buffer 91 in the arithmetic and register circuit 20). With P=12, LDC can be followed by another LDC but not by any other type 2 or 5 instruction. When used with the pointer in position 14, the instruction has no effect. However, when P=12 and LDC is followed by a type 2 or 5 instruction, position 13 in the register C is modified. Loading non-digit codes (1010—1111) is not allowed since they will be modified passing through the adder.

The next set of instructions ($I_6 I_5 I_4 = 01X$) in the type 5 instruction decoding table contains two display instructions and six stack or memory instructions. The display flip-flop in the arithmetic and register circuit 20 controls blanking of all the LED's. When it is reset, the 1111 code is set into the display buffer 96, which is decoded so that no segments are on. There is one instruction to reset this flip-flop ($I_9 I_8 I_7 = 100$) and another to toggle it (000). The toggle feature is convenient for blinking the display.

The remaining instructions in the type 5 instruction decoding table include two affecting memory (Exchange C←→M and Recall M→C), three affecting the stack (Up, Down, and Rotate Down), one general clear, one for loading the register A from the I_s buss 28 (namely, $I_7 I_6 I_5 = 011$), and one for loading the register C from BCD (111). Neither of the two last-mentioned instructions depends on bits I_9, I_8, or I_4. The I_s → A instruction is designed to allow a key code to be transmitted from a program storage circuit to the arithmetic and register circuit 20 for display. The entire fifty-six bits are loaded although only two digits of

information are of interest. The BCD → C instruction allows data input to the arithmetic and register circuit 20 from a data storage circuit or other external source such as might be employed with other embodiments of the calculator.

The ROM select and other type six instructions are denoted by the pattern 10000 in instruction bits I_4—I_0. The decoding table for these instructions is shown below.

TABLE OF TYPE SIX INSTRUCTION DECODING

Circuit Affected	I_9	I_8	I_7	I_6	I_5	I_4	I_3	I_2	I_1	I_0	Instruction
ROM	0	0	0	0	0	1	0	0	0	0	ROM select. One of 8 as specified in bits 19—17.
		↓		0	0	1	0	0	0	0	
	1	1	1	0	0	1	0	0	0	0	
C&T	X	X	X	0	1	1	0	0	0	0	Subroutine return
	X	X	0	1	0	1	0	0	0	0	External key code entry to C&T
	X	X	1	1	0	1	0	0	0	0	Keyboard entry
DATA STORAGE	1	X	0	1	1	1	0	0	0	0	Send *Address* from C Register to Data Storage Circuit
	1	0	1	1	1	1	0	0	0	0	Send *data* from C Register into Data Storage Circuit

The ROM SELECT instruction allows transfer of control from one ROM to another. Each ROM has a masking option which is programmed to decode bits I_9—I_7. A select ROM 3 instruction read from ROM 1 will reset the ROE flip-flop 70 in ROM 1 and set the ROE flip-flop 70 in ROM 3. The address is incremented in the control and timing circuit 16 as usual. Thus, if Select ROM 3 is in location 197 in ROM 1, the first instruction read from ROM 3 will be location 198.

There are three ways to arrive at a desired address, on a different ROM as shown in Fig. 30. In path AA', a transfer (via an unconditional branch or a jump subroutine) to an address one before the desired address (L1) is executed in ROM N first. Then a ROM select M is given. In BB', the opposite order is shown (first ROM N select, then a transfer). Because the desired transfer location (L1 or L2) may already be occupied by an instruction, a third possibility may be used that is less efficient in states but does not depend on program locations. A transfer to L3 is made, then a ROM select, and then an additional transfer from L4 to the final desired location. With this method, L3 and L4 are overhead states.

Bits $I_6I_5 = 01$ designate a subroutine return (RET). There are eight bits of storage in the twenty eight-bit shift register 58—62 of the control and timing circuit 16 for retaining the return address when Jump Subroutine is executed. This address has already been incremented so execution of RET is simply a matter of outputting the address on I_a line 32 at bit times b_{19}—b_{26} and also inserting it into the ROM address register 58 of the shift register. It is also still retained in the return address register 60.

A keycode is entered into the control and timing circuit 16 by depressing a key on the keyboard. A key depression is detected by a positive interrogation of status bit 0. During a computation the keyboard is locked out because this status bit would ordinarily not be interrogated until return to the display loop. The actual key depression saves the state of the system counter (which is also the key code) in the key code buffer 56 (see Fig. 4) and also sets status bit 0. Execution of the KEYBOARD ENTRY instruction routes the key code (six bits) in the key code buffer 56 onto the I_a line 32 and into the ROM address register 58 at bit times

b_{19}—b_{26}. The most significant two bits b_{25} and b_{26} are set to zero so that a keyboard entry always jumps to one of the first sixty-four states.

Two algorithms used in the calculator will now be discussed to further illustrate the instruction set. The first of these algorithms is a display wait loop, used after a key has been processed and while waiting for another key to be actuated. The second of these algorithms is a floating point mulitply operation.

A flow diagram of the display wait loop is shown in Fig. 31. This loop is entered after a keystroke has been processed, the register A has been properly loaded with the number to be displayed, and the register B contains the display "mask" as discussed above. Two flags or status bits are required. Status bit 0 (S0) is hardwired in the control and timing circuit 16 to automatically set whenever a key is down. Status bit 8 (S8) is used in this program to denote the fact that the key which is presently down has already been processed (since a routine may be finished before the key is released). In states D1S1 and D1S2 these two status bits are initialized. Then a loop is used as a time delay (about 14.4 ms.) to wait out any key bounce. In D1S4 status bit 8 (S8) is checked. The first time through the algorithm it must be 1 since it was set in D1S1 to denote the key has been processed. In state D1S5 the display is turned on (actually it is toggled since it must previously have been off; there is no DISPLAY ON instruction). At this time the answer appears to the user. In D1S6 status bit 0 (S0) is checked to see if a key is down. If not (i.e., S0=0), the previous key has been released, and status bit 8 (S8) is reset to 0 (D1S7). The machine is now ready to accept a new key since the previous key has been processed and released. The algorithm cycles through D1S6 and D1S7 waiting for a new key. This is the basic wait cycle of the calculator. If S0=1 in D1S6, the key which is down may be the old key (i.e., the one just processed) or a new key. This can be determined upon return to D1S4 where status bit 8 (S8) is checked. If a new key is down (S8=0), execution jumps to D1S8, the display is blanked, and a jump out is made to service the key. A listing of the algorithm is given in the table below.

TABLE OF WAIT LOOP ALGORITHM

LABEL	OPERATION	COMMENT
D1S1:	1 → S8	Set Status 8
D1S2:	0 → S0	Reset Status 0
D1S3:	P–1 → P	Decrement pointer,
	IF P # 12	48 word loop (3 × 16)
	THEN GO TO D1S3	to wait out key bounce
	DISPLAY OFF	
D1S4:	IF S8 # 1	If key not processed,
	THEN GO TO DIS8:	leave routine
D1S5:	DISPLAY TOGGLE	Turn on display
D1S6:	IF SO# 1	If key up, reset
	THEN GO TO D1S7:	S8 and wait
	GO TO D1S2:	Key down. Check if same key
D1S7:	0 → S8	Indicate key *not* processed
	GO TO D1S6:	Back to wait for key
D1S8:		Blank display
D1S9:	KEYS → ROM ADDRESS	Jump to start of program to
	↓	process key that was down.
	CONTINUE	

The floating point mulitply algorithm multiplies x times y, where the register C contains x in scientific notation and the register D contains y (note that in the calculator the register C corresponds to the user's X register and the register D to the user's Y register). When the multiply key is depressed, the wait loop algorithm will jump to a ROM address corresponding to the first step of the multiply algorithm because of the way the instruction KEYS → ROM ADDRESS (state D1S9 in Fig. 31) is executed. The key code actually becomes the next ROM address. At this time the contents of the registers A—D are indicated by the following:

Register A floating point form of x
Register B display mask for x
Register C scientific form of x
Register D scientific form of y

The algorithm for executing floating point multiply is given in the table below. The letters in parentheses indicate word select options as follows:

P	pointer position	M	mantissa field without sign
WP	Up to pointer position	MS	mantissa with sign
X	Exponent field	W	entire word
XS	Exponent sign	S	mantissa sign only

TABLE OF FLOATING POINT MULTIPLY ALGORITHM

LABEL	OPERATION	COMMENT
MPY1:	STACK → A	Transfer y to A. Drop stack
MPY2:	A+C → C(X)	Add exponents to form exponent of answer
	A+C → C(S)	Add signs to form sign
	IF NO CARRY GO TO MPY3	of answer.
	0 → C(S)	Correct sign if both negative
MPY3:	0 → B(W)	Clear B, then transfer
	A → B(M)	mantissa of y. B(X) = 0.
	0 → A(W)	Prepare A to accumulate product
	2 → P	Set pointer to LSD (Least Significant Digit) Multiplier (Minus 1)
MPY4	P+1 → P	Increment to next digit.
MPY5	A+B → A(W)	Add multiplier mantissa to partial
	C–1 → C(P)	product C(P) times. When C(P)=0,
		IF NO CARRY GO TO MPY5
	SHIFT RIGHT A(W)	Shift partial product right.
	IF P # 12	Check if multiply is complete
	THEN GO TO MPY4	i.e. is pointer at MSD.
	IF A(P) > 1	Check if MSD = 0. If so must
	THEN GO TO MPY6	shift left and correct exp.
	SHIFT LEFT A(M)	Multiply by 10 and decrement exponent
	C–1 → C(X)	
MPY6	C+1 → C(X)	Always do this to correct for factor of 10 too small
	A → B(XS)	Duplicate extra product digits
	A+B → A(XS)	add 11th digits
	IF NO CARRY GO TO MPY7	If sum less than 10, then done
	A+1 → A(M)	If sum more than 10, add 1
	IF NO CARRY GO TO MPY7	If answer was not all 9's, then done
	A+1 → A(P)	If answer was all 9's add 1
	C+1 → C(X)	and increment exponent
MPY7	A EXCHANGE C(M)	Get answer mantissa into C
	GO TO MASK 1	Go to routine to position the answer in A and make the proper mask in B. Then to the DISPLAY program.

DETAILED LISTING OF ROUTINES AND SUBROUTINES OF INSTRUCTIONS

A complete listing of all of the routines and subroutines of instructions employed by the calculator and of all of the constants employed by these routines and subroutines is given below. All of these routines, subroutines, and constants are stored in the ROM's Ø—6, as indicated at the top of the first page associated with each ROM. Each line in each ROM is separately numbered in the first column from the left-hand side of the page. This facilitates reference to different parts of the listing. Each address in ROM's Ø—6 is represented in octal form by four digits in the second column from the left-hand side of the page. The first digit identifies which ROM, and the next three digits represent a nine-bit address (the L preceding these four digits is merely an address identifier). The instruction or constant stored in each address of ROM's Ø—6 is represented in binary form in the third column from the left-hand side of the page. Branching addresses are represented in octal form by four digits in the fourth column from the left-hand side of the page. Explanatory comments are given in the remaining columns.

ROM 0

0	L0000:	1.11..1..1	->	L0262		POWER1 :	JSB POWER2
1	L0001:	.1.111..11	->	L0134			GO TO ERZ
2	L0002:	11111.1.1.				DIG3 :	A + 1 -> A[X]
3	L0003:	11111.1.1.				DIG2 :	A + 1 -> A[X]
4	L0004:	11111.1.1.				DIG1 :	A + 1 -> A[X]
5	L0005:	..1..1..11	->	L0044			IF NO CARRY GO TO DIG0
6	L0006:	.11.1.1...				MUL1 :	STACK -> A
7	L0007:	..1..1....	->	L1010	*****		SELECT ROM 1
8	L0010:	11..1.1...				MS1 :	DOWN ROTATE
9	L0011:	1.1.....11	->	L0240			GO TO MS2
10	L0012:	..1..1....	->	L1013	*****	YTX :	SELECT ROM 1
11	L0013:	111111.111	->	L0375		STOR1 :	GO TO STOR2
12	L0014:	11..1.1...				RDOWN1:	DOWN ROTATE
13	L0015:	.1..111111	->	L0117			GO TO OWFL3
14	L0016:	.11.1.1...				XEY :	STACK -> A
15	L0017:	..1....111	->	L0041			GO TO XEY1
16	L0020:	....					NO OPERATION
17	L0021:	....					NO OPERATION
18	L0022:	11111.1.1.				DIG6 :	A + 1 -> A[X]
19	L0023:	11111.1.1.				DIG5 :	A + 1 -> A[X]
20	L0024:	11111.1.1.				DIG4 :	A + 1 -> A[X]
21	L0025:	......1.11	->	L0002			IF NO CARRY GO TO DIG3
22	L0026:	.11.1.1...				PLS1 :	STACK -> A
23	L0027:	..1..1....	->	L1030	*****		SELECT ROM 1
24	L0030:	1.11...1..				FV1 :	1 -> S11
25	L0031:	...1111.11	->	L0036			GO TO N1
26	L0032:	...1111.11	->	L0036		PV1 :	GO TO N1
27	L0033:	1.1....1..				PMT1 :	1 -> S10
28	L0034:	...1111.11	->	L0036		ROR1 :	GO TO N1
29	L0035:	....11....					RETURN
30	L0036:	.111.1.1..				N1 :	IF S7 # 1
31	L0037:	..11....11	->	L0060			THEN GO TO N2
32	L0040:	.11..1....	->	L3041	*****		SELECT ROM 3
33	L0041:	..1..1....	->	L1042	*****	XEY1 :	SELECT ROM 1
34	L0042:	..1..1....	->	L1043	*****	SUM1 :	SELECT ROM 1
35	L0043:	.1.1...1..				DP1 :	1 -> S5
36	L0044:	..1..1....	->	L1045	*****	DIG0 :	SELECT ROM 1
37	L0045:	....					NO OPERATION
38	L0046:	.11.1.1...				DIV1 :	STACK -> A
39	L0047:	..1..1....	->	L1050	*****		SELECT ROM 1
40	L0050:	11...1....	->	L6051	*****	DATE :	SELECT ROM 6
41	L0051:	....					NO OPERATION
42	L0052:	1....1....	->	L4.53	*****	SOD1 :	SELECT ROM 4
43	L0053:	1....1....	->	L4054	*****	TRND1 :	SELECT ROM 4
44	L0054:	.11.1.1...				PRC1 :	STACK -> A
45	L0055:	..1..1....	->	L1056	*****		SELECT ROM 1
46	L0056:	.111...1..				PRE :	1 -> S7
47	L0057:	.1....1.11	->	L0102			GO TO STOR3
48	L0060:	.111...1..				N2 :	1 -> S7
49	L0061:	.1..111111	->	L0117			GO TO OWFL3
50	L0062:	11111.1.1.				DIG9 :	A + 1 -> A[X]
51	L0063:	11111.1.1.				DIG8 :	A + 1 -> A[X]
52	L0064:	11111.1.1.				DIG7 :	A + 1 -> A[X]
53	L0065:	...1..1.11	->	L0022			IF NO CARRY GO TO DIG6
54	L0066:	..1111111.				MIN1 :	0 - C - 1 -> C[S]
55	L0067:	...1.11..1	->	L0026			JSB PLS1

```
 56 LØØ7Ø:  ..11..111.
 57 LØØ71:  .1...1...1  ->  LØ1Ø4
 58 LØØ72:  1111.11.11  ->  LØ366
 59 LØØ73:  1....1.1..
 6Ø LØØ74:  .1..11..11  ->  LØ114
 61 LØØ75:  .1..11.111  ->  LØ115
 62 LØØ76:  .1..1.1...
 63 LØØ77:  1.111..1..
 64 LØ1ØØ:  1.1.1..1..
 65 LØ1Ø1:  .1111..1..
 66 LØ1Ø2:  .1..1..1..
 67 LØ1Ø3:  .1.1....11  ->
 68 LØ1Ø4:  .111.1.1..
 69 LØ1Ø5:  1...111.11  ->  LØ216
 7Ø LØ1Ø6:  .1...1.1..
 71 LØ1Ø7:  .1..1..111  ->  LØ111
 72 LØ11Ø:  1...111.11  ->  LØ216
 73 LØ111:  .1..1.1...
 74 LØ112:  .1..1.1...
 75 LØ113:  ..11111.11  ->  LØØ76
 76 LØ114:  .1..1.1...
 77 LØ115:  1.1.1.1...
 78 LØ116:  .1111..1..
 79 LØ117:  .1.....1..
 8Ø LØ12Ø:  1...1..1..
 81 LØ121:  .11...111.
 82 LØ122:  .1..1.111.
 83 LØ123:  11....11..
 84 LØ124:  ..11.1.11.
 85 LØ125:  .1111...1.
 86 LØ126:  .1111...1.
 87 LØ127:  .11.111.1.
 88 LØ13Ø:  .111111111  ->  LØ177
 89 LØ131:  ..111.1.1.
 9Ø LØ132:  .11.111.1.
 91 LØ133:  1..1...111  ->  LØ221
 92 LØ134:  .1.1...1..
 93 LØ135:  111..11.1.
 94 LØ136:  .11....111  ->  LØ141
 95 LØ137:  ..11..111.
 96 LØ14Ø:  .1.1.....1  ->  LØ12Ø
 97 LØ141:  ..11..111.
 98 LØ142:  .1.111..1.
 99 LØ143:  ..11.11.1.
1ØØ LØ144:  111.11111.
1Ø1 LØ145:  .1.1....11  ->  LØ12Ø
1Ø2 LØ146:  .1..1..1..
1Ø3 LØ147:  1..11..1..
1Ø4 LØ15Ø:  11....11..
1Ø5 LØ151:  ....1..1..
1Ø6 LØ152:  .....111..
1Ø7 LØ153:  11..1.11..
1Ø8 LØ154:  .11.1.1.11  ->  LØ152
1Ø9 LØ155:  1...1.1...
11Ø LØ156:  1..1.1.1..
111 LØ157:  .1111..111  ->  LØ171
112 LØ16Ø:  .1.11..1..
113 LØ161:  .1....1.1.
114 LØ162:  ..11.1....
115 LØ163:  1..1...1..
```

```
CLR1  : Ø -> C[W]
        JSB CLR2
CHS1  : GO TO CHS2
RCL1  : IF S8 # 1
            THEN GO TO RCL3
        GO TO RCL4
ENTER1: C -> STACK
        Ø -> S11
        Ø -> S1Ø
        Ø -> S7
STOR3 : Ø -> S4
GO TO OWFL1
CLR2  : IF S7 # 1
            THEN GO TO CLR3
        IF S4 # 1
            THEN GO TO CLR4
        GO TO CLR3
CLR4  : C -> STACK
      : C -> STACK
        GO TO ENTER1
RCL3  : C-> STACK
RCL4  : M -> C
OWFL7 : Ø -> S7
OWFL3 : 1 -> S4
OWFL1 : Ø -> S8
OWFL4 : C -> A[W]
OWFL5 : A -> B[W]
        12 -> P
        Ø -> C[MS]
        C + 1 -> C[P]
        C + 1 -> C[P]
        IF C[XS] = Ø
            THEN GO TO MSK1
        Ø - C - 1 -> C[X]
        IF C[XS] = Ø
            THEN GO TO MSK2
ERZ   : 1 -> S5
        A + B -> A[XS]
        IF NO CARRY GO TO OWFL2
        Ø -> C[W]
        JSB OWFL1
OWFL2 : Ø -> C[W]
        C - 1 -> C[WP]
        Ø -> C[XS]
        A EXCHANGE C[S]
        GO TO OWFL1
DIS4  : Ø -> S4
DIS3  : Ø -> S9
        12 -> P
DIS5  : Ø -> SØ
DIS6  : P - 1 -> P
        IF P # 12
            THEN GO TO DIS6
        DISPLAY OFF
        IF S9 # 1
            THEN GO TO DIS7
        Ø -> S5
        SHIFT LEFT A[X]
TKR   : KEYS -> ROM ADDRESS
DIS9  : 1 -> S9
```

```
116 LØ164:  ...1..11..
117 LØ165:  .1.1.1.1..
118 LØ166:  .1111.1.11  ->  LØ172
119 LØ167:  .11111..1.
120 LØ170:  .111..1111  ->  LØ163
121 LØ171:  ....1.1...
122 LØ172:  .....1.1..
123 LØ173:  .111..1111  ->  LØ163
124 LØ174:  .11.1..111  ->  LØ151
125 LØ175:  .1..1.1.1.
126 LØ176:  1.1..1.111  ->  LØ245
127 LØ177:  1..1111..1  ->  LØ236
128 LØ200:  1.111.1.1.
129 LØ201:  11111.1.1.
130 LØ202:  .1....1.1.
131 LØ203:  11..1.111.
132 LØ204:  1.....1.1.
133 LØ205:  .11111.111  ->  LØ175
134 LØ206:  .1..1.1.1.
135 LØ207:  11.11.1.1.
136 LØ210:  1..11.1111  ->  LØ233
137 LØ211:  ..111.11..
138 LØ212:  1..1.11.11  ->  LØ226
139 LØ213:  ..1..1....  ->  L1214  *****
140 LØ214:  .....111..
141 LØ215:  1...1..111  ->  LØ211
142 LØ216:  .1111..1..
143 LØ217:  .1..1..1..
144 LØ220:  .1.1...111  ->  LØ121
145 LØ221:  .11...1.1.
146 LØ222:  1..1111..1  ->  LØ236
147 LØ223:  11111.1.1.
148 LØ224:  11.11.1.1.
149 LØ225:  1..11..111  ->  LØ231
150 LØ226:  .1.11.1.1.
151 LØ227:  1...11..11  ->  LØ214
152 LØ230:  1...1.1111  ->  LØ213
153 LØ231:  1.11...11.
154 LØ232:  1..1.1...1  ->  LØ224
155 LØ233:  .....111..
156 LØ234:  1..1...11.
157 LØ235:  1....111.1  ->  LØ207
158 LØ236:  ..1..1....  ->  L1237  *****
159 LØ237:  ....11....
160 LØ240:  ..1..1....  ->  L1241  *****
161 LØ241:  1....11.1.
162 LØ242:  1.1..1.111  ->  LØ245
163 LØ243:  11111.1.1.
164 LØ244:  11.1111.1.
165 LØ245:  ..11..1.1.
166 LØ246:  ..11..11..
167 LØ247:  11..1.11..
168 LØ250:  1111...111  ->  LØ361
169 LØ251:  1...1.111.
170 LØ252:  .11.1..1..
171 LØ253:  .11..111.1  ->  LØ147
172 LØ254:  1.1111.11.
173 LØ255:  .1...1.1..
174 LØ256:  1.11....11  ->  LØ260
175 LØ257:  .1..1.1...
```

```
                1 -> P
                IF S5 # 1
                    THEN GO TO DIS1Ø
                C + 1 -> C[WP]
                IF NO CARRY GO TO DIS9
DIS7        :   DISPLAY TOGGLE
DIS1Ø       :   IF SØ # 1
                    THEN GO TO DIS9
                GO TO DIS5
SCINT9      :   A -> B[X]
                GO TO SCINT4
MSK1        :   JSB SROUND
                Ø -> A[X]
                A + 1 -> A[X]
                SHIFT LEFT A[X]
                A EXCHANGE B[W]
                IF A >= B[X]
                    THEN GO TO SCINT9
                A -> B[X]
MSK11       :   A - 1 -> A[X]
                IF NO CARRY GO TO MSK12
MSK14       :   IF P # 3
                    THEN GO TO MSK13
MSK15       :   SELECT ROM 1
MSK28       :   P - 1 -> P
                GO TO MSK14
CLR3        :   Ø -> S7
                Ø -> S4
                GO TO OWFL4
MSK2        :   C -> A[X]
                JSB SROUND
                A + 1 -> A[X]
MSK21       :   A - 1 -> A[X]
                IF NO CARRY GO TO MSK22
MSK13       :   C - 1 -> C[X]
                IF NO CARRY GO TO MSK28
                GO TO MSK15
MSK22       :   SHIFT RIGHT A[M]
                JSB MSK21
MSK12       :   P - 1 -> P
                SHIFT RIGHT C[M]
                JSB MSK11
SROUND      :   SELECT ROM 1
                RETURN
MS2         :   SELECT ROM 1
SCINT3      :   IF A >= B[XS]
                    THEN GO TO SCINT4
SCINT2      :   A + 1 -> A[X]
                A - 1 -> A[XS]
SCINT4      :   Ø -> C[X]
                3 -> P
SCINT7      :   IF P # 12
                    THEN GO TO SCINT5
SCINT6      :   B EXCHANGE C[W]
DIS1        :   Ø -> S6
                JSB DIS3
                Ø -> A[MS]
DENT1       :   IF S4 # 1
                    THEN GO TO DENT2
                C -> STACK
```

```
176  LØ26Ø:   .11.1..1..
177  LØ261:   111.1..111  ->  LØ351
178  LØ262:   111.1.1...
179  LØ263:   ....11.1..
180  LØ264:   ..1....1..
181  LØ265:   .1..1..111  ->  LØ111
182  LØ266:   11111.1.1.
183  LØ267:   .......11.
184  LØ270:   111..11.11  ->  LØ346
185  LØ271:   ..111.11..
186  LØ272:   1.11111111  ->  LØ277
187  LØ273:   ..11..111.
188  LØ274:   .11111111.
189  LØ275:   .11111111.
190  LØ276:   11.1..11..
191  LØ277:   1..1.1..1.
192  LØ300:   .......11.
193  LØ301:   11..1.1111  ->  LØ313
194  LØ302:   11....11..
195  LØ303:   1..11...1.
196  LØ304:   11..1.1111  ->  LØ313
197  LØ305:   1.111.1.1.
198  LØ306:   11.11.1.1.
199  LØ307:   1..11...1.
200  LØ310:   11..1.1111  ->  LØ313
201  LØ311:   .1.....11.
202  LØ312:   11...11.11  ->  LØ306
203  LØ313:   .1..1.1.1.
204  LØ314:   1...1.111.
205  LØ315:   111.1.111.
206  LØ316:   .1.11..1..
207  LØ317:   .11..11..1  ->  LØ146
208  LØ320:   1...1.111.
209  LØ321:   ..11..1.1.
210  LØ322:   .11111.11.
211  LØ323:   ......11..
212  LØ324:   .1.11...1.
213  LØ325:   ....1111..
214  LØ326:   .1.11...1.
215  LØ327:   11.11.1.11  ->  LØ332
216  LØ330:   .1...1..1.
217  LØ331:   11.1.1.111  ->  LØ325
218  LØ332:   11..1.1.1.
219  LØ333:   .1..1.111.
220  LØ334:   .1.1.1.1..
221  LØ335:   111.....11  ->  LØ340
222  LØ336:   .11....1..
223  LØ337:   11..1.1111  ->  LØ313
224  LØ340:   .11..1.1..
225  LØ341:   1.11.11.11  ->  LØ266
226  LØ342:   .....111..
227  LØ343:   ..1.1.11..
228  LØ344:   1.11111111  ->  LØ277
229  LØ345:   11......11  ->  LØ300
230  LØ346:   1..1..111.
231  LØ347:   1...1.111.
232  LØ350:   .11..11..1  ->  LØ146
233  LØ351:   ..11..111.
234  LØ352:   ....1.111.
235  LØ353:   11.1..11..
```

```
DENT2  : Ø -> S6
         GO TO DENT3
POWER2 : CLEAR REGISTERS
         CLEAR STATUS
         1 -> S2
         GO TO CLR4
DENT8  : A + 1 -> A[X]
         IF B[M] = Ø
              THEN GO TO DENT18
         IF P # 3
              THEN GO TO DENT5
         Ø -> C[W]
         C + 1 -> C[S]
         C + 1 -> C[S]
         13 -> P
DENT5  : SHIFT RIGHT C[WP]
DENT19 : IF B[M] = Ø
              THEN GO TO DENT1Ø
         12 -> P
         IF A[P] >= 1
              THEN GO TO DENT1Ø
         Ø -> A[X]
DENT11 : A - 1 -> A[X]
         IF A[P] >= 1
              THEN GO TO DENT1Ø
         SHIFT LEFT A[M]
         GO TO DENT11
DENT1Ø : A -> B[X]
         B EXCHANGE C[W]
         A EXCHANGE C[W]
         Ø -> S5
         JSB DIS4
         B EXCHANGE C[W]
         Ø -> C[X]
         C + 1 -> C[MS]
DENT12 : Ø -> P
         C - 1 -> C[P]
DENT4  : P + 1 -> P
         C - 1 -> C[P]
         IF NO CARRY GO TO DENT6
         SHIFT LEFT A[WP]
         GO TO DENT4
DENT6  : A EXCHANGE B[X]
         A -> B[W]
         IF S5 # 1
              THEN GO TO DENT7
         1 -> S6
         GO TO DENT1Ø
DENT7  : IF S6 # 1
              THEN GO TO DENT8
         P - 1 -> P
         IF P # 2
              THEN GO TO DENT5
         GO TO DENT19
DENT18 : SHIFT RIGHT C[W]
         B EXCHANGE C[W]
         JSB DIS4
DENT3  : Ø -> C[W]
         Ø -> B[W]
         13 -> P
```

```
236  LØ354:   ..11.11...
237  LØ355:   1...1..1..
238  LØ356:   .1.11.1.1.
239  LØ357:   1...1.1.1.
240  LØ360:   11.1..1111  ->  LØ323
241  LØ361:   1..11...1.
242  LØ362:   1.1.1..111  ->  LØ251
243  LØ363:   .1.11...1.
244  LØ364:   ....1111..
245  LØ365:   1.1..11111  ->  LØ247
246  LØ366:   ..1111111.
247  LØ367:   .11..1111.
248  LØ370:   .11...1.1.
249  LØ371:   .11..11111  ->  LØ147
250  LØ372:   ..........
251  LØ373:   ..........
252  LØ374:   ..........
253  LØ375:   ..1.1.1...
254  LØ376:   1.1.1.1...
255  LØ377:   .1....1.11  ->  LØ102
```

```
                LOAD CONSTANT 3
                Ø -> S8
                C - 1 -> C[X]
                B EXCHANGE C[X]
                GO TO DENT12
SCINT5  :       IF A[P] >= 1
                        THEN GO TO SCINT6
                C - 1 -> C[P]
                P + 1 -> P
                GO TO SCINT7
CHS2    :       Ø - C - 1 -> C[S]
                C -> A[S]
                C -> A[X]
                GO TO DIS3
                NO OPERATION
                NO OPERATION
                NO OPERATION
STOR2   :       C EXCHANGE M
                M -> C
                GO TO STOR3
```

ROM 1

0	L1000:	.....					NO OPERATION
1	L1001:	.....					NO OPERATION
2	L1002:	...1...1..				R3	: 1 –> S1
3	L1003:	..11.11.11	–>	L1066		R2	: GO TO R12
4	L1004:	...1...1..				R1	: 1 –> S1
5	L1005:	.1..11.111	–>	L1115			GO TO R13
6	L1006:	1..11..1..				XTY	: 0 –> 89
7	L1007:	.1...1....	–>	L2010	*****		SELECT ROM 2
8	L1010:	111..11..1	–>	L1346		SMUL11	: JSB MPY
9	L1011:	.1..11.111	–>	L1115			GO TO R13
10	L1012:	.1...1....	–>	L2013	*****	SQR1	: SELECT ROM 2
11	L1013:	1......1..				XTY11	: 1 –> S8
12	L1014:	.111.1.1..					IF S7 # 1
13	L1015:	...1.11.11	–>	L10026			THEN GO TO XTY12
14	L1016:	.1111..1..					0 –> S7
15	L1017:	111111...1	–>	L1374			JSB SQR
16	L1020:	.1..11.111	–>	L1115			GO TO R13
17	L1021:	1....1....	–>	L4022	*****	RETR4	: SELECT ROM 4
18	L1022:	..11.1.111	–>	L1065		R6	: GO TO R11
19	L1023:	...1...1..				R5	: 1 –> S1
20	L1024:	..11...1..				R4	: 1 –> S3
21	L1025:	.1..11.111	–>	L1115			GO TO R13
22	L1026:	.....11..1	–>	L1006		XTY12	: JSB XTY
23	L1027:	.1..11..11	–>	L1114			GO TO R14
24	L1030:	.1111..1..					0 –> S7
25	L1031:	.11.11...1	–>	L1154		ADD11	: JSB ADD
26	L1032:	.1..11.111	–>	L1115			GO TO R13
27	L1033:	.1111..1..				DIG10	: 0 –> S7
28	L1034:	.....1....	–>	L0035	*****		SELECT ROM 0
29	L1035:	....11....				RET11	: RETURN
30	L1036:	.1...1.1..				DIG11	: IF S4 # 1
31	L1037:	..11....11	–>	L1060			THEN GO TO DIG14
32	L1040:	...11.1111	–>	L1033			GO TO DIG10
33	L1041:	.....					NO OPERATION
34	L1042:	11..111111	–>	L1317		XEY	: GO TO MS17
35	L1043:	.1.11.1111	–>	L1133		SUM11	: TO TO SUM12
36	L1044:	.1..11.111	–>	L1115		R0	: GO TO R13
37	L1045:	.111.1.1..					IF S7 # 1
38	L1046:	...11.1111	–>	L1033			THEN GO TO DIG10
39	L1047:	...1111.11	–>	L1036			GO TO DIG11
40	L1050:	.1111..1..				SDIV11	: 0 –> S7
41	L1051:	..11111.11	–>	L1076			GO TO DI
42	L1052:	.1..1.1...				PRC2	: C –> STACK
43	L1053:	.111.1.1..					IF S7 # 1
44	L1054:	.1......11	–>	L1100			THEN GO TO PRC4
45	L1055:	..111...11	–>	L1070			GO TO PRC3
46	L1056:	111.1.111.				PRC11	: A EXCHANGE C[W]
47	L1057:	..1.1.1.11	–>	L1052			GO TO PRC2
48	L1060:	....11.1..				DIG14	: CLEAR STATUS
49	L1061:	..11.1....				TKRR1	: KEYS –> ROM ADDRESS
50	L1062:	.....				R9	: NO OPERATION
51	L1063:	.....				R8	: NO OPERATION
52	L1064:	...1...1..				R7	: 1 –> S1
53	L1065:	..11...1..				R11	: 1 –> S3
54	L1066:	..1....1..				R12	: 1 –> S2
55	L1067:	.1..11.111	–>	L1115			GO TO R13

```
56  L1070:  .1111..1..                                PRC3  : Ø -> S7
57  L1071:  .11.1.11.1  ->  L1153                           JSB SUB
58  L1072:  11..1.1...                                      DOWN ROTATE
59  L1073:  .1..1.1...                                      C -> STACK
60  L1074:  .1.11.1.1.                                     C - 1 -> C[X]
61  L1075:  .1.11.1.1.                                     C - 1 -> C[X]
62  L1076:  111..1...1  ->  L1344                   DI    : JSB DIV
63  L1077:  .1..11.1.1  ->  L1115                          JSB R13
64  L1100:  111..11..1  ->  L1346                   PRC4  : JSB MPY
65  L1101:  .1.11.1.1.                                     C - 1 -> C[X]
66  L1102:  .1.11.1.1.                                     C - 1 -> C[X]
67  L1103:  .1..11.1.1  ->  L1115                          JSB R13
68  L1104:  11..1.1...                              R100  : DOWN ROTATE
69  L1105:  .1.11.1.1.                                     C - 1 -> C[X]
70  L1106:  .1.11.1.1.                                     C - 1 -> C[X]
71  L1107:  1.111.111.                              ONE   : Ø -> A[W]
72  L1110:  111111111.                                      A + 1 -> A[S]
73  L1111:  1.11..111.                                      SHIFT RIGHT A[W]
74  L1112:  111.1.111.                                      A EXCHANGE C[W]
75  L1113:  11.1111111  ->  L1337                           GO TO RTN16
76  L1114:  .11.1.1...                              R14   : STACK -> A
77  L1115:  .....1....  ->  LØ116   *****   R13   : SELECT ROM Ø
78  L1116:  ..11.1111.                              MSK2Ø : Ø -> C[S]
79  L1117:  ..11.11.1.                                     Ø -> C[XS]
80  L1120:  1.1.1...1.                                     C + C -> C[P]
81  L1121:  .1.11...11  ->  L1130                          IF NO CARRY TO MSK16
82  L1122:  ..1..1..1.                                     B -> C[WP]
83  L1123:  .1111.111.                                     C + 1 -> C[W]
84  L1124:  .11.11111.                                     IF C[S] = Ø
85  L1125:  .1.11...11  ->  L1130                                THEN GO TO MSK16
86  L1126:  1..1.1.11.                                     SHIFT RIGHT C[MS]
87  L1127:  1.1..1.11.                                     SHIFT RIGHT B[MS]
88  L1130:  111.1.111.                              MSK16 : A EXCHANGE C[W]
89  L1131:  .11..1111.                                      C -> A[S]
90  L1132:  1.1.1...11  ->  L1250                           GO TO MSKRØ
91  L1133:  .111.1.1..                              SUM12 : IF S7 # 1
92  L1134:  1.1.11.111  ->  L1255                                THEN GO TO SUM13
93  L1135:  .1...1.1..                                      IF S4 # 1
94  L1136:  1.1.1.1.11  ->  L1252                                THEN GO TO SUM14
95  L1137:  .11..1....  ->  L3140   *****                   SELECT ROM 3
96  L1140:  ..11..1.1.                              R     : Ø -> C[X]
97  L1141:  ..11.1.1..                                      IF S3 # 1
98  L1142:  1..1.11111  ->  L1227                                THEN GO TO RND1
99  L1143:  .1111.1.1.                                      C + 1 -> C[X]
100 L1144:  1.1.1.1.1.                                      C + C -> C[X]
101 L1145:  1.1.1.1.1.                                      C + C -> C[X]
102 L1146:  ..1..1.1..                              RN3   : IF S2 # 1
103 L1147:  1..1.11111  ->  L1227                            THEN GO TO RND1
104 L1150:  ...1.1.1..                                      IF S1 # 1
105 L1151:  1..111..11  ->  L1234                            THEN GO TO RND3
106 L1152:  1.1.....11  ->  L1240                           GO TO SCIN
107 L1153:  ..1111111.                              SUB   : Ø - C - 1 -> C[S]
108 L1154:  .1..1.111.                              ADD   : A -> B[W]
109 L1155:  1111111.1.                              ADD1  : A + 1 -> A[XS]
110 L1156:  1111111.1.                                      A + 1 -> A[XS]
111 L1157:  .111111.1.                                      C + 1 -> C[XS]
112 L1160:  .111111.1.                                      C + 1 -> C[XS]
113 L1161:  ...1..1.1.                                      IF A >= C[X]
114 L1162:  .111.1..11  ->  L1164                            THEN GO TO ADD4
115 L1163:  111.1.111.                                      A EXCHANGE C[W]
```

```
116 L1164:  1..11..11.
117 L1165:  1111.11111  ->  L1367
118 L1166:  .1111.1.11  ->  L1172
119 L1167:  1.11...11.
120 L1170:  1..11..11.
121 L1171:  11111...11  ->  L1370
122 L1172:  .1.1111.1.
123 L1173:  .1.1111.1.
124 L1174:  1.111.1.1.
125 L1175:  111.11111.
126 L1176:  11.1.1111.
127 L1177:  1..111111.
128 L1200:  1....1..11  ->  L12404
129 L1201:  1111.1.11.
130 L1202:  11.1.1111.
131 L1203:  .1...1....  ->  L2204   *****
132 L1204:  .1.1...11.
133 L1205:  1....11111  ->  L1207
134 L1206:  ..1.11.11.
135 L1207:  .11....11.
136 L1210:  .1...1....  ->  L2211   *****
137 L1211:  ..........
138 L1212:  ..........
139 L1213:  ..........
140 L1214:  .1111...1.
141 L1215:  ..11..1.1.
142 L1216:  .1.111..1.
143 L1217:  1...1.111.
144 L1220:  111.1.111.
145 L1221:  ....111..
146 L1222:  .1..111.11  ->  L1116
147 L1223:  ..........
148 L1224:  ..........
149 L1225:  ..........
150 L1226:  ..........
151 L1227:  ...1.1.1..
152 L1230:  1..11.1.11  ->  L1232
153 L1231:  .1111.1.1.
154 L1232:  ..1..1.1..
155 L1233:  1..1111.11  ->  L1236
156 L1234:  .1111.1.1.
157 L1235:  .1111.1.1.
158 L1236:  .....1....  ->  L0237   *****
159 L1237:  .11.....11  ->  L1140
160 L1240:  .....1....  ->  L0241   *****
161 L1241:  11..1.1...
162 L1242:  .111.1.1..
163 L1243:  111.1..111  ->  L1351
164 L1244:  .1111..1..
165 L1245:  11.11..1.1  ->  L1331
166 L1246:  .1..1.1...
167 L1247:  ....1...11  ->  L1010
168 L1250:  .11.1..1..
169 L1251:  .....1....  ->  L0252   *****
170 L1252:  ..1111111.
171 L1253:  .1111..1..
172 L1254:  .1.....1..
173 L1255:  .11.1.1...
174 L1256:  1...1..1..
175 L1257:  .1..1.1...
```

```
ADD4  : IF A[M] >= 1
            THEN GO TO ADD2
        GO TO ADD7
ADD3  : SHIFT RIGHT A[M]
        IF A[M] >= 1
            THEN GO TO ADD5
ADD7  : C - 1 -> C[XS]
        C - 1 -> C[XS]
        Ø -> A[X]
        A EXCHANGE C[S]
        A - C -> A[S]
        IF A[S] >= 1
            THEN GO TO ADD8
        A + C -> A[MS]
        A - C -> A[S]
        SELECT ROM 2
ADD8  : A - C -> C[M]
        IF NO CARRY GO TO ADD9
        Ø - C -> C[MS]
ADD9  : C -> A[M]
ADD10 : SELECT ROM 2
        NO OPERATION
        NO OPERATION
        NO OPERATION
        C + 1 -> C[P]
        Ø -> C[X]
        C - 1 -> C[WP]
        B EXCHANGE C[W]
        A EXCHANGE C[W]
        P - 1 -> P
        GO TO MSK20
        NO OPERATION
        NO OPERATION
        NO OPERATION
        NO OPERATION
RND1  : IF S1 # 1
            THEN GO TO RND2
        C + 1 -> C[X]
RND2  : IF S2 # 1
            THEN GO TO RND4
RND3  : C + 1 -> C[X]
        C + 1 -> C[X]
RND4  : SELECT ROM Ø
        GO TO R
SCIN  : SELECT ROM Ø
MS11  : DOWN ROTATE
        IF S7 # 1
            THEN GO TO MS12
        Ø -> S7
        JSB ROT1
        C -> STACK
        GO TO SMUL11
MSKRØ : Ø -> S6
        SELECT ROM Ø
SUM14 : Ø - C - 1 -> C[S]
        Ø -> S7
        1 -> S4
SUM13 : STACK -> A
        Ø -> S8
        C -> STACK
```

```
176 L1260:  .11.11...1  ->  L1154          JSB ADD
177 L1261:  11..1.1...                     DOWN ROTATE
178 L1262:  .11...111.                     C -> A[W]
179 L1263:  111..11..1  ->  L1346          JSB MPY
180 L1264:  .1...1.1..                     IF S4 # 1
181 L1265:  1.11.1111   ->  L1267                THEN GO TO SUM16
182 L1266:  ..1111111.                     0 - C - 1 -> C[S]
183 L1267:  .11.1.1...             SUM16 : STACK -> A
184 L1270:  .1..1.1...                     C -> STACK
185 L1271:  111.1.111.                     A EXCHANGE C[W]
186 L1272:  .1...111.1  ->  L1107          JSB ONE
187 L1273:  .1...1.1..                     IF S4 # 1
188 L1274:  1.11111.11  ->  L1276                THEN GO TO SUM15
189 L1275:  .1.111111.                     C - 1 -> C[S]
190 L1276:  .11.11...1  ->  L1154  SUM15 : JSB ADD
191 L1277:  11..1.1...                     DOWN ROTATE
192 L1300:  .11.1.1...                     STACK -> A
193 L1301:  .11.11...1  ->  L1154          JSB ADD
194 L1302:  .1..1.1...                     C -> STACK
195 L1303:  11..1.1...                     DOWN ROTATE
196 L1304:  11..1.1...                     DOWN ROTATE
197 L1305:  .1..11.111  ->  L1115          GO TO R13
198 L1306:  .1...111.1  ->  L1107  MS14 : JSB ONE
199 L1307:  .11.1.11.1  ->  L1153          JSB SUB
200 L1310:  1...1.111.                     B EXCHANGE C[W]
201 L1311:  11..1.1...                     DOWN ROTATE
202 L1312:  111.1.111.                     A EXCHANGE C[W]
203 L1313:  111..1...1  ->  L1344          JSB DIV
204 L1314:  1.....1...                     1 -> S8
205 L1315:  111111...1  ->  L1374          JSB SQR
206 L1316:  .11.1.1...                     STACK -> A
207 L1317:  .1..1.1...             MS17 : C -> STACK
208 L1320:  111.1.111.                     A EXCHANGE C[W]
209 L1321:  .1..11.111  ->  L1115          GO TO R13
210 L1322:  11..1.1...             CSN  : DOWN ROTATE
211 L1323:  11..1.1...                     DOWN ROTATE
212 L1324:  ..1111111.                     0 - C - 1 -> C[S]
213 L1325:  11..1.1...                     DOWN ROTATE
214 L1326:  11..1.1...                     DOWN ROTATE
215 L1327:  11.1111111  ->  L1337          GO TO RTN16
216 L1330:  ..........                     NO OPERATION
217 L1331:  1...1.111.             ROT1 : B EXCHANGE C[W]
218 L1332:  11..1.1...                     DOWN ROTATE
219 L1333:  .11.1.1...                     STACK -> A
220 L1334:  1...1.111.                     B EXCHANGE C[W]
221 L1335:  .1..1.1...                     C -> STACK
222 L1336:  ..1...111.                     B -> C[W]
223 L1337:  1...1.1...             RTN16 : DISPLAY OFF
224 L1340:  1111.1..11  ->  L1364          GO TO RTN9
225 L1341:  .1...1.1..             RTN8 : IF S4 # 1
226 L1342:  ...1...111  ->  L1021                T
227 L1343:  .11..1....  ->  L3344  *****   RETR3 : SELECT ROM 3
228 L1344:  111.11.11.              DIV : A EXCHANGE C[MS]
229 L1345:  111..11111  ->  L1347          GO TO DIV12
230 L1346:  .1...1....  ->  L2347  *****   MPY : SELECT ROM 2
231 L1347:  .1.1..1.1.             DIV12 : A - C -> C[X]
232 L1350:  .1...1....  ->  L2351  *****         SELECT ROM 2
233 L1351:  .11.1.1...             MS12 : STACK -> A
234 L1352:  11.11..1.1  ->  L1331          JSB ROT1
235 L1353:  .1..1.1...                     C -> STACK
```

```
236 L1354:  111.1.111.
237 L1355:  111..1...1  ->  L1344          A EXCHANGE C[W]
238 L1356:  11..1.1...                     JSB DIV
239 L1357:  111..11..1  ->  L1346          DOWN ROTATE
240 L1360:  .11.1.1...                     JSB MPY
241 L1361:  .11.1.11.1  ->  L1153          STACK -> A
242 L1362:  11.11..1.1  ->  L1331          JSB SUB
243 L1363:  11...11.11  ->  L1306          JSB ROT1
244 L1364:  .111.1.1..                     GO TO MS14
245 L1365:  ...111.111  ->  L1035  RTN9  : IF S7 # 1
246 L1366:  111....111  ->  L1341              THEN GO TO RET11
247 L1367:  111.1.111.                     GO TO RTN8
248 L1370:  ...1..1.1.             ADD2  : A EXCHANGE C[W]
249 L1371:  .1111.1.11  ->  L1172  ADD5  : IF A >= C[X]
250 L1372:  11111.1.1.                         THEN GO TO ADD7
251 L1373:  .111.11111  ->  L1167          A + 1 -> A[X]
252 L1374:  ...11..11.                     IF NO CARRY GO TO ADD3
253 L1375:  ....1.1.11  ->  L1012  SQR   : IF C[M] >= 1
254 L1376:  ....11....                         THEN GO TO SQR1
                                           RETURN
```

ROM 2

0	L2000:	.....1....	->	L0001	*****	ERR21	: SELECT ROM 0
1	L2001:	111...111.				PMU23	: A + B -> A[W]
2	L2002:	.1.111111.				PMU24	: C - 1 -> C[S]
3	L2003:	111	->	L2001			IF NO CARRY GO TO PMU23
4	L2004:	111.1.111.					A EXCHANGE C[W]
5	L2005:	.1...1.11.					SHIFT LEFT A[MS]
6	L2006:	111.1.111.					A EXCHANGE C[W]
7	L2007:	..1111..11	->	L2074			GO TO PQO23
8	L2010:	.11.1.1...				XTY21	: STACK -> A
9	L2011:	.1..1.1...					C -> STACK
10	L2012:	111.1.111.					A EXCHANGE C[W]
11	L2013:	1.111.111.				LN22	: 0 -> A[W]
12	L2014:	.11....1..					1 -> S6
13	L2015:	11.1...11.					A - C -> A[M]
14	L2016:	11	->	L2000			IF NO CARRY GO TO ERR21
15	L2017:	1.11..111.					SHIFT RIGHT A[W]
16	L2020:	.1.111111.					C - 1 -> C[S]
17	L2021:	11	->	L2000			IF NO CARRY GO TO ERR21
18	L2022:	.11111111.				LN25	: C + 1 -> C[S]
19	L2023:	.1..1.111.				LN26	: A -> B[W]
20	L2024:	...1.11.11	->	L2026			GO TO ECA22
21	L2025:	1.11.1..1.				ECA21	: SHIFT RIGHT A[WP]
22	L2026:	11.111111.				ECA22	: A - 1 -> A[S]
23	L2027:	...1.1.111	->	L2025			IF NO CARRY GO TO ECA21
24	L2030:	1.1111111.					0 -> A[S]
25	L2031:	111...111.					A + B -> A[W]
26	L2032:	.11..1.1..					IF S6 # 1
27	L2033:	.1.11.1.11	->	L2132			THEN GO TO EXP29
28	L2034:	11.11...1.					A - 1 -> A[P]
29	L2035:	...1..1.11	->	L2022			IF NO CARRY GO TO LN25
30	L2036:	11..11..1.					A EXCHANGE B[WP]
31	L2037:	.1...1..1.					SHIFT LEFT A[WP]
32	L2040:	111..1111.					A + B -> A[S]
33	L2041:	111....111	->	L2341			IF NO CARRY GO TO LN24
34	L2042:	.111..11..					7 -> P
35	L2043:	..1111..11	->	L2074			GO TO PQO23
36	L2044:	11111.1.1.				PRE23	: A + 1 -> A[X]
37	L2045:	1..1111.1.				PRE29	: IF A[XS] >= 1
38	L2046:	11.1111111	->	L2337			THEN GO TO PRE27
39	L2047:	11...1.11.				PRE24	: A - B -> A[MS]
40	L2050:	..1..1..11	->	L2044			IF NO CARRY GO TO PRE23
41	L2051:	111..1.11.					A + B -> A[MS]
42	L2052:	.1....111.					SHIFT LEFT A[W]
43	L2053:	.1.11.1.1.					C - 1 -> C[X]
44	L2054:	..1..1.111	->	L2045			IF NO CARRY GO TO PRE29
45	L2055:	1.11..111.				PRE25	: SHIFT RIGHT A[W]
46	L2056:	..11.1..1.					0 -> C[WP]
47	L2057:	111.1.1.1.					A EXCHANGE C[X]
48	L2060:	.11.11111.				PRE26	: IF C[S] = 0
49	L2061:	..11.1.111	->	L2065			THEN GO TO PRE28
50	L2062:	11..1.111.					A EXCHANGE B[W]
51	L2063:	11....111.					A - B -> A[W]
52	L2064:	..111.111.					0 - C - 1 -> C[W]
53	L2065:	1.11..111.				PRE28	: SHIFT RIGHT A[W]
54	L2066:	1...1..1..					0 -> S8
55	L2067:	..1111..11	->	L2074			GO TO PQO23

```
56  L2070:   .11111111.
57  L2071:   11....111.
58  L2072:   ..111...11  ->  L2070
59  L2073:   111..111.
60  L2074:   1...1.111.
61  L2075:   ..11..111.
62  L2076:   .1.11..11.
63  L2077:   .1...11...
64  L2100:   .1111..11.
65  L2101:   1..1..111.
66  L2102:   .1.11.11..
67  L2103:   11.1...111  ->  L2321
68  L2104:   .11...11..
69  L2105:   1.1111..1.
70  L2106:   11.1..11..
71  L2107:   1...1.111.
72  L2110:   111.1.111.
73  L2111:   .11..11...
74  L2112:   .11....111  ->  L2141
75  L2113:   1.111.11..
76  L2114:   1.1..11.11  ->  L2246
77  L2115:   .11..11...
78  L2116:   1..1.11...
79  L2117:   ..11.11...
80  L2120:   ...1.11...
81  L2121:   .1...11...
82  L2122:   .111.11...
83  L2123:   ...1.11...
84  L2124:   1....11...
85  L2125:   .....11...
86  L2126:   .1.1.11...
87  L2127:   .11..11...
88  L2130:   1.11..11..
89  L2131:   11.1.11111  ->  L2327
90  L2132:   11111...1.
91  L2133:   .1..1.111.
92  L2134:   .1.111111.
93  L2135:   ...1.11.11  ->  L2026
94  L2136:   1.11.1..1.
95  L2137:   111.1.111.
96  L2140:   .1...1.11.
97  L2141:   111.1.111.
98  L2142:   11.111111.
99  L2143:   .1.11.1111  ->  L2133
100 L2144:   11..1.111.
101 L2145:   11111...1.
102 L2146:   1...1..111  ->  L2211
103 L2147:   1..1.1.11.
104 L2150:   .1....111.
105 L2151:   ..111..111  ->  L2071
106 L2152:   1..11.11..
107 L2153:   .111.1..11  ->  L2164
108 L2154:   .111..11..
109 L2155:   ..11.11...
110 L2156:   ..11.11...
111 L2157:   .....11...
112 L2160:   1....11...
113 L2161:   .1.1.11...
114 L2162:   1..1..11..
115 L2163:   11.1.11111  ->  L2327
```

```
PQO15   :  C + 1 -> C[S]
PQO16   :  A - B -> A[W]
           IF NO CARRY GO TO PQO15
           A + B -> A[W]
PQO23   :  B EXCHANGE C[W]
           0 -> C[W]
           C - 1 -> C[M]
           LOAD CONSTANT 4
           C + 1 -> C[M]
PQO24   :  SHIFT RIGHT C[W]
           IF P # 5
                THEN GO TO EXP35
           6 -> P
           0 -> A[WP]
           13 -> P
           B EXCHANGE C[W]
           A EXCHANGE C[W]
           LOAD CONSTANT 6
           GO TO EXP23
EXP32   :  IF P # 11
                THEN GO TO EXP31
LNC2    :  LOAD CONSTANT 6
           LOAD CONSTANT 9
           LOAD CONSTANT 3
           LOAD CONSTANT 1
           LOAD CONSTANT 4
           LOAD CONSTANT 7
           LOAD CONSTANT 1
           LOAD CONSTANT 8
           LOAD CONSTANT 0
           LOAD CONSTANT 5
           LOAD CONSTANT 6
           11 -> P
           GO TO LN35
EXP29   :  A + 1 -> A[P]
EXP22   :  A -> B[W]
           C - 1 -> C[S]
           IF NO CARRY GO TO ECA22
           SHIFT RIGHT A[WP]
           A EXCHANGE C[W]
           SHIFT LEFT A[MS]
EXP23   :  A EXCHANGE C[W]
           A - 1 -> A[S]
           IF NO CARRY GO TO EXP22
           A EXCHANGE B[W]
           A + 1 -> A[P]
           IF NO CARRY GO TO NRM21
PQO21   :  SHIFT RIGHT C[MS]
           SHIFT LEFT A[W]
           GO TO PQO16
EXP34   :  IF P # 9
                THEN GO TO EXP33
LNCD2   :  7 -> P
           LOAD CONSTANT 3
           LOAD CONSTANT 3
           LOAD CONSTANT 0
           LOAD CONSTANT 8
           LOAD CONSTANT 5
           9 -> P
           GO TO LN35
```

```
116 L2164:  1.1.1.11..
117 L2165:  .1..1.1111  ->  L2113
118 L2166:  1..1..11..
119 L2167:  ..11.11...
120 L2170:  ...1.11...
121 L2171:  .....11...
122 L2172:  ...1.11...
123 L2173:  .111.11...
124 L2174:  1..1.11...
125 L2175:  1....11...
126 L2176:  ...1.11...
127 L2177:  1.1...11..
128 L2200:  11.1.11111  ->  L2327
129 L2201:  111..1.11.
130 L2202:  .1.11...1.
131 L2203:  1.....111  ->  L2201
132 L2204:  1.11..111.
133 L2205:  ....1111..
134 L2206:  11.11.11..
135 L2207:  1.....1.11  ->  L2202
136 L2210:  .1111.1.1.
137 L2211:  1.1111111.
138 L2212:  11....11..
139 L2213:  1..11...1.
140 L2214:  1..1..1.11  ->  L2222
141 L2215:  .1....111.
142 L2216:  .1.11.1.1.
143 L2217:  1..11.111.
144 L2220:  1...1.1111  ->  L2213
145 L2221:  ..11..111.
146 L2222:  111.1.1.1.
147 L2223:  1.1.111.1.
148 L2224:  1..1.11.11  ->  L2226
149 L2225:  111111.11.
150 L2226:  111.1.1.1.
151 L2227:  1..111111.
152 L2230:  1....1..11  ->  L2204
153 L2231:  111.1..11.
154 L2232:  .11...111.
155 L2233:  1...1.1...
156 L2234:  11.1111.11  ->  L2336
157 L2235:  .11..1.1...
158 L2236:  1.1..11.11  ->  L2246
159 L2237:  .11.1..1...
160 L2240:  1..1.1.1..
161 L2241:  111..1.111  ->  L2345
162 L2242:  ..11..111.
163 L2243:  .....111..
164 L2244:  .1.1.11...
165 L2245:  111..11111  ->  L2347
166 L2246:  11..1.11..
167 L2247:  11.1.11111  ->  L2327
168 L2250:  ..11..111.
169 L2251:  ..1..11...
170 L2252:  ..11.11...
171 L2253:  .....11...
172 L2254:  ..1..11...
173 L2255:  .1.1.11...
174 L2256:  1....11...
175 L2257:  .1.1.11...
```

```
EXP33   :  IF P # 10
               THEN GO TO EXP32
LNCD1   :  9 -> P
           LOAD CONSTANT 3
           LOAD CONSTANT 1
           LOAD CONSTANT 0
           LOAD CONSTANT 1
           LOAD CONSTANT 7
           LOAD CONSTANT 9
           LOAD CONSTANT 8
           LOAD CONSTANT 1
           10 -> P
           GO TO LN35
MPY26   :  A + B -> A[MS]
MPY27   :  C - 1 -> C[P]
           IF NO CARRY GO TO MPY26
MPY28   :  SHIFT RIGHT A[W]
           P + 1 -> P
           IF P # 13
               THEN GO TO MPY27
           C + 1 -> C[X]
NRM21   :  0 -> A[S]
           12 -> P
NRM23   :  IF A[P] >= 1
               THEN GO TO NRM24
           SHIFT LEFT A[W]
           C - 1 -> C[X]
           IF A[W] >= 1
               THEN GO TO NRM23
           0 -> C[W]
NRM24   :  A EXCHANGE C[X]
           C + C -> C[XS]
           IF NO CARRY GO TO NRM29
           A + 1 -> A[MS]
NRM29   :  A EXCHANGE C[X]
           IF A[S] >= 1
               THEN GO TO MPY28
           A EXCHANGE C[M]
NRM25   :  C -> A[W]
           IF S8 # 1
               THEN GO TO NRM26
           IF S6 # 1
               THEN GO TO EXP31
           0 -> S6
           IF S9 # 1
               THEN GO TO XTY32
           0 -> C[W]
           P - 1 -> P
           LOAD CONSTANT 5
           GO TO MPY21
EXP31   :  IF P # 12
               THEN GO TO LN35
LNC10   :  0 -> C[W]
           LOAD CONSTANT 2
           LOAD CONSTANT 3
           LOAD CONSTANT 0
           LOAD CONSTANT 2
           LOAD CONSTANT 5
           LOAD CONSTANT 8
           LOAD CONSTANT 5
```

```
176 L2260:  .....11...
177 L2261:  1..1.11...
178 L2262:  ..11.11...
179 L2263:  11....11..
180 L2264:  111.1.111.
181 L2265:  .11..1.1..
182 L2266:  11..1...11  ->  L2310
183 L2267:  .1.1..111.
184 L2270:  .....11.1.
185 L2271:  1.111.1111  ->  L2273
186 L2272:  .1.1..111.
187 L2273:  11..1.111.
188 L2274:  .....111..
189 L2275:  .1....111.
190 L2276:  ...11.11..
191 L2277:  1.1111..11  ->  L2274
192 L2300:  111.1.111.
193 L2301:  .11.11111.
194 L2302:  11...1..11  ->  L2304
195 L2303:  ..111..11.
196 L2304:  .1111.1.1.
197 L2305:  ....1.1...
198 L2306:  1.11..11..
199 L2307:  1.....1.11  ->  L2202
200 L2310:  .1..1.111.
201 L2311:  .11....11.
202 L2312:  1.1.111.1.
203 L2313:  ..1..11111  ->  L2047
204 L2314:  .111111.1.
205 L2315:  1.11..111.
206 L2316:  .1111.1.1.
207 L2317:  11..11.111  ->  L2315
208 L2320:  ..11....11  ->  L2060
209 L2321:  1...1.11..
210 L2322:  .11.1.1.11  ->  L2152
211 L2323:  .1.1..11..
212 L2324:  ..11.11...
213 L2325:  ..11.11...
214 L2326:  1.....11..
215 L2327:  1...1.111.
216 L2330:  .11..1.1..
217 L2331:  .11..11111  ->  L2147
218 L2332:  1.11..111.
219 L2333:  ....1111..
220 L2334:  ....1111..
221 L2335:  ......1.11  ->  L2002
222 L2336:  ..1..1....  ->  L1337   *****  NRM26  :  SELECT ROM 1
223 L2337:  11111..11.                     PRE27  :  A + 1 -> A[M]
224 L2340:  ..1.11.111  ->  L2055                    IF NO CARRY GO TO PRE25
225 L2341:  11..11111.                     LN24   :  A EXCHANGE B[S]
226 L2342:  1..1.1.11.                               SHIFT RIGHT C[MS]
227 L2343:  111111111.                               A + 1 -> A[S]
228 L2344:  ...1..1111  ->  L2023                    IF NO CARRY GO TO LN26
229 L2345:  11..1.1...                     XTY32  :  DOWN ROTATE
230 L2346:  .1..1.1...                               C -> STACK
231 L2347:  ..11..11..                     MPY21  :  3 -> P
232 L2350:  .111..1.1.                     MPY22  :  A + C -> C[X]
233 L2351:  .1.1.1111.                     DIV21  :  A - C -> C[S]
234 L2352:  111.11..11  ->  L2354                    IF NO CARRY GO TO DIV22
235 L2353:  ..1.11111.                               0 - C -> C[S]

                                                     LOAD CONSTANT 0
                                                     LOAD CONSTANT 9
                                                     LOAD CONSTANT 3
                                                     12 -> P
                                                     A EXCHANGE C[W]
                                                     IF S6 # 1
                                                          THEN GO TO PRE21
                                                     A - C -> C[W]
                                                     IF B[XS] = 0
                                                          THEN GO TO LN27
                                                     A - C -> C[W]
                                           LN27   :  A EXCHANGE B[W]
                                           LN28   :  P - 1 -> P
                                                     SHIFT LEFT A[W]
                                                     IF P # 1
                                                          THEN GO TO LN28
                                                     A EXCHANGE C[W]
                                                     IF C[S] = 0
                                                          THEN GO TO LN29
                                                     0 - C - 1 -> C[M]
                                           LN29   :  C + 1 -> C[X]
                                                     DISPLAY TOGGLE
                                                     11 -> P
                                                     GO TO MPY27
                                           PRE21  :  A -> B[W]
                                                     C -> A[M]
                                                     C + C -> C[XS]
                                                     IF NO CARRY GO TO PRE24
                                                     C + 1 -> C[XS]
                                           PRE22  :  SHIFT RIGHT A[W]
                                                     C + 1 -> C[X]
                                                     IF NO CARRY GO TO PRE22
                                                     GO TO PRE26
                                           EXP35  :  IF P # 8
                                                          THEN GO TO EXP34
                                           LNCD3  :  5 -> P
                                                     LOAD CONSTANT 3
                                                     LOAD CONSTANT 3
                                                     8 -> P
                                           LN35   :  B EXCHANGE C[W]
                                                     IF S6 # 1
                                                          THEN GO TO PQO21
                                                     SHIFT RIGHT A[W]
                                                     P + 1 -> P
                                                     P + 1 -> P
                                                     GO TO PMU24
```

```
236 L2354:  11..1.111.
237 L2355:  1.111.111.
238 L2356:  .1...11111.
239 L2357:  11..1.11..
240 L2360:  1.....1.11  ->  L2202
241 L2361:  ........11.
242 L2362:  ..........11  ->  L2000
243 L2363:  111.11..1.
244 L2364:  1111.11.11  ->  L2366
245 L2365:  .1111...1.
246 L2366:  11....1.11.
247 L2367:  1111.1.111  ->  L2365
248 L2370:  111..1.11.
249 L2371:  .1...1.11.
250 L2372:  .....111..
251 L2373:  ....1.11..
252 L2374:  1111.11.11  ->  L2366
253 L2375:  .11..1111.
254 L2376:  111.1.111.
255 L2377:  1...1..111  ->  L2211
```

```
DIV22  :  A EXCHANGE B[W]
          Ø -> A[W]
          A -> B[S]
          IF P # 12
               THEN GO TO MPY27
          IF B[M] = Ø
               THEN GO TO ERR21
DIV23  :  A EXCHANGE C[WP]
          GO TO DIV15
DIV14  :  C + 1 -> C[P]
DIV15  :  A - B -> A[MS]
          IF NO CARRY GO TO DIV14
          A + B -> A[MS]
          SHIFT LEFT A[MS]
DIV16  :  P - 1 -> P
          IF P # Ø
               THEN GO TO DIV15
          C -> A[S]
          A EXCHANGE C[W]
          GO TO NRM21
```

ROM 3

```
 0  L3000:  .1...11..1  ->  L3106
 1  L3001:  111.1.111.
 2  L3002:  111...11.1  ->  L3343
 3  L3003:  ...1.1..11  ->  L3024
 4  L3004:  1.....1..
 5  L3005:  ..1..1....  ->  L1006
 6  L3006:  1...1..1..
 7  L3007:  ....1..111  ->  L3011
 8  L3010:  1.....1..
 9  L3011:  ..1..1....  ->  L1012
10  L3012:  111..1.1.1  ->  L3345
11  L3013:  .1...11..1  ->  L3106
12  L3014:  1.11.1.1..
13  L3015:  ..1111.111  ->  L3075
14  L3016:  .11.1.11.1  ->  L3153
15  L3017:  .....11..1  ->  L3006
16  L3020:  11..1.1...
17  L3021:  .....11..1  ->  L3006
18  L3022:  .1...11..1  ->  L3106
19  L3023:  .1.11..111  ->  L3131
20  L3024:  .11.1.1...
21  L3025:  .1..1.1...
22  L3026:  11.11..1.1  ->  L3331
23  L3027:  .1.1111.11  ->  L3136
24  L3030:  1.111..1..
25  L3031:  11..11..11  ->  L3314
26  L3032:  .1...1..11  ->  L3104
27  L3033:  11..1.1.11  ->  L3312
28  L3034:  .11.11.111  ->  L3155
29  L3035:  ..........
30  L3036:  .11...111.
31  L3037:  11..1.1...
32  L3040:  1111.1.111  ->  L3365
33  L3041:  .1...1.1..
34  L3042:  1111.1..11  ->  L3364
35  L3043:  ..11.1....
36  L3044:  ..........
37  L3045:  11..1.1...
38  L3046:  ..1.1.1...
39  L3047:  11..1.1...
40  L3050:  .1..1.1...
41  L3051:  .1....11.1  ->  L3103
42  L3052:  .11.1.11.1  ->  L3153
43  L3053:  .11.1.1...
44  L3054:  .1..1.1...
45  L3055:  111.1.111.
46  L3056:  .1...11..1  ->  L3106
47  L3057:  .11.1.11.1  ->  L3153
48  L3060:  .....1...1  ->  L3004
49  L3061:  11..1.1...
50  L3062:  .1..1.1...
51  L3063:  11..1.1...
52  L3064:  11..1.1...
53  L3065:  111.1.111.
54  L3066:  111...11.1  ->  L3343
55  L3067:  1.1.1.1...
```

```
        FVR47  :  JSB ONE
                  A EXCHANGE C[W]
                  JSB DIV
                  GO TO FVR48
        XTY    :  1 -> S8
*****           SELECT ROM 1
        LN     :  0 -> S8
                  GO TO SQR1
        SQR    :  1 -> S8
***** SQR1     :  SELECT ROM 1
        N46    :  JSB MPY
                  JSB ONE
                  IF S11 # 1
                        THEN GO TO N42
                  JSB ADD
        N44    :  JSB LN
                  DOWN ROTATE
                  JSB LN
                  JSB ONE
                  GO TO N48
        FVR48  :  STACK -> A
                  C -> STACK
                  JSB S12
                  GO TO P47
        FV40   :  0 -> S11
                  GO TO FV46
        PV40   :  GO TO PV41
        PMT40  :  GO TO PMT42
        ROR40  :  GO TO FVR
                  NO OPERATION
        N40    :  C -> A[W]
                  DOWN ROTATE
                  GO TO N41
        N5     :  IF S4 # 1
                        THEN GO TO SELR4
        TKRR3  :  KEYS -> ROM ADDRESS
                  NO OPERATION
        CASH1  :  DOWN ROTATE
                  C EXCHANGE M
                  DOWN ROTATE
                  C -> STACK
                  JSB R100
                  JSB ADD
                  STACK -> A
                  C -> STACK
                  A EXCHANGE C[W]
                  JSB ONE
                  JSB ADD
                  JSB XTY
                  DOWN ROTATE
                  C -> STACK
                  DOWN ROTATE
                  DOWN ROTATE
                  A EXCHANGE C[W]
                  JSB DIV
                  M -> C
```

```
56 L3070: .11.1.11.1 -> L3153          JSB ADD
57 L3071: 1.1.1..1..          R13   :  Ø -> S1Ø
58 L3072: 1.111..1..                   Ø -> S11
59 L3073: .1..11.111 -> L3115          GO TO R14
60 L3074: ..........                   NO OPERATION
61 L3075: 111.1.111.          N42   :  A EXCHANGE C[W]
62 L3076: .11.1.1..1 -> L3152          JSB SUB
63 L3077: 11..1.111.                   A EXCHANGE B[W]
64 L3100: 111...11.1 -> L3343          JSB DIV
65 L3101: ....111111 -> L3017          GO TO N44
66 L3102: ..........                   NO OPERATION
67 L3103: ..1..1.... -> L1104  *****  R100  :  SELECT ROM 1
68 L3104: 1.111..1..          PV41  :  Ø -> S11
69 L3105: .1..1...11 -> L3110          GO TO PV42
70 L3106: ..1..1.... -> L1107  *****  ONE   :  SELECT ROM 1
71 L3107: 1.11...1..          PV46  :  1 -> S11
72 L3110: 11.1...1.1 -> L3321  PV42  :  JSB CSN
73 L3111: .1....11.1 -> L3103  PV49  :  JSB R100
74 L3112: .11.1.11.1 -> L3153          JSB ADD
75 L3113: 11.11....1 -> L3330          JSB ROT1
76 L3114: .1..111.11 -> L3116          GO TO PV48
77 L3115: .....1.... -> L0116  *****  R14   :  SELECT ROM Ø
78 L3116: .....1...1 -> L3004  PV48  :  JSB XTY
79 L3117: .1...11..1 -> L3106          JSB ONE
80 L3120: 111.1.111.                   A EXCHANGE C[W]
81 L3121: 1.1..1.1..          PV43  :  IF S1Ø # 1
82 L3122: .1.111..11 -> L3134                THEN GO TO PV44
83 L3123: .11.1.1..1 -> L3152          JSB SUB
84 L3124: 11..1.1...                   DOWN ROTATE
85 L3125: 11..1.1...                   DOWN ROTATE
86 L3126: 11..1.1...                   DOWN ROTATE
87 L3127: 1.11.1.1..                   IF S11 # 1
88 L3130: .1.11.1.11 -> L3132                THEN GO TO PV45
89 L3131: 111.1.111.          N48   :  A EXCHANGE C[W]
90 L3132: 111...11.1 -> L3343  PV45  :  JSB DIV
91 L3133: .11.1.1...                   STACK -> A
92 L3134: .11.1.1...          PV44  :  STACK -> A
93 L3135: .11.1.1...                   STACK -> A
94 L3136: 111..1.1.1 -> L3345  P47   :  JSB MPY
95 L3137: ..111..111 -> L3071          GO TO R13
96 L3140: 1.1..1.1..          CASH  :  IF S1Ø # 1
97 L3141: ..1..1.111 -> L3045                THEN GO TO CASH1
98 L3142: .1..1..1..                   Ø -> S4
99 L3143: 1....1.... -> L4144  *****          SELECT ROM 4
100 L3144: .1111.1.1.          FVR49 :  C + 1 -> C[X]
101 L3145: 111...11.1 -> L3343         JSB DIV
102 L3146: .1...11..1 -> L3106         JSB ONE
103 L3147: .11.1.11.1 -> L3153         JSB ADD
104 L3150: .11.1.1...                  STACK -> A
105 L3151: .111.11111 -> L3167         GO TO FVR43
106 L3152: ..1..1.... -> L1153  *****  SUB   :  SELECT ROM 1
107 L3153: ..1..1.... -> L1154  *****  ADD   :  SELECT ROM 1
108 L3154: ..1..1.... -> L1155  *****  ADD1  :  SELECT ROM 1
109 L3155: 1.11.1.1..          FVR   :  IF S11 # 1
110 L3156: 111.....11 -> L3340               THEN GO TO FV42
111 L3157: 1.111..1..                  Ø -> S11
112 L3160: 1.1..1.1..                  IF S1Ø # 1
113 L3161: 1.111.1111 -> L3273               THEN GO TO FVR1
114 L3162: 11.1...1.1 -> L3321         FVR3  :  JSB CSN
115 L3163: ..1111111.                  Ø - C - 1 -> C[S]
```

```
116  L3164:   .1..1.1...
117  L3165:   .11.1.1...
118  L3166:   11..1.1...
119  L3167:   111...11.1  ->  L3343
120  L3170:   ..1.1.1...
121  L3171:   11..1.1...
122  L3172:   .1..1.1...
123  L3173:   .1...11..1  ->  L3106
124  L3174:   .11.1.11.1  ->  L3153
125  L3175:   11..1.111.
126  L3176:   111..1.1.1  ->  L3345
127  L3177:   ..1.1.1...
128  L3200:   .11.1.1...
129  L3201:   .1..1.1...
130  L3202:   11.1...1.1  ->  L3321
131  L3203:   11..1.1...
132  L3204:   .11.1.1..1  ->  L3152
133  L3205:   .11.1.11.1  ->  L3153
134  L3206:   ..1.1.1...
135  L3207:   111...11.1  ->  L3343
136  L3210:   ..1.1.1...
137  L3211:   11..1.1...
138  L3212:   ..1.1.1...
139  L3213:   .11.1.1...
140  L3214:   .1...11..1  ->  L3106
141  L3215:   .11.1.11.1  ->  L3153
142  L3216:   .1..1.1...
143  L3217:   .1..1.1...
144  L3220:   ..1...111.
145  L3221:   ..1.1.1...
146  L3222:   .....1...1  ->  L3004
147  L3223:   11..1.1...
148  L3224:   .1..1.1...
149  L3225:   111..1.1.1  ->  L3345
150  L3226:   ..1...111.
151  L3227:   11..1.1...
152  L3230:   11..1.1...
153  L3231:   111...11.1  ->  L3343
154  L3232:   11..1.1...
155  L3233:   11..1.1...
156  L3234:   .1...11..1  ->  L3106
157  L3235:   .11.1.1..1  ->  L3152
158  L3236:   1.1.1.1...
159  L3237:   111...11.1  ->  L3343
160  L3240:   11..1.1...
161  L3241:   11..1.1...
162  L3242:   .11.1.1..1  ->  L3152
163  L3243:   .11.1.1...
164  L3244:   .1..1.1...
165  L3245:   1...1.111.
166  L3246:   .11.1.11.1  ->  L3153
167  L3247:   11..1.1...
168  L3250:   1...1.111.
169  L3251:   11..1.1...
170  L3252:   1...1.111.
171  L3253:   111...11.1  ->  L3343
172  L3254:   1.1.1.1...
173  L3255:   111..1.1.1  ->  L3345
174  L3256:   ..1.1.1...
175  L3257:   .11.1.11.1  ->  L3153
```

```
FVR2   :  C -> STACK
          STACK -> A
          DOWN ROTATE
FVR43  :  JSB DIV
          C EXCHANGE M
          DOWN ROTATE
          C -> STACK
          JSB ONE
          JSB ADD
          A EXCHANGE B[W]
          JSB MPY
          C EXCHANGE M
          STACK -> A
          C -> STACK
          JSB CSN
          DOWN ROTATE
          JSB SUB
          JSB ADD
          C EXCHANGE M
          JSB DIV
          C EXCHANGE M
FVR44  :  DOWN ROTATE
          C EXCHANGE M
          STACK -> A
          JSB ONE
          JSB ADD
          C -> STACK
          C -> STACK
          B -> C[W]
          C EXCHANGE M
          JSB XTY
          DOWN ROTATE
          C -> STACK
          JSB MPY
          B -> C[W]
          DOWN ROTATE
          DOWN ROTATE
          JSB DIV
          DOWN ROTATE
          DOWN ROTATE
          JSB ONE
          JSB SUB
          M -> C
          JSB DIV
          DOWN ROTATE
          DOWN ROTATE
          JSB SUB
          STACK -> A
          C -> STACK
          B EXCHANGE C[W]
          JSB ADD
          DOWN ROTATE
          B EXCHANGE C[W]
          DOWN ROTATE
          B EXCHANGE C[W]
          JSB DIV
          M -> C
          JSB MPY
          C EXCHANGE M
          JSB ADD
```

```
176 L3260:  ..1.1.1...                          C EXCHANGE M
177 L3261:  .11...111.                          C -> A[W]
178 L3262:  111.11...1  ->  L3354               JSB TEN6
179 L3263:  1..1111.1.                          IF A[XS] >= 1
180 L3264:  11.1..1.11  ->  L3322                   THEN GO TO FVR46
181 L3265:  1...1..111  ->  L3211               GO TO FVR44
182 L3266:  111..1.1.1  ->  L3345   FVR9    :   JSB MPY
183 L3267:  11.11..1.1  ->  L3331               JSB S12
184 L3270:  .1111.1.1.                          C + 1 -> C[X]
185 L3271:  1.11...1..                          1 -> S11
186 L3272:  .11..1..11  ->  L3144               GO TO FVR49
187 L3273:  .11.1.1...          FVR1   :        STACK -> A
188 L3274:  111.1.111.                          A EXCHANGE C[W]
189 L3275:  111...11.1  ->  L3343               JSB DIV
190 L3276:  .11.1.1...                          STACK -> A
191 L3277:  .1..1.1...                          C -> STACK
192 L3300:  111.1.111.                          A EXCHANGE C[W]
193 L3301:  .1...11..1  ->  L3106               JSB ONE
194 L3302:  111.1.111.                          A EXCHANGE C[W]
195 L3303:  111...11.1  ->  L3343               JSB DIV
196 L3304:  .....1...1  ->  L3004               JSB XTY
197 L3305:  .1...11..1  ->  L3106               JSB ONE
198 L3306:  .11.1.1..1  ->  L3152               JSB SUB
199 L3307:  .1111.1.1.                          C + 1 -> C[X]
200 L3310:  .1111.1.1.                          C + 1 -> C[X]
201 L3311:  ..111..1.1  ->  L3071               JSB R13
202 L3312:  1.11.1.1..          PMT42  :        IF S11 # 1
203 L3313:  .1...11111  ->  L3107                   THEN GO TO PV46
204 L3314:  1.1..1.1..          FV46   :        IF S10 # 1
205 L3315:  .1..1..111  ->  L3111                   THEN GO TO PV49
206 L3316:  ..1111111.                          0 - C - 1 -> C[S]
207 L3317:  .1..1..1.1  ->  L3111               JSB PV49
208 L3320:  ..........                          NO OPERATION
209 L3321:  ..1..1....  ->  L1322   *****  CSN  :   SELECT ROM 1
210 L3322:  1.11.1.1..          FVR46  :        IF S11 # 1
211 L3323:  ..111..111  ->  L3071                   THEN GO TO R13
212 L3324:  11..1.1...                          DOWN ROTATE
213 L3325:  11..1.1...                          DOWN ROTATE
214 L3326:  11..1.1...                          DOWN ROTATE
215 L3327:  ........11  ->  L3000               GO TO FVR47
216 L3330:  ..1..1....  ->  L1331   *****  ROT1 :   SELECT ROM 1
217 L3331:  ..11..111.          S12    :        0 -> C[W]
218 L3332:  .1111...1.                          C + 1 -> C[P]
219 L3333:  .11111111.                          C + 1 -> C[S]
220 L3334:  1.1.11..1.                          C + C -> C[WP]
221 L3335:  1..1.1.11.                          SHIFT RIGHT C[MS]
222 L3336:  .1111.1.1.                          C + 1 -> C[X]
223 L3337:  ....11....                          RETURN
224 L3340:  1.1..1.1..          FV42   :        IF S10 # 1
225 L3341:  111..11.11  ->  L3346                   THEN GO TO FVR4
226 L3342:  .111.1..11  ->  L3164               GO TO FVR2
227 L3343:  ..1..1....  ->  L1344   *****  DIV  :   SELECT ROM 1
228 L3344:  ....11....          TRN16  :        RETURN
229 L3345:  ..1..1....  ->  L1346   *****  MPY  :   SELECT ROM 1
230 L3346:  111.1.111.          FVR4   :        A EXCHANGE C[W]
231 L3347:  11..1.1...                          DOWN ROTATE
232 L3350:  .1..1.1...                          C -> STACK
233 L3351:  .1..1.1...                          C -> STACK
234 L3352:  .1..1.1...                          C -> STACK
235 L3353:  1.11.11.11  ->  L3266               GO TO FVR9
```

```
236 L3354:  1.1.1.1...                          TEN6  : M -> C
237 L3355:  .1111.1.1.                                  C + 1 -> C[X]
238 L3356:  .1111.1.1.                                  C + 1 -> C[X]
239 L3357:  11111.1.1.                                  A + 1 -> A[X]
240 L3360:  11111.1.1.                                  A + 1 -> A[X]
241 L3361:  11111.1.1.                                  A + 1 -> A[X]
242 L3362:  11111.1.1.                                  A + 1 -> A[X]
243 L3363:  ....11....                                  RETURN
244 L3364:  1....1....  ->  L4365   *****  SELR4  : SELECT ROM 4
245 L3365:  111...11.1  ->  L3343          N41   : JSB DIV
246 L3366:  .1....11.1  ->  L3103                  JSB R100
247 L3367:  .11.1.11.1  ->  L3153                  JSB ADD
248 L3370:  11..1.1...                             DOWN ROTATE
249 L3371:  .11.1.1...                             STACK -> A
250 L3372:  .11.1.1...                             STACK -> A
251 L3373:  1...1.111.                             B EXCHANGE C[W]
252 L3374:  111.1.111.                             A EXCHANGE C[W]
253 L3375:  1.1..1.1..                             IF S10 # 1
254 L3376:  ....111111  ->  L3017                        THEN GO TO N44
255 L3377:  ....1.1.11  ->  L3012                  GO TO N46
```

ROM 4

```
 0  L4000:  .....1....  ->  L0001  *****  ERROR  :  SELECT ROM 0
 1  L4001:  ..........                             NO OPERATION
 2  L4002:  ..........                             NO OPERATION
 3  L4003:  .11..1....  ->  L3004  *****  XTY    :  SELECT ROM 3
 4  L4004:  ....11....                     RETUR1 :  RETURN
 5  L4005:  ....111..1  ->  L4016         SOD2   :  JSB DOWN3
 6  L4006:  .111...1..                             1 -> S7
 7  L4007:  .1..1..1..                             0 -> S4
 8  L4010:  .1...11..1  ->  L4106                  JSB ONE
 9  L4011:  .11.1.11.1  ->  L4153                  JSB ADD
10  L4012:  ..1....111  ->  L4041                  GO TO SOD3
11  L4013:  .11.1.1...                    STA1   :  STACK -> A
12  L4014:  .1..1.1...                             C -> STACK
13  L4015:  ....11....                             RETURN
14  L4016:  11..1.1...                     DOWN3  :  DOWN ROTATE
15  L4017:  11..1.1...                     DOWN2  :  DOWN ROTATE
16  L4020:  11..1.1...                             DOWN ROTATE
17  L4021:  ....11....                             RETURN
18  L4022:  .1.1.1.1..                             IF S5 # 1
19  L4023:  .....1..11  ->  L4004                       THEN GO TO RETUR1
20  L4024:  1.1..1....  ->  L5025  *****            SELECT ROM 5
21  L4025:  .111.1.1..                     SOD    :  IF S7 # 1
22  L4026:  .....1.111  ->  L4005                       THEN GO TO SOD2
23  L4027:  ...1111111  ->  L4037                   GO TO SOD6
24  L4030:  ........11  ->  L4000          FV     :  GO TO ERROR
25  L4031:  ..........                             NO OPERATION
26  L4032:  1.1..1....  ->  L5033  *****    PV     :  SELECT ROM 5
27  L4033:  1111.11.11  ->  L4366          PMT    :  GO TO DNOTE1
28  L4034:  .1.1...1..                     R      :  1 -> S5
29  L4035:  1.1..1....  ->  L5036  *****            SELECT ROM 5
30  L4036:  ........11  ->  L4000          N      :  GO TO ERROR
31  L4037:  .1...1.1..                     SOD6   :  IF S4 # 1
32  L4040:  111..11111  ->  L4347                       THEN GO TO SOD1
33  L4041:  11..1.1...                     SOD3   :  DOWN ROTATE
34  L4042:  .1..1..1..                     SOD5   :  0 -> S4
35  L4043:  .11.1.1...                             STACK -> A
36  L4044:  11..1.1...                             DOWN ROTATE
37  L4045:  .11...111.                             C -> A[W]
38  L4046:  ....1111.1  ->  L4017                  JSB DOWN2
39  L4047:  .11.1.1..1  ->  L4152                  JSB SUB
40  L4050:  ....1.11.1  ->  L4013                  JSB STA1
41  L4051:  .1...11..1  ->  L4106                  JSB ONE
42  L4052:  .1.11.1.11  ->  L4132                  GO TO SOD4
43  L4053:  ...1.1.111  ->  L4025          DEPR   :  GO TO SOD
44  L4054:  .111.1.1..                     TRND1  :  IF S7 # 1
45  L4055:  ..11..1.11  ->  L4062                       THEN GO TO TRND5
46  L4056:  .1...1.1..                              IF S4 # 1
47  L4057:  .11.11.111  ->  L4155                       THEN GO TO TRND3
48  L4060:  .1..1..1..                              0 -> S4
49  L4061:  1..11..111  ->  L4231                   GO TO TRND8
50  L4062:  .111...1..                     TRND5  :  1 -> S7
51  L4063:  .1...1.1..                              IF S4 # 1
52  L4064:  .1...11111  ->  L4107                       THEN GO TO TRND4
53  L4065:  .1..1..1..                              0 -> S4
54  L4066:  11..1.1...                              DOWN ROTATE
55  L4067:  1..1.1.111  ->  L4225                   GO TO TRND2
```

```
 56 L4070:  .11..1....  ->  L3071  *****  R13     :  SELECT ROM 3
 57 L4071:  111.1.111.                    L360    :  A EXCHANGE C[W]
 58 L4072:  ..11..111.                            Ø -> C[W]
 59 L4073:  ..11.11...                            LOAD CONSTANT 3
 60 L4074:  .11..11...                            LOAD CONSTANT 6
 61 L4075:  .1111.1.1.                            C + 1 -> C[X]
 62 L4076:  .1111.1.1.                            C + 1 -> C[X]
 63 L4077:  ....11....                            RETURN
 64 L4100:  .11.1.1..1  ->  L4152         DNOTE4  :  JSB SUB
 65 L4101:  ....1.11.1  ->  L4013                 JSB STA1
 66 L4102:  1.1..1....  ->  L5103  *****          SELECT ROM 5
 67 L4103:  ..1..1....  ->  L1104  *****  R100    :  SELECT ROM 1
 68 L4104:  11..1.1...                    TRND6   :  DOWN ROTATE
 69 L4105:  ..111...11  ->  L4070                 GO TO R13
 70 L4106:  ..1..1....  ->  L1107  *****  ONE     :  SELECT ROM 1
 71 L4107:  .111...1..                    TRND4   :  1 -> S7
 72 L4110:  ....1.11.1  ->  L4013                 JSB STA1
 73 L4111:  111.1.111.                            A EXCHANGE C[W]
 74 L4112:  .1...11..1  ->  L4106                 JSB ONE
 75 L4113:  .11.1.11.1  ->  L4153                 JSB ADD
 76 L4114:  11..1.1...                            DOWN ROTATE
 77 L4115:  .1..1.1...                            C -> STACK
 78 L4116:  111..1.1.1  ->  L4345                 JSB MPY
 79 L4117:  11..1.1...                            DOWN ROTATE
 80 L4120:  1...1.111.                            B EXCHANGE C[W]
 81 L4121:  11..1.1...                            DOWN ROTATE
 82 L4122:  11..1.111.                    TRND9   :  A EXCHANGE B[W]
 83 L4123:  .11.1.11.1  ->  L4153                 JSB ADD
 84 L4124:  11..1.1...                            DOWN ROTATE
 85 L4125:  .11.1.1...                            STACK -> A
 86 L4126:  .11.1.11.1  ->  L4153                 JSB ADD
 87 L4127:  .1..1.1...                            C -> STACK
 88 L4130:  ....1111.1  ->  L4017                 JSB DOWN2
 89 L4131:  ..111...11  ->  L4070                 GO TO R13
 90 L4132:  .11.1.11.1  ->  L4153         SOD4    :  JSB ADD
 91 L4133:  1.1.1.1...                            M -> C
 92 L4134:  111..1.1.1  ->  L4345                 JSB MPY
 93 L4135:  .11.1.11.1  ->  L4153                 JSB ADD
 94 L4136:  ....1.11.1  ->  L4013                 JSB STA1
 95 L4137:  ..1...111.                            B -> C[W]
 96 L4140:  111..1.1.1  ->  L4345                 JSB MPY
 97 L4141:  ....1.11.1  ->  L4013                 JSB STA1
 98 L4142:  111.1.111.                            A EXCHANGE C[W]
 99 L4143:  ..111...11  ->  L4070                 GO TO R13
100 L4144:  ..1.1.1...                    INTER   :  C EXCHANGE M
101 L4145:  .1....11.1  ->  L4103                JSB R100
102 L4146:  1.1.1.1...                           M -> C
103 L4147:  111.1.111.                           A EXCHANGE C[W]
104 L4150:  ..1.1.1...                           C EXCHANGE M
105 L4151:  1.1...1.11  ->  L4242                GO TO INTER1
106 L4152:  ..1..1....  ->  L1153  *****  SUB     :  SELECT ROM 1
107 L4153:  ..1..1....  ->  L1154  *****  ADD     :  SELECT ROM 1
108 L4154:  ..1..1....  ->  L1155  *****  ADD1    :  SELECT ROM 1
109 L4155:  ....1.11.1  ->  L4013         TRND3   :  JSB STA1
110 L4156:  .1..1.1...                           C -> STACK
111 L4157:  111...11.1  ->  L4343                JSB DIV
112 L4160:  11..1.1...                           DOWN ROTATE
113 L4161:  .1...11..1  ->  L4106                JSB ONE
114 L4162:  .11.1.11.1  ->  L4153                JSB ADD
115 L4163:  ..1...111.                           B -> C[W]
```

```
116 L4164:  11..1.1...                          DOWN ROTATE
117 L4165:  111..1.1.1  ->  L4345               JSB MPY
118 L4166:  .11.1.1...                          STACK -> A
119 L4167:  111...11.1  ->  L4343               JSB DIV
120 L4170:  .11.1.11.1  ->  L4153               JSB ADD
121 L4171:  11..1.1...                          DOWN ROTATE
122 L4172:  .1..1.1...                          C -> STACK
123 L4173:  .11.1.1..1  ->  L4152               JSB SUB
124 L4174:  .11.1.11.1  ->  L4153               JSB ADD
125 L4175:  11..1.111.                          A EXCHANGE B[W]
126 L4176:  .11.1.11.1  ->  L4153               JSB ADD
127 L4177:  ....111..1  ->  L4016               JSB DOWN3
128 L4200:  .1...11..1  ->  L4106               JSB ONE
129 L4201:  .11.1.1..1  ->  L4152               JSB SUB
130 L4202:  .11.1.1...                          STACK -> A
131 L4203:  111...11.1  ->  L4343               JSB DIV
132 L4204:  .11.1.11.1  ->  L4153               JSB ADD
133 L4205:  11..1.1...                          DOWN ROTATE
134 L4206:  11..1.111.                          A EXCHANGE B[W]
135 L4207:  .11.1.1..1  ->  L4152               JSB SUB
136 L4210:  .11.1.1...                          STACK -> A
137 L4211:  ....1.11.1  ->  L4013               JSB STA1
138 L4212:  ..1...111.                          B -> C[W]
139 L4213:  111..1.1.1  ->  L4345               JSB MPY
140 L4214:  .11.1.1...                          STACK -> A
141 L4215:  .11.1.11.1  ->  L4153               JSB ADD
142 L4216:  ..1111111.                          0 - C - 1 -> C[S]
143 L4217:  ..1.1.1...                          C EXCHANGE M
144 L4220:  ..11..111.                          0 -> C[W]
145 L4221:  .1..1.1...                          C -> STACK
146 L4222:  1.1.1.1...                          M -> C
147 L4223:  .1..1.1...                          C -> STACK
148 L4224:  .1...1..11  ->  L4104               GO TO TRND6
149 L4225:  .1...11..1  ->  L4106   TRND2   :   JSB ONE
150 L4226:  .11.1.11.1  ->  L4153               JSB ADD
151 L4227:  .1..1.1...                          C -> STACK
152 L4230:  .1..1.1...                          C -> STACK
153 L4231:  .11.1.1...  TRND8   :   STACK -> A
154 L4232:  .11.1.1...                          STACK -> A
155 L4233:  .11...111.                          C -> A[W]
156 L4234:  ....1111.1  ->  L4017               JSB DOWN2
157 L4235:  111..1.1.1  ->  L4345               JSB MPY
158 L4236:  1.1.1.1...                          M -> C
159 L4237:  .11.1.11.1  ->  L4153               JSB ADD
160 L4240:  ....1.11.1  ->  L4013               JSB STA1
161 L4241:  .1...1..11  ->  L4104               GO TO TRND6
162 L4242:  1.1.1.1...  INTER1   :   M -> C
163 L4243:  111...11.1  ->  L4343               JSB DIV
164 L4244:  11..1.1...                          DOWN ROTATE
165 L4245:  .11.1.1...                          STACK -> A
166 L4246:  .11.1.1..1  ->  L4152               JSB SUB
167 L4247:  ....1.11.1  ->  L4013               JSB STA1
168 L4250:  ..1...111.                          B -> C[W]
169 L4251:  .11.1.1..1  ->  L4152               JSB SUB
170 L4252:  ..1.1.1...                          C EXCHANGE M
171 L4253:  .1...11..1  ->  L4106               JSB ONE
172 L4254:  .11.1.11.1  ->  L4153               JSB ADD
173 L4255:  .1..1.1...                          C -> STACK
174 L4256:  ..1.1.1...                          C EXCHANGE M
175 L4257:  ......11.1  ->  L4003               JSB XTY
```

```
176 L4260:  ..1.1.1...                                  C EXCHANGE M
177 L4261:  .1...11..1  ->  L4106                       JSB ONE
178 L4262:  .11.1.1..1  ->  L4152                       JSB SUB
179 L4263:  ....1.11.1  ->  L4013                       JSB STA1
180 L4264:  111..1.1.1  ->  L4345                       JSB MPY
181 L4265:  11..1.1...                                  DOWN ROTATE
182 L4266:  .1...11..1  ->  L4106                       JSB ONE
183 L4267:  .11.1.11.1  ->  L4153                       JSB ADD
184 L4270:  ....1.11.1  ->  L4013                       JSB STA1
185 L4271:  111.1.111.                                  A EXCHANGE C[W]
186 L4272:  ......11.1  ->  L4003                       JSB XTY
187 L4273:  .11.1.1...                                  STACK -> A
188 L4274:  ..1.1.1...                                  C EXCHANGE M
189 L4275:  .1...11..1  ->  L4106                       JSB ONE
190 L4276:  .11.1.1..1  ->  L4152                       JSB SUB
191 L4277:  1.1.1.1...                                  M -> C
192 L4300:  111..1.1.1  ->  L4345                       JSB MPY
193 L4301:  ..1.1.1...                                  C EXCHANGE M
194 L4302:  .1...11..1  ->  L4106                       JSB ONE
195 L4303:  .11.1.1..1  ->  L4152                       JSB SUB
196 L4304:  11..1.1...                                  DOWN ROTATE
197 L4305:  ..1111111.                                  0 - C - 1 -> C[S]
198 L4306:  .1..1.1...                                  C -> STACK
199 L4307:  111..1.1.1  ->  L4345                       JSB MPY
200 L4310:  11..1.1...                                  DOWN ROTATE
201 L4311:  .11.1.1...                                  STACK -> A
202 L4312:  .11.1.1...                                  STACK -> A
203 L4313:  ..1.1.1...                                  C EXCHANGE M
204 L4314:  .11.1.1..1  ->  L4152                       JSB SUB
205 L4315:  1.1.1.1...                                  M -> C
206 L4316:  111..1.1.1  ->  L4345                       JSB MPY
207 L4317:  ..111...11  ->  L4070                       GO TO R13
208 L4320:  111..1.1.1  ->  L4345           DNOTE3 :    JSB MPY
209 L4321:  ..1.1.1...                                  C EXCHANGE M
210 L4322:  .11.1.1...                                  STACK -> A
211 L4323:  ....1.11.1  ->  L4013                       JSB STA1
212 L4324:  ..111..1.1  ->  L4071                       JSB L360
213 L4325:  11....11..                                  12 -> P
214 L4326:  111...11.1  ->  L4343                       JSB DIV
215 L4327:  11..1.1...                                  DOWN ROTATE
216 L4330:  ..111..1.1  ->  L4071                       JSB L360
217 L4331:  .1.1.11...                                  LOAD CONSTANT 5
218 L4332:  11....11..                                  12 -> P
219 L4333:  111...11.1  ->  L4343                       JSB DIV
220 L4334:  ....1.11.1  ->  L4013                       JSB STA1
221 L4335:  .11.1.1..1  ->  L4152                       JSB SUB
222 L4336:  ....1111.1  ->  L4017                       JSB DOWN2
223 L4337:  .11.1.1...                                  STACK -> A
224 L4340:  111.1.111.                                  A EXCHANGE C[W]
225 L4341:  .1..1.1...                                  C -> STACK
226 L4342:  .1......11  ->  L4100                       GO TO DNOTE4
227 L4343:  ..1..1....  ->  L1344  *****  DIV    :     SELECT ROM 1
228 L4344:  ..........                                  NO OPERATION
229 L4345:  ..1..1....  ->  L1346  *****  MPY    :     SELECT ROM 1
230 L4346:  ..1..1....  ->  L1347  *****  TEN6   :     SELECT ROM 1
231 L4347:  .1..1..1..             SOD1   :     0 -> S4
232 L4350:  ..1.1.1...                                  C EXCHANGE M
233 L4351:  11..1.1...                                  DOWN ROTATE
234 L4352:  .1..1.1...                                  C -> STACK
235 L4353:  .1..1.1...                                  C -> STACK
```

```
236 L4354:  .1...11..1  ->  L41Ø6        JSB ONE
237 L4355:  .11.1.11.1  ->  L4153        JSB ADD
238 L4356:  1...1.111.                   B EXCHANGE C[W]
239 L4357:  111..1.1.1  ->  L4345        JSB MPY
240 L4360:  ..1.1.1...                   C EXCHANGE M
241 L4361:  111.1.111.                   A EXCHANGE C[W]
242 L4362:  111...11.1  ->  L4343        JSB DIV
243 L4363:  ..1.1.1...                   C EXCHANGE M
244 L4364:  ..1...1.11  ->  L4Ø42        GO TO SOD5
245 L4365:  ..11.1....          SEL4  :  KEYS -> ROM ADDRESS
246 L4366:  .1..1..1..          DNOTE1 :  Ø -> S4
247 L4367:  ..1.1.1...                   C EXCHANGE M
248 L4370:  .1....11.1  ->  L41Ø3        JSB R1ØØ
249 L4371:  111.1.111.                   A EXCHANGE C[W]
250 L4372:  .1..1.1...                   C -> STACK
251 L4373:  111...11.1  ->  L4343        JSB DIV
252 L4374:  .11.1.1...                   STACK -> A
253 L4375:  11..1.1...                   DOWN ROTATE
254 L4376:  ..1.1.1...                   C EXCHANGE M
255 L4377:  11.1....11  ->  L432Ø        GO TO DNOTE3
```

ROM 5

```
 0 L5000: ..........                                    NO OPERATION
 1 L5001: ..........                                    NO OPERATION
 2 L5002: 1....1....  ->  L4003  *****  XTY    :       SELECT ROM 4
 3 L5003: 11..1.1...                    S182   :       DOWN ROTATE
 4 L5004: .1..1.1...                                   C -> STACK
 5 L5005: 111.1.111.                                   A EXCHANGE C[W]
 6 L5006: .1..1.1...                                   C -> STACK
 7 L5007: ..11..111.                                   0 -> C[W]
 8 L5010: ...1.11...                                   LOAD CONSTANT 1
 9 L5011: 1....11...                                   LOAD CONSTANT 8
10 L5012: ..1..11...                                   LOAD CONSTANT 2
11 L5013: .1.1.11...                                   LOAD CONSTANT 5
12 L5014: .....11...                                   LOAD CONSTANT 0
13 L5015: .1111.1.1.                   S185   :       C + 1 -> C[X]
14 L5016: .1111.1.1.                                   C + 1 -> C[X]
15 L5017: 11....11..                                   12 -> P
16 L5020: ....11....                   RETR5  :       RETURN
17 L5021: ..11..111.                   S180   :       0 -> C[W]
18 L5022: ...1.11...                                   LOAD CONSTANT 1
19 L5023: 1....11...                                   LOAD CONSTANT 8
20 L5024: ....11.111  ->  L5015                        GO TO S185
21 L5025: 1.1..1.1..                                   IF S10 # 1
22 L5026: ...11...11  ->  L5030                            THEN GO TO SEL6
23 L5027: ....11....                                   RETURN
24 L5030: 11...1....  ->  L6031  *****  SEL6   :       SELECT ROM 6
25 L5031: ..........                                   NO OPERATION
26 L5032: ..........                                   NO OPERATION
27 L5033: .1.1...1..                   BOND1  :       1 -> S5
28 L5034: .1...1.1.1  ->  L5105                        JSB ONE
29 L5035: .11.11.111  ->  L5155                        GO TO BOND3
30 L5036: ..11111..1  ->  L5076        BONDR1 :        JSB STA1
31 L5037: 1.11...1..                                   1 -> S11
32 L5040: .1..1.111.                                   A -> B(W)
33 L5041: .11...111.                                   C -> A[W]
34 L5042: .11.11...1  ->  L5154                        JSB ADD1
35 L5043: 11..1.111.                                   A EXCHANGE B[W]
36 L5044: 111...11.1  ->  L5343                        JSB DIV
37 L5045: ..1.1.1...                                   C EXCHANGE M
38 L5046: .1....1..1  ->  L5102                        JSB R100
39 L5047: 111.1.111.                                   A EXCHANGE C[W]
40 L5050: 111...11.1  ->  L5343                        JSB DIV
41 L5051: ......11.1  ->  L5003                        JSB S182
42 L5052: 111...11.1  ->  L5343                        JSB DIV
43 L5053: ...1111.1.                                   IF C[XS] >= 1
44 L5054: .1.111..11  ->  L5134                            THEN GO TO BONDR2
45 L5055: ..111.1..1  ->  L5072                        JSB DOWN2
46 L5056: 1.1.1.1...                                   M -> C
47 L5057: 11..1.1...                   BON2   :        DOWN ROTATE
48 L5060: 1.1.1.1...                   BONDR3 :        M -> C
49 L5061: .1...1.1.1  ->  L5115                        JSB ONE
50 L5062: .11.1.11.1  ->  L5153                        JSB ADD
51 L5063: ..11111..1  ->  L5076                        JSB STA1
52 L5064: 111.1.111.                                   A EXCHANGE C[W]
53 L5065: 1.11...111  ->  L5261                        GO TO BONDR7
54 L5066: .11.1.1...                   DNOTE2 :        STACK -> A
55 L5067: .1.11..1..                   R13    :        0 -> S5
```

```
 56 L5070:  .11..1....  ->  L3071  *****           SELECT ROM 3
 57 L5071:  11..1.1...                  DOWN3  :   DOWN ROTATE
 58 L5072:  11..1.1...                  DOWN2  :   DOWN ROTATE
 59 L5073:  11..1.1...                             DOWN ROTATE
 60 L5074:  ....11....                             RETURN
 61 L5075:  11..1.1...                  STA2   :   DOWN ROTATE
 62 L5076:  .11.1.1...                  STA1   :   STACK -> A
 63 L5077:  .1..1.1...                             C -> STACK
 64 L5100:  ....11....                             RETURN
 65 L5101:  ..........                             NO OPERATION
 66 L5102:  1....1....  ->  L4103  *****  R100    :  SELECT ROM 4
 67 L5103:  .1.1..1...                  DNOTE5 :   1 -> S5
 68 L5104:  .1...11.11  ->  L5106                  GO TO DNOTE6
 69 L5105:  1....1....  ->  L4106  *****  ONE     :  SELECT ROM 4
 70 L5106:  1.1.1.1...                  DNOTE6 :   M -> C
 71 L5107:  111..1.1.1  ->  L5345                  JSB MPY
 72 L5110:  .1....1..1      L5102                  JSB R100
 73 L5111:  111.1.111.                             A EXCHANGE C[W]
 74 L5112:  111...11.1  ->  L5343                  JSB DIV
 75 L5113:  ..1111.1.1  ->  L5075                  JSB STA2
 76 L5114:  1.1.1.1...                             M -> C
 77 L5115:  111..1.1.1  ->  L5345                  JSB MPY
 78 L5116:  .1....1..1  ->  L5102                  JSB R100
 79 L5117:  111.1.111.                             A EXCHANGE C[W]
 80 L5120:  111...11.1  ->  L5343                  JSB DIV
 81 L5121:  11..1.1...                             DOWN ROTATE
 82 L5122:  1.11.1.1..                             IF S11 # 1
 83 L5123:  ..11.11.11  ->  L5066                        THEN GO TO DNOTE2
 84 L5124:  ..11.11111  ->  L5067                  GO TO R13
 85 L5125:  11..1.1...                  IT1    :   DOWN ROTATE
 86 L5126:  .11...111.                             C -> A[W]
 87 L5127:  1..1111.1.                  IT2    :   IF A[XS] >= 1
 88 L5130:  ...1....11  ->  L5020                        THEN GO TO RETR5
 89 L5131:  11.11.1.1.                             A - 1 -> A[X]
 90 L5132:  .1.....11.                             SHIFT LEFT A[M]
 91 L5133:  .1.1.11111  ->  L5127                  GO TO IT2
 92 L5134:  .11.1.1...                  BONDR2 :   STACK -> A
 93 L5135:  1.1.1.1...                             M -> C
 94 L5136:  .11.1.11.1  ->  L5153                  JSB ADD
 95 L5137:  ..11111..1  ->  L5076                  JSB STA1
 96 L5140:  ...1...1.1  ->  L5021                  JSB S180
 97 L5141:  111...11.1  ->  L5343                  JSB DIV
 98 L5142:  .1...1.1.1  ->  L5105                  JSB ONE
 99 L5143:  .11.1.1..1  ->  L5152                  JSB SUB
100 L5144:  1...1.111.                             B EXCHANGE C[W]
101 L5145:  ..1.1.1...                             C EXCHANGE M
102 L5146:  ..1111111.                             0 - C - 1 -> C[S]
103 L5147:  111..1.1.1  ->  L5345                  JSB MPY
104 L5150:  .1...1.1.1  ->  L5105                  JSB ONE
105 L5151:  11.11..111  ->  L5331                  GO TO BONDR8
106 L5152:  ..1..1....  ->  L1153  *****  SUB     :  SELECT ROM 1
107 L5153:  ..1..1....  ->  L1154  *****  ADD     :  SELECT ROM 1
108 L5154:  ..1..1....  ->  L1155  *****  ADD1    :  SELECT ROM 1
109 L5155:  1.1.1.111.                 BOND3  :   C + C -> C[W]
110 L5156:  111...11.1  ->  L5343                  JSB DIV
111 L5157:  ..1.1.1...                             C EXCHANGE M
112 L5160:  .1....1..1  ->  L5102                  JSB R100
113 L5161:  ......11.1  ->  L5003                  JSB S182
114 L5162:  111...11.1  ->  L5343                  JSB DIV
115 L5163:  ...1111.1.                             IF C[XS] >= 1
```

```
116 L5164:  .1..11.1.11  ->  L5232
117 L5165:  ..1111.1.1   ->  L5075
118 L5166:  .1...1.1.1   ->  L5105
119 L5167:  1.1.1.111.
120 L5170:  111.1.111.
121 L5171:  .11.1.11.1   ->  L5153
122 L5172:  ..1...111.
123 L5173:  111...11.1   ->  L5343
124 L5174:  11..1.1...
125 L5175:  .11.1.1...
126 L5176:  11..1.1...
127 L5177:  ..1111111.
128 L5200:  ......1..1   ->  L5002
129 L5201:  .1.1.1.1.1   ->  L5125
130 L5202:  111.1.111.
131 L5203:  .1...1.1.1   ->  L5105
132 L5204:  .11.1.11.1   ->  L5153
133 L5205:  ......1..1   ->  L5002
134 L5206:  ..111..1.1   ->  L5071
135 L5207:  ..11111..1   ->  L5076
136 L5210:  .11.1.1..1   ->  L5152
137 L5211:  .11.1.11.1   ->  L5153
138 L5212:  1.1.1.1...
139 L5213:  111..1.1.1   ->  L5345
140 L5214:  11..1.1...
141 L5215:  ....11.1.1   ->  L5015
142 L5216:  11..1.1...
143 L5217:  .11...111.
144 L5220:  1.1.1.1...
145 L5221:  111..1.1.1   ->  L5345
146 L5222:  11..1.1...
147 L5223:  .11.1.1...
148 L5224:  111...11.1   ->  L5343
149 L5225:  .11.1.1...
150 L5226:  .11.1.11.1   ->  L5153
151 L5227:  11..1.1...
152 L5230:  .11.1.1..1   ->  L5152
153 L5231:  ..11.11111   ->  L5067
154 L5232:  ..1111.1.1   ->  L5075
155 L5233:  ...1...1.1   ->  L5021
156 L5234:  111...11.1   ->  L5343
157 L5235:  11..1.1...
158 L5236:  111..1.1.1   ->  L5345
159 L5237:  .1...1.1.1   ->  L5105
160 L5240:  1.1.1.111.
161 L5241:  .11.1.11.1   ->  L5153
162 L5242:  ..1.1.1...
163 L5243:  .1...1.1.1   ->  L5105
164 L5244:  ....11.1.1   ->  L5015
165 L5245:  .11.1.11.1   ->  L5153
166 L5246:  ..1...111.
167 L5247:  ..1.1.1...
168 L5250:  111...11.1   ->  L5343
169 L5251:  .11.1.11.1   ->  L5153
170 L5252:  ..111..1.1   ->  L5071
171 L5253:  .1...1.1.1   ->  L5105
172 L5254:  .11.1.1..1   ->  L5152
173 L5255:  ..1.1.1...
174 L5256:  111..1.1.1   ->  L5345
175 L5257:  11..1.1...
```

```
                THEN GO TO BOND2
        JSB STA2
        JSB ONE
        C + C -> C[W]
        A EXCHANGE C[W]
        JSB ADD
        B -> C[W]
        JSB DIV
        DOWN ROTATE
        STACK -> A
        DOWN ROTATE
        0 - C - 1 -> C[S]
        JSB XTY
        JSB IT1
        A EXCHANGE C[W]
        JSB ONE
        JSB ADD
        JSB XTY
        JSB DOWN3
        JSB STA1
        JSB SUB
        JSB ADD
        M -> C
        JSB MPY
        DOWN ROTATE
        JSB S185
        DOWN ROTATE
        C -> A[W]
        M -> C
        JSB MPY
        DOWN ROTATE
        STACK -> A
        JSB DIV
        STACK -> A
        JSB ADD
        DOWN ROTATE
        JSB SUB
        GO TO R13
BOND2 : JSB STA2
        JSB S180
        JSB DIV
        DOWN ROTATE
        JSB MPY
        JSB ONE
        C + C -> C[W]
        JSB ADD
        C EXCHANGE M
        JSB ONE
        JSB S185
        JSB ADD
        B -> C[W]
        C EXCHANGE M
        JSB DIV
        JSB ADD
        JSB DOWN3
        JSB ONE
        JSB SUB
        C EXCHANGE M
        JSB MPY
        DOWN ROTATE
```

```
176 L5260:  1111111.11  ->  L5376          GO TO BONDR6
177 L5261:  ......1..1  ->  L5002  BONDR7 : JSB XTY
178 L5262:  .1...1.1.1  ->  L5105:         JSB ONE
179 L5263:  .11.1.1..1  ->  L5152          JSB SUB
180 L5264:  11.11....1  ->  L5330          JSB ROT1
181 L5265:  ..111..1.1  ->  L5071          JSB DOWN3
182 L5266:  .11.1.1..1  ->  L5152          JSB SUB
183 L5267:  11.11....1  ->  L5330          JSB ROT1
184 L5270:  11..1.1...                     DOWN ROTATE
185 L5271:  111.1.111.                     A EXCHANGE C[W]
186 L5272   111...11.1  ->  L5343          JSB DIV
187 L5273:  1.1.1.1...                     M -> C
188 L5274:  111..1.1.1  ->  L5345          JSB MPY
189 L5275:  ..11111..1  ->  L5076          JSB STA1
190 L5276:  .11.1.11.1  ->  L5153          JSB ADD
191 L5277:  .11.1.1...                     STACK -> A
192 L5300:  ..111.1..1  ->  L5072          JSB DOWN2
193 L5301:  ..1...111.                     B -> C[W]
194 L5302:  ..1111.1.1  ->  L5075          JSB STA2
195 L5303:  1.1.1.1...                     M -> C
196 L5304:  .11.1.11.1  ->  L5153          JSB ADD
197 L5305:  ..1.1.1...                     C EXCHANGE M
198 L5306:  ..1...111.                     B -> C[W]
199 L5307:  ....11.1.1  ->  L5015          JSB S185
200 L5130:  ....11.1.1  ->  L5015          JSB S185
201 L5311:  ....11.1.1  ->  L5015          JSB S185
202 L5312:  .11.1..11.                     IF C[M] = 0
203 L5313:  11..111.11  ->  L5316                THEN GO TO BON1
204 L5314:  .11.111.1.                     IF C[XS] = 0
205 L5315:  ..11....11  ->  L5060                THEN GO TO BONDR3
206 L5316:  1.11.1.1..  BON1    : IF S11 # 1
207 L5317:  11111.1111  ->  L5373                THEN GO TO BONDR4
208 L5320:  1.111..1..                     0 -> S11
209 L5321:  11..1.1...                     DOWN ROTATE
210 L5322:  .1..1.1...                     C -> STACK
211 L5323:  .1.1.1.1.1  ->  L5125          JSB IT1
212 L5324:  111.1.111.                     A EXCHANGE C[W]
213 L5325:  .1...1.1.1  ->  L5105          JSB ONE
214 L5326:  .11.1.1..1  ->  L5152          JSB SUB
215 L5327:  111..11.11  ->  L5346          GO TO BONDR9
216 L5330:  ..1..1....  ->  L1331  ***** ROT1  : SELECT ROM 1
217 L5331:  .11.1.11.1  ->  L5153  BONDR8 : JSB ADD
218 L5322:  .11.1.1...                     STACK -> A
219 L5333:  111...11.1  ->  L5343          JSB DIV
220 L5334:  .1...1.1.1  ->  L5105          JSB ONE
221 L5335:  .11.1.1..1  ->  L5152          JSB SUB
222 L5336:  1.1.1.1...                     M -> C
223 L5337:  111...11.1  ->  L5343          JSB DIV
224 L5340:  111111..11  ->  L5374          GO TO BONDR5
225 L5341:  ..........                     NO OPERATION
226 L5342:  ..........                     NO OPERATION
227 L5343:  ..1..1....  ->  L1344  ***** DIV   : SELECT ROM 1
228 L5344:  ..........                     NO OPERATION
229 L5345:  ..1..1....  ->  L1346  ***** MPY   : SELECT ROM 1
230 L5346:  ..1...111.          BONDR9 : B -> C[W]
231 L5347:  111..1.1.1  ->  L5345          JSB MPY
232 L5350:  1.1.1.1...                     M -> C
233 L5351:  111..1.1.1  ->  L5345          JSB MPY
234 L5352:  ..111.1..1  ->  L5072          JSB DOWN2
235 L5353:  .11...111.                     C -> A[W]
```

```
236 L5354:  ..111.1..1  ->  L5072      JSB DOWN2
237 L5355:  111..1.1.1  ->  L5345      JSB MPY
238 L5356:  .1...1.1.1  ->  L5105      JSB ONE
239 L5357:  1.1.1.111.                 C + C -> C[W]
240 L5360:  111.1.111.                 A EXCHANGE C[W]
241 L5361:  .11.1.11.1  ->  L5153      JSB ADD
242 L5362:  ..1...111.                 B -> C[W]
243 L5363:  111...11.1  ->  L5343      JSB DIV
244 L5364:  ..11111..1  ->  L5076      JSB STA1
245 L5365:  111..1.1.1  ->  L5345      JSB MPY
246 L5366:  11..1.1...                 DOWN ROTATE
247 L5367:  .11.1.1...                 STACK -> A
248 L5370:  111..1.1.1  ->  L5345      JSB MPY
249 L5371:  .1..1.1...                 C -> STACK
250 L5372:  ..1.111111  ->  L5057      GO TO BON2
251 L5373:  1.1.1.1...
252 L5374:  ....11.1.1  ->  L5015  BONDR4:  M -> C
253 L5375:  .11...111.             BONDR5 :  JSB S185
254 L5376:  .11.1.11.1  ->  L5153              C -> A[W]
255 L5377:  ..11.11111  ->  L5067  BONDR6 :  JSB ADD
                                               GO TO R13
```

ROM 6

```
 0  L6000:  .....1....  ->  L0001   *****  ERR71  :  SELECT ROM 0
 1  L6001:  .1.....1..                    DA8    :  1 -> S4
 2  L6002:  111.11..11  ->  L6354                   GO TO DA12
 3  L6003:  1..11.11..                    DM6    :  IF P # 9
 4  L6004:  1...11..11  ->  L6214                       THEN GO TO DM7
 5  L6005:  ....11....                              RETURN
 6  L6006:  11..1.111.                    DM3    :  A EXCHANGE B[W]
 7  L6007:  ..1.1.11..                    DM1    :  IF P # 2
 8  L6010:  1...1..111  ->  L6211                       THEN GO TO DM4
 9  L6011:  11111..11.                              A + 1 -> A[M]
10  L6012:  .1.11..11.                              C - 1 -> C[M]
11  L6013:  .11.1.1.1.                              IF C[X] = 0
12  L6014:  ....111111  ->  L6017                       THEN GO TO DM2
13  L6015:  11111..11.                              A + 1 -> A[M]
14  L6016:  .1.11..11.                              C - 1 -> C[M]
15  L6017:  ....11....                    DM2    :  RETURN
16  L6020:  ..11.11...                    YC1    :  LOAD CONSTANT 3
17  L6021:  .11..11...                              LOAD CONSTANT 6
18  L6022:  .1.1.11...                              LOAD CONSTANT 5
19  L6023:  .1....1.1.                              IF S4 # 1
20  L6024:  ...1.11111  ->  L6027                       THEN GO TO YC2
21  L6025:  11111.1.1.                              A + 1 -> A[X]
22  L6026:  ....11....                              RETURN
23  L6027:  ..1..11...                    YC2    :  LOAD CONSTANT 2
24  L6030:  .1.1.11...                              LOAD CONSTANT 5
25  L6031:  ....11....                              RETURN
26  L6032:  ..........                              NO OPERATION
27  L6033:  ..........                              NO OPERATION
28  L6034:  .....11..1  ->  L6006         DD6    :  JSB DM3
29  L6035:  11..1.111.                              A EXCHANGE B[W]
30  L6036:  .111...11.                              A + C -> C[M]
31  L6037:  .....111..                    DD8    :  P - 1 -> P
32  L6040:  ....1.11..                              IF P # 0
33  L6041:  ...111..11  ->  L6034                       THEN GO TO DD6
34  L6042:  ..11..1.1.                              0 -> C[X]
35  L6043:  .11...111.                              C -> A[W]
36  L6044:  .111.1.1..                              IF S7 # 1
37  L6045:  1..1..1.11  ->  L6222                       THEN GO TO DA4
38  L6046:  .11.1.1...                    DN1    :  STACK -> A
39  L6047:  111.1.111.                              A EXCHANGE C[W]
40  L6050:  1..111..11  ->  L6234                   GO TO DN3
41  L6051:  .111.1.1..                              IF S7 # 1
42  L6052:  ..1.11.111  ->  L6055                       THEN GO TO DA1
43  L6053:  .1...1.1..                              IF S4 # 1
44  L6054:  ..11....11  ->  L6060                       THEN GO TO DA3
45  L6055:  .1111..1..                    DA1    :  0 -> S7
46  L6056:  .1..1.1...                              C -> STACK
47  L6057:  .1..1.1...                              C -> STACK
48  L6060:  .11.1.1...                    DA3    :  STACK -> A
49  L6061:  .111.1.1..                              IF S7 # 1
32  L
50  L6062:  ..11.1..11  ->  L6064                       THEN GO TO DA13
51  L6063:  .1..1.1...                              C -> STACK
52  L6064:  111.1.111.                    DA13   :  A EXCHANGE C[W]
53  L6065:  111.1.1111  ->  L6353                   GO TO DA5
54  L6066:  .11.1.11..                    DM5    :  IF P # 6
```

```
55 L6067:  ......1111  ->  L6003
56 L6070:  ....11....
57 L6071:  ........
58 L6072:  .1.1.1.11.
59 L6073:  ..1111.111  ->  L6075
60 L6074:  ..1.11.11.
61 L6075:  1...1.111.
62 L6076:  .11.1.1...
63 L6077:  11..1.1...
64 L6100:  ..1111111.
65 L6101:  .11.1..1.1  ->  L6151
66 L6102:  1.1111111.
67 L6103:  ..11..111.
68 L6104:  .1.1..11..
69 L6105:  ...1.11...
70 L6106:  1....11...
71 L6107:  111.1.111.
72 L6110:  1....1.11.
73 L6111:  .11..1.111  ->  L6145
74 L6112:  .1...1.1...
75 L6113:  ...1...111.
76 L6114:  .11.1....1  ->  L6150
77 L6115:  .1.11..1..
78 L6116:  .1111..1..
79 L6117:  .....1....  ->  L0120  *****
80 L6120:  ....1111..
81 L6121:  .1.11.1.1.
82 L6122:  1....1.111  ->  L6205
83 L6123:  111.1.111.
84 L6124:  ........11.
85 L6125:  .........11  ->  L6000
86 L6126:  .....11..1  ->  L6006
87 L6127:  .111...11.
88 L6130:  11..1.111.
89 L6131:  .1...1.1..
90 L6132:  .1.111..11  ->  L6134
91 L6133:  ...1111111  ->  L6037
92 L6134:  1.......11.
93 L6135:  ...1111111  ->  L6037
94 L6136:  .........11  ->  L6000
95 L6137:  1.111.111.
96 L6140:  1...11..1.
97 L6141:  ...1.....1  ->  L6020
98 L6142:  1.....11..
99 L6143:  1...11..1.
100 L6144:  .111....11  ->  L6160
101 L6145:  ..1...111.
102 L6146:  .11.1....1  ->  L6150
103 L6147:  .1..1.1.11  ->  L6112
104 L6150:  1.111.111.
105 L6151:  .1.1...1..
106 L6152:  .111...1..
107 L6153:  11....11..
108 L6154:  ..1..1....  ->  L1155  *****
109 L6155:  111...111.
110 L6156:  .1.11...1.
111 L6157:  .11.11.111  ->  L6155
112 L6160:  1.1...111.
113 L6161:  .....111..
114 L6162:  ..111.11..
```

```
                THEN GO TO DM6
            RETURN
            NO OPERATION
DA7     :   A - C -> C[MS]
            IF NO CARRY GO TO DA11
            0 - C -> C[MS]
DA11    :   B EXCHANGE C[W]
            STACK -> A
            DOWN ROTATE
            0 - C - 1 -> C[S]
            JSB ADD63
            0 -> A[S]
            0 -> C[W]
            5 -> P
            LOAD CONSTANT 1
            LOAD CONSTANT 8
            A EXCHANGE C[W]
            IF A >= B[MS]
                THEN GO TO DA10
DA9     :   C -> STACK
            B -> C[W]
ADD62   :   JSB ADD61
            0 -> S5
            0 -> S7
            SELECT ROM 0
DD4     :   P + 1 -> P
            C - 1 -> C[X]
            IF NO CARRY GO TO DD3
            A EXCHANGE C[W]
            IF B[M] = 0
                THEN GO TO ERR71
            JSB DM3
            A + C -> C[M]
            A EXCHANGE B[W]
            IF S4 # 1
                THEN GO TO DD5
            GO TO DD8
DD5     :   IF A >= B[M]
                THEN GO TO DD8
            GO TO ERR71
DY1     :   0 -> A[W]
            B EXCHANGE C[WP]
            JSB YC1
            8 -> P
            B EXCHANGE C[WP]
            GO TO MU3
DA10    :   B -> C[W]
            JSB ADD61
            GO TO DA9
ADD61   :   0 -> A[W]
ADD63   :   1 -> S5
            1 -> S7
            12 -> P
            SELECT ROM 1
MU1     :   A + B -> A[W]
MU2     :   C - 1 -> C[P]
            IF NO CARRY GO TO MU1
MU3     :   SHIFT RIGHT B[W]
            P - 1 -> P
            IF P # 3
```

```
115 L6163:  .11.111.11  ->  L6156
116 L6164:  11.11.111.
117 L6165:  .111.11111  ->  L6167
118 L6166:  11111.111.
119 L6167:  11111.1.1.
120 L6170:  ....1111..
121 L6171:  1..1..111.
122 L6172:  1..11.11..
123 L6173:  .1111...11  ->  L6170
124 L6174:  ..11.11...
125 L6175:  .1....11..
126 L6176:  1...11..1.
127 L6177:  1..1..111.
128 L6200:  .....111..
129 L6201:  11111.11..
130 L6202:  .111111111  ->  L6177
131 L6203:  .11.1.1.1.
132 L6204:  .........11  ->  L6000
133 L6205:  11..1.11..
134 L6206:  .1.1....11  ->  L6120
135 L6207:  .........11  ->  L6000
136 L6210:  ..........
137 L6211:  .1..1.11..
138 L6212:  ..11.11.11  ->  L6066
139 L6213:  ....11....
140 L6214:  1.111.11..
141 L6215:  1...111111  ->  L6217
142 L6216:  ....11....
143 L6217:  11.11..11.
144 L6220:  .1111..11.
145 L6221:  ....11....
146 L6222:  .1.11...1.
147 L6223:  11..1.1...
148 L6224:  1..1.1.1..
149 L6225:  111.1..111  ->  L6351
150 L6226:  .1...1.1..
151 L6227:  .......111  ->  L6001
152 L6230:  1..11..1..
153 L6231:  111.11..11  ->  L6354
154 L6232:  ......11..
155 L6233:  1..1...11.
156 L6234:  .1111...1.
157 L6235:  1..11.1.11  ->  L6232
158 L6236:  ...11.1.1.
159 L6237:  .........11  ->  L6000
160 L6240:  .11.11111.
161 L6241:  1.1...1111  ->  L6243
162 L6242:  ..1.1..11.
163 L6243:  1111.1.11.
164 L6244:  .111..11..
165 L6245:  ..11..111.
166 L6246:  .111.11...
167 L6247:  ..11.11...
168 L6250:  .....11...
169 L6251:  .1.1.11...
170 L6252:  ...1.1.11.
171 L6253:  .........11  ->  L6000
172 L6254:  1.....11..
173 L6255:  ...1.....1  ->  L6020
174 L6256:  ....1.111.
```

```
                THEN GO TO MU2
            A - 1 -> A[W]
            IF NO CARRY GO TO DY2
            A + 1 -> A[W]
DY2     :   A + 1 -> A[X]
DD1     :   P + 1 -> P
            SHIFT RIGHT C[W]
            IF P # 9
                THEN GO TO DD1
            LOAD CONSTANT 3
            4 -> P
            B EXCHANGE C[WP]
DD2     :   SHIFT RIGHT C[W]
            P - 1 -> P
            IF P # 14
                THEN GO TO DD2
            IF C[X] = 0
                THEN GO TO ERR71
DD3     :   IF P # 12
                THEN GO TO DD4
            GO TO ERR71
            NO OPERATION
DM4     :   IF P # 4
                THEN GO TO DM5
            RETURN
DM7     :   IF P # 11
                THEN GO TO DM8
            RETURN
DM8     :   A - 1 -> A[M]
            C + 1 -> C[M]
            RETURN
DA4     :   C - 1 -> C[P]
            DOWN ROTATE
            IF S9 # 1
                THEN GO TO DA6
            IF S4 # 1
                THEN GO TO DA8
            0 -> S9
            GO TO DA12
DN2     :   0 -> P
            SHIFT RIGHT C[M]
DN3     :   C + 1 -> C[P]
            IF NO CARRY GO TO DN2
            IF C[X] >= 1
                THEN GO TO ERR71
            IF C[S] = 0
                THEN GO TO DN4
            0 - C -> C[M]
DN4     :   A + C -> A[MS]
            7 -> P
            0 -> C[W]
            LOAD CONSTANT 7
            LOAD CONSTANT 3
            LOAD CONSTANT 0
            LOAD CONSTANT 5
            IF A >= C[MS]
                THEN GO TO ERR71
            8 -> P
            JSB YC1
            0 -> B[W]
```

```
175 L6257:  1...1.111.
176 L6260:  1..11..11.
177 L6261:  1.11..1111  ->  L6263
178 L6262:  ........11  ->  L6000
179 L6263:  11111..11.
180 L6264:  1.1...111.
181 L6265:  .....111..
182 L6266:  1.111...11  ->  L6270
183 L6267:  .1111...1.
184 L6270:  11....111.
185 L6271:  1.11.11111  ->  L6267
186 L6272:  111...111.
187 L6273:  ....1.11..
188 L6274:  1.11.1..11  ->  L6264
189 L6275:  1..11..11.
190 L6276:  11.....111  ->  L6301
191 L6277:  111...111.
192 L6300:  .1.11.1.1.
193 L6301:  ...11.1.1.
194 L6302:  11...1..11  ->  L6304
195 L6303:  11.11.111.
196 L6304:  .1....11..
197 L6305:  ..11.11...
198 L6306:  ......11..
199 L6307:  1...1.111.
200 L6310:  ..11..111.
201 L6311:  111.1.1.1.
202 L6312:  ....1111..
203 L6313:  11111.1.1.
204 L6314:  ..11...11.
205 L6315:  .....111.1  ->  L6007
206 L6316:  11.....11.
207 L6317:  11.1...111  ->  L6321
208 L6320:  11.1..1111  ->  L6323
209 L6321:  1..11..11.
210 L6322:  11..1.1.11  ->  L6312
211 L6323:  111....11.
212 L6324:  1111...11.
213 L6325:  .1.....11.
214 L6326:  11111..11.
215 L6327:  11..1.1.1.
216 L6330:  ..11..111.
217 L6331:  .1.1111.1.
218 L6332:  1111..111.
219 L6333:  11..1.111.
220 L6334:  11.1..11..
221 L6335:  .....111..
222 L6336:  .1....111.
223 L6337:  .1111.11..
224 L6340:  11.111.111  ->  L6335
225 L6341:  111...111.
226 L6342:  ....1111..
227 L6343:  .1....111.
228 L6344:  11..1.11..
229 L6345:  111...1.11  ->  L6342
230 L6346:  11111.1.1.
231 L6347:  111.1.111.
232 L6350:  .1..11..11  ->  L6114
233 L6351:  .1...1.1..
234 L6352:  ..111.1.11  ->  L6072
```

```
            B EXCHANGE C[W]
            IF A[M] >= 1
                THEN GO TO DN11
            GO TO ERR71
DN11    :   A + 1 -> A[M]
DN15    :   SHIFT RIGHT B[W]
            P - 1 -> P
            GO TO DN6
DN5     :   C + 1 -> C[P]
DN6     :   A - B -> A[W]
            IF NO CARRY GO TO DN5
            A + B -> A[W]
            IF P # 0
                THEN GO TO DN15
            IF A[M] >= 1
                THEN GO TO DN12
            A + B -> A[W]
            C - 1 -> C[X]
DN12    :   IF C[X] >= 1
                THEN GO TO DN7
            A - 1 -> A[W]
DN7     :   4 -> P
            LOAD CONSTANT 3
            0 -> P
            B EXCHANGE C[W]
            0 -> C[W]
            A EXCHANGE C[X]
DN8     :   P + 1 -> P
            A + 1 -> A[X]
            0 -> C[M]
            JSB DM1
            A - B -> A[M]
            IF NO CARRY GO TO DN13
            GO TO DN14
DN13    :   IF A[M] >= 1
                THEN GO TO DN8
DN14    :   A + B -> A[M]
            A + C -> A[M]
            SHIFT LEFT A[M]
            A + 1 -> A[M]
            A EXCHANGE B[X]
            0 -> C[W]
            C - 1 -> C[XS]
            A + C -> A[W]
            A EXCHANGE B[W]
            13 -> P
DN9     :   P - 1 -> P
            SHIFT LEFT A[W]
            IF P # 7
                THEN GO TO DN9
            A + B -> A[W]
DN10    :   P + 1 -> P
            SHIFT LEFT A[W]
            IF P # 12
                THEN GO TO DN10
            A + 1 -> A[X]
            A EXCHANGE C[W]
            GO TO ADD62
DA6     :   IF S4 # 1
                THEN GO TO DA7
```

```
235 L6353:   .1..1..1..
236 L6354:   .1.11.1.1.
237 L6355:   1111....11  ->  L6360
238 L6356:   1..1...11.
239 L6357:   ..11..1.1.
240 L6360:   ...11.1.1.
241 L6361:   ........11  ->  L6000
242 L6362:   ....1.111.
243 L6363:   .11...111.
244 L6364:   1.....11..
245 L6365:   ..11.1..1.
246 L6366:   ..1..11...
247 L6367:   ...1.11...
248 L6370:   1.....11..
249 L6371:   ...1.1..1.
250 L6372:   ........11  ->  L6000
251 L6373:   ...1.11...
252 L6374:   1..1.11...
253 L6375:   1.....11..
254 L6376:   .1.1.1..1.
255 L6377:   .1.1111111  ->  L6137
```

```
DA5   :  0 -> S4
DA12  :  C - 1 -> C[X]
         IF NO CARRY GO TO DA2
         SHIFT RIGHT C[M]
         0 -> C[X]
DA2   :  IF C[X] >= 1
                THEN GO TO ERR71
         0 -> B[W]
         C -> A[W]
         8 -> P
         0 -> C[WP]
         LOAD CONSTANT 2
         LOAD CONSTANT 1
         8 -> P
         IF A >= C[WP]
                THEN GO TO ERR71
         LOAD CONSTANT 1
         LOAD CONSTANT 9
         8 -> P
         A - C -> C[WP]
         IF NO CARRY GO TO DY1
```

FUNCTIONS

All of the functions performed by the calculator are given in the table below. The notes referred to in this table are given at the end of the table.

TABLE OF FUNCTIONS INCORPORATED INTO THE BUSINESS CALCULATOR

1. SIMPLE COMPOUNDING

1.1 $FV = PV\ (1 + i)^n$

1.2 $PV = FV/(1 + i)^n$

1.3 $i = (FV/PV)^{1/n} - 1$

1.4 $n = (\text{Log}(FV))/\text{Log}\ (PV(1 + i))$

2. ANNUITY

2.1 $$FV = PMT\ \frac{(1 + i)^n - 1}{i}$$

2.2 $$PV = PMT\ \frac{(1 + i)^n - 1}{i\,(1 + i)^n}$$

2.3 Solve For i In (see Note 1):

$$PV - PMT\ \frac{(1 + i)^n - 1}{i\,(1 + i)^n} = 0$$

2.4 Solve For i In (see Note 1):

$$FV - PMT\ \frac{(1 + i)^n - 1}{i} = 0$$

2.5 $$n = \frac{\log\,(PMT/(PV - PMT))}{\log\,(1 + i)}$$

2.6 $$n = \frac{\log\,(FV \times i/PMT + 1)}{\log\,(1 + i)}$$

2.7 $$PMT = PV\ \frac{i\,(1 + i)^n}{(1 + i)^n - 1}$$

2.8 $$PMT = FV\ \frac{i}{(1 + i)^n - 1}$$

3. ADD ON TO ANNUAL RATE

3.1 Solve For i In (see Note 1):

$$1 - \frac{1 + \frac{n}{12} \times \frac{R}{100}}{n} \times \frac{(1+i)^n - 1}{i(1+i)^n}$$

n = No. of Months

R = Annual Add-On Rate

4. ACCRUED INTEREST

n = No. of Days

i = Annual Interest Rate (%)

PV = Principal Amount

4.1 $i_{360} = \frac{n \, PV \, i}{36000}$

4.2 $i_{365} = i_{360} \times .98630137$

5. DISCOUNTED NOTE

n = No. of Days

i = Annual Interest Rate (%)

FV = Face Value of Note

5.1 $d_{360} = \frac{FV \times n \times i}{36000}$

5.2 $yield_{360} = \frac{d_{360} \times 36000}{n(FV - d_{360})}$

5.3 $d_{365} = d_{360} \times \frac{360}{365}$

5.4 $yield_{365} = \frac{d_{365} \times 36500}{n(FV - d_{365})}$

6. BOND

6.1 Price of a Bond (PV) (see Note 2):

n = No. of Days (uncompensated for leap days)

i = yield

c = coupon rate

For $n \geq 182.5$:

$$PV = 100\left(1 + \frac{i}{200}\right)^{\frac{-n}{182.5}} + \frac{100c}{i}\left(1 + \frac{i}{200}\right)^{j} - \left(1 + \frac{i}{200}\right)^{\frac{-n}{182.5}} - \frac{cj}{2}$$

where $j = 1 - \text{frac } n/182.5$

For $n < 182.5$:

$$PV = \frac{200 + c}{2 + \frac{n}{180} \cdot \frac{i}{100}} \quad \frac{(1-n)c}{2}$$

6.2 Yield of a Bond (see Note 2):

Solve for i knowing PV, in the above 2 equations, which one depending on n.

Solution gives $| i_{actual} - i_{calc} | < 2 \times i^2_{actual} \times C \times 10^{-6}$

7. DATE (see Note 3):

7.1 Date 1 – Date 2

7.2 Date ± n Days

1900 ≤ Date ≤ 2099 A.D.

8. ACCUMULATED INTEREST

8.1 accumulated interest (in $) =

$$PMT \left\{ k - j\frac{\frac{(1+i)^{k-n}}{100}}{i/100} \left[1 - \left(1 + \frac{i}{100}\right)^{j-k}\right] \right\}$$

8.2 $$PV_k = \frac{PMT \times 100}{i} \left\{1 - \left(1 + \frac{i}{100}\right)^{k-n}\right\}$$

9. ACCUMULATION & MEAN & σ

9.1 Sum $= \sum_{1}^{n} x_i$

9.2 Sum of Squares $= \sum_{1}^{n} x_i^2$

9.3 Mean $= \frac{1}{n}\sum_{1}^{n} x_i$

$$9.4\ \sigma = \left\{ \frac{1}{n-1} \sum_{1}^{n^1} x_i^2 - \text{Mean}^2 \right\}^{1/2}$$

10. TREND LINE

$$10.1\ \underset{(m)}{\text{Slope}} = \frac{2\sum_{1}^{n} k y_k - (n+1)\sum_{1}^{n} y_k}{n(n^2-1)/6}$$

$$10.2\ \underset{(c)}{\text{Y Intercept}} = \frac{1}{n}\sum_{1}^{n} y_k - \frac{n+1}{2} \cdot \text{slope}$$

10.3 $y_{(k)} = mk + c$

11. SUM OF DIGITS DEPRECIATION

n = Depreciable Lifetime

PV = Initial Value of Asset

$$11.1\ \text{Depreciation at time (k)} = \frac{2\,PV}{n(n+1)}(n-k+1)$$

$$11.2\ \text{Remaining book value at (k)} = \frac{PV(n-k)(n-k+1)}{n(n+1)}$$

12. CASH FLOW

12.1 Current Sum of Present Value of Cash Flow

$$= \sum_{j=0}^{n} F_j (1+i)^{-j}$$

where j = j^{th} cash flow

and i = cost of capital

Note 1: Fig. 32 illustrates the algorithm used for the solution of 2.3, 2.4 and 3.1 above. The technique is a simple Newton-Raphson method for the solution of an implicit equation.

Note 2: Fig. 33 shows how the price of a bond is calculated, and Fig. 34 illustrates the algorithm used to compute the yield to maturity of a bond.

Note 3: Fig. 35 illustrates the date algorithm. The first half computes the dates difference and the next half the date ± n days.

OPERATING INSTRUCTIONS

All of the operations described below are controlled or initiated from the keyboard input unit 12 which is shown in Fig. 1.

BASIC INSTRUCTIONS

Clearing

To clear display — only [CLX]

To clear everything (except constant storage) — press [f] [CLEAR CLX]

Constant Storage

To store a constant — press [STO]

To recall a constant — press [RCL]

NOTE: Certain important pre-programmed calculations overwrite previous contents of the constant storage. These are:

—Add-on to annual Percentage Rate Conversion
—Effective yield of an annuity (Loan repayment and sinking fund)
—Accrued interest and discounted note problems
—Trend lines (least squares linear regression)
—Sum-of-the-digits calculations
—Bond calculations (price and yield)
—Accumulated interest paid on a loan
—Discounted Cash Flow Analysis

Except where noted above, a constant remains in the machine until it is turned off or over-written by another constant.

Rounding

To round-off (the display only) press [f], then any desired numeral key between [0] and [6]. A numeral key greater than [6] will put display in so-called "scientific notation". Normal turn-on mode is automatically rounded to two decimal places.

NOTE: Rounding affects the display *only*. The full internal accuracy of the machine is maintained.

Arithmetic Operations

To perform simple arithmetic operations between two numbers:
—key in the first number
—key in the second number, press desired operation, [+], [−], [×] or [÷] — press [SAVE ↑]

To perform chain calculations, only the first number has to be loaded through a [SAVE ↑] operation . . . all subsequent numbers need only be keyed in and the desired function key pressed after each one.

Automatic computation between a displayed number and a stored constant is achieved by pressing [RCL] and the desired function.

Changing Sign

To change the sign of a displayed number — press [CHS]

To enter a negative number, key in number — press [CHS]

Raising a Number to a Power

Key in positive base number (to be raised to a power) — press [SAVE↑]

Key in power (exponent) — press [y^x]

To Obtain Square Root of a Number

Key in number — press [shaded] [$\sqrt{x}$ / y^x]

Percentage Operations

To obtain the *percentage amount* of a number:

—key in the base number — press [SAVE↑]

—key in the percent (as a %) — press [%]

To add or subtract the percentage amount to the base number simply press [+] or [−], respectively.

To obtain the *percent difference* between two numbers:

—key in the base (or reference) number — press [SAVE↑]

—key in the second number (answer is displayed in percent) — press [shaded] [Δ% / %]

Calendar Functions

Date entry sequence is: month, decimal point, two numeral day and four numeral year. Example: May 8, 1972 = 5.081972. Calendar range is from January 1, 1900 to December 31, 2099.

To obtain *difference between two dates:*

—key in first date — press [SAVE↑]

—key in second date — press [DAY]

To obtain a *date* from a base date:

—key in the base date — press [SAVE↑]

—key in the number of days (can be positive or negative) — press [shaded] [DATE / DAY]

To obtain the *day of the week* of a date:

—key in today's date — press [SAVE↑]

—key in desired date — press [DAY] [SAVE↑]

—key in [7] — press [÷]

—key in that portion of the display *left* of the decimal point — press [−]

—key in [7] again — press [×]

If the date in question is *beyond* today, its day of the week will be today's day *plus* the number shown in the display.

If the date in question is *before* today, its day of the week will be today's day *minus* the number shown in the display.

Error Indication

An improper or illegal operation (such as dividing by zero) will result in a steady blinking display.

Battery Condition (low charge indication)

All decimals in the display indicates low battery condition. Plug into recharger.

COMPOUND INTEREST

NOTE: To use the compound interest keys (top row) simply remember to enter your known values in left-to-right sequence and then press the key which corresponds to your answer.

Future Value

Key in number of time periods — press [n]

Key in interest rate *per* time period (in %) — press [i]

Key in present value (principal) — press [PV]

To obtain future value — press [FV]

NOTE: Simple arithmetic operations may be performed prior to entering any value. Also, a mistaken last entry may be corrected by pressing [CLX], then keying in the correct value and pressing the appropriate key.

Present Value

Key in number of time periods — press [n]

Key in interest rate *per* time period (in %) — press [i]

Key in future value amount — press [FV]

To obtain present value — press [PV]

Rate of Return (growth rate)

Key in number of periods	press [n]
Key in present (beginning) value	press [PV]
Key in future (ending) value	press [FV]
To obtain effective rate *per* period (in %)	press [i]

Number of Time Periods (for a compounded amount)

Key in interest rate *per* period (in %)	press [i]
Key in present (beginning) value	press [PV]
Key in future (ending) value	press [FV]
To obtain number of time periods	press [n]

Nominal Rate Converted to Effective Annual Rate

Key in number of time periods *per* year	press [STO] [n]
Key in Nominal Rate (as a %)	press [RCL] [÷] [i]
Key in [1] [0] [0]	press [STO] [PV] [FV]
To obtain effective annual rate (in %)	press [RCL] [—]

Effective Annual Rate Converted to Nominal Rate

Key in number of time periods *per* year	press [STO] [n]
Key in [1] [0] [0]	press [SAVE↑] [PV]
Key in effective annual rate (in %)	press [+] [FV] [i]
To obtain nominal rate (in %)	press [RCL] [×]

SINKING FUND

Future Value of an Annuity (sinking fund)

Key in number of time periods	press [n]
Key in interest rate *per* period (as a %)	press [i]
Key in payment (installment) amount	press [PMT]
To obtain future value	press [FV]

Sinking Fund Payment Amount

Key in number of time periods	press [n]
Key in interest rate *per* period (as a %)	press [i]
Key in future value	press [FV]
To obtain payment amount	press [PMT]

Effective Yield of a Sinking Fund

Key in number of time periods	press [n]
Key in payment (installment) amount	press [PMT]
Key in future value	press [FV]
To obtain interest rate *per* period (as a %)	press [i]

Number of Periods Required for a Sinking Fund

Key in interest rate *per* period (as a %)	press [i]
Key in payment (installment) amount	press [PMT]
Key in future value	press [FV]
To obtain number of time periods	press [n]

LOAN REPAYMENT

Accrued (Simple) Interest Payment Due

Key in number of *days*	press [n]
Key in *annual* interest rate (in %)	press [i]
Key in the principal (present value)	press [PV]
To obtain interest payment due on a 360 day basis	press [▨] [INTR] [PMT]
To obtain interest payment due on a 365 day basis	press [x≠y]

Discounted Note and Effective Annual Yields

Key in number of days	press [n]
Key in *annual* interest (discount) rate (in %)	press [i]
Key in the face (future) value of note	press [FV]

To obtain the discount amount (i.e.—the interest portion) of the note on a 360 day basis	press [▨]	[INTR] [PMT]
To obtain the effective annual yield on a 360 day basis	press	[R↓]
To obtain the discount amount of the note on a 365 day basis	press [R↓]	
To obtain the effective annual yield on a 365 day basis	press	[R↓]

True Equivalent Annual Yield

Key in number of day's	press	[SAVE↑]
Key in [3] [6] [5]	press [÷]	[n]
Key in the principal (present value) of note	press [PV]	
Key in the face value (future value) of note	press [FV]	
To obtain true equivalent annual yield	press [i]	

Present Value of an Annuity (Principal Amount of a Loan)

Key in the number of time periods (months, years, etc.)	press [n]	
Key in interest rate *per* period (in %)	press [i]	
Key in the amount of the payment *per* period	press [PMT]	
To obtain present value (principal)	press [PV]	

Loan Repayment Amount

Key in number of time periods	press [n]	
Key in interest rate *per* period (in %)	press [i]	
Key in present value (principal)	press [PV]	
To obtain payment amount *per* period	press [PMT]	

True Interest Rate of a Loan

Key in number of time periods	press [n]	
Key in payment amount *per* period	press [PMT]	
Key in present value (principal)	press [PV]	
To obtain interest rate *per* period (in %)	press [i]	

NOTE: To obtain an *annual* rate simply key in the number of time periods per year and press [x].

Number of Time Periods Required for a Loan

Key in the interest rate *per* time period	press [i]
Key in the payment amount *per* time period	press [PMT]
Key in the present value (principal)	press [PV]
To obtain the number of time periods	press [n]

Accumulated Interest Paid on a Loan (between two points in time)

Key in the payment number corresponding to the first point of the time span in question	press [STO]
Key in the payment number corresponding to the last point of the time span in question	press [n]
Key in the *total* number of payments of the loan	press [n]
Key in the interest rate *per* payment (or period)	press [i]
Key in the payment amount *per* period	press [PMT]
To obtain the accumulated interest	press [Σ+]

Remaining Balance (Principal) of a Loan

As an extension of the previous problem

To obtain the remaining balance (principal)	press [x≓y]

"Add-on" Interest Converted to a True Annual Percentage Rate

Key in the number of *months* of the loan	press [n]
Key in the "add-on" rate (per annum)	press [i]
To obtain true annual percentage rate	press [i]
To obtain the monthly payment amount	press [x≓y]
Then key in the principal amount to be loaned	press [x]

Interest Rebate (Rule of 78's)

Key in last payment number	press [n]
Key in *total* number of payments for the loan	press [n]
Key in the *total* finance charge	press [PV]

To obtain the unearned interest (rebate) press [▨] [SOD] [x⇄y]

To obtain the remaining principal due,

key in the amount of each payment press [SAVE↑]

key in the number of payments remaining press [x] [x⇄y] [−]

DEPRECIATION AMORTIZATION

Sum-of-the-years' Digits Depreciation

① Key in given year number (or beginning year number) press [n]

② Key in life of asset (number of years) press [n]

③ Key in depreciable amount (purchase less salvage value) press [PV]

④ To obtain given year's depeciation press [▨] [SOD]

⑤ To obtain subsequent year's depreciation press [SOD]

⑥ Continue step ⑤ as desired

⑦ To obtain the depreciation for a particular year *not* in sequence, simply key in the year number desired and press [n] [SOD]

⑧ Continue step ⑦ as desired.

NOTE: To obtain the remaining book value after each year's depreciation press [x⇄y]. The [x⇄y] key must be pressed *again* before the next SOD calculation (step 5).

Straight Line Depreciation

Key in depreciable amount (purchase less salvage value) press [SAVE↑] [SAVE↑]

To obtain each year's depreciation

—key in life of asset (number of years) press [÷]

NOTE: To obtain the remaining book value after each year's depreciation, first press [STO] [−] (for book value after first year) then [RCL] [−] for each subsequent year.

Variable Rate, Declining-Balance Depreciation

① Key in [1] [0] [0] and — press [SAVE↑]

② Key in life of asset (number of years) — press [÷]

③ Key in declining factor or rate (i.e.—1.5, 2 etc.) — press [x] [STO]

④ Key in depreciable amount (purchase less salvage value)

⑤ To obtain year's depreciation — press [RCL] [%]

⑥ To obtain remaining book value — press [−]

⑦ Continue steps ⑤ and ⑥ for subsequent years.

Diminishing Balance Depreciation

① Key in life of asset (number of years) — press [n]

② Key in beginning value of asset — press [PV]

③ Key in ending (salvage) value of asset — press [FV]

NOTE: Salvage must be greater than zero.

④ To obtain and store rate of depreciation — press [i] [CHS] [STO]

⑤ Key in beginning value of asset

⑥ To obtain year's depreciation — press [RCL] [%]

⑦ To obtain remaining book value — press [−]

⑧ Continue steps ⑥ and ⑦ for subsequent years.

BONDS

Price of a Bond

① Key in either maturity or purchase date — press [SAVE↑]

② Key in remaining date — press [DAY]

③ Key in yield-to-maturity (as a %) — press [i]

④ Key in coupon rate (as a %) — press [PMT]

⑤ To obtain bond price — press [▨] [BOND] [PV]

Yield-to-Maturity of a Bond

① Key in either maturity or purchase date*	press	SAVE↑
② Key in remaining date	press	DAY
③ Key in coupon rate (as a %)	press	PMT
④ Key in the bond price	press	PV
⑤ To obtain bond yield	press	YTM i

NOTE: Normal accuracy of bond calculations is two decimal places for most cases. If further accuracy is required, the following procedure should replace steps ① and ② of either of the above.

Extended Precision Bond Calculations

NOTE: This procedure replaces steps ① and ② in normal bond calculations. It provides six decimal place accuracy for all bond price calculations and three decimal place accuracy for most yield calculations.

a) Determine the number of days, months and years to maturity (in accordance with trade custom)

b) Key in number of days	press	SAVE↑
c) Key in 3 0 (days/month)	press	÷
d) Key in number of months	press	+
e) Key in 1 2 (months/year)	press	÷
f) Key in number of years	press	+
g) Key in 3 6 5 (days/year)	press	× n

Continue with step ③ of bond calculations.

INVESTMENT ANALYSIS

Discounted Rate of Return (for even cash flows)

Key in number of time periods	press	n
Key in amount of cash flow *per* period	press	PMT
Key in original investment	press	PV
To obtain discounted rate of return (in %) *per* period	press	i

Discounted Cash Flow Analysis (for uneven cash flows)

① Key in discount rate (in %) *per* period — press [i]

② Key in original investment — press [CHS] [PV]

③ Key in cash flow *per* period — press [PV] [Σ+]

④ Continue step ③ for subsequent flows.

NOTE: Investment is profitable (to the extent of the discount rate) if the result is positive. Furthermore, the user can determine the "break-even" period by noting the period in which step ③ first yielded a positive result.

STATISTICS

Mean and Standard Deviation

① Clear the entire machine by pressing [f] [CLEAR CLX]

② Key in data item — press [Σ+]

③ Continue step ② until all data are entered.

④ To obtain mean (arithmetic average) — press [x̄]

NOTE: To obtain the standard deviation after each mean calculation press [x≷y]. The [x≷y] key must be pressed *again* before resuming.

⑤ To return to the summation mode — press [f] [→Σ x̄]

⑥ Continue with step ② if desired.

NOTE: To correct a data item key in its value and press [f] [Σ− Σ+]

Trend Lines (Least Squares Linear Regression)

① Clear the entire machine by pressing [f] [CLEAR CLX]

② Sequentially, key in data item — press [TL]

NOTE: Each time [TL] is pressed, the sequence number for that item is displayed.

③ Continue step ② until all data are entered.

④ To terminate the data entry sequence — press [f] [TL]

⑤ To obtain a specific value on the trend line, key in the appropriate time period number — press [n] [TL]

⑥ Repeat step ⑤ as often as desired.

NOTE: The user may also "step-along" the trend line by simply pressing [TL] as many times as desired. Further, the current time period number may be obtained by pressing [x≠y]. The [x≠y] key must be pressed *again* before resuming.

⑦ To obtain the amount of change of the trend line *per* period (commonly called "slope") — press [R↓] [R↓]

⑧ To resume operation — press [R↓] [R↓]

WHAT WE CLAIM IS:—

1. An electronic calculator comprising:

keyboard input means having a plurality of numeric keys manually operable for entering numerical data into the calculator and having a plurality of non-numeric control keys manually operable for controlling the calculator, said non-numeric control keys including a plurality of function keys associated with a plurality of functionally related financial variables and manually operable for designating selected numerical data as said financial variables and for conditioning the calculator to perform mathematical operations involving said financial variables;

storage means coupled to said keyboard input means for storing numerical data entered into or calculated by the calculator;

processing means coupled to said keyboard input means and to said storage means and responsive to successive actuation of one or more of said numeric keys and one or more of said non-numeric control keys in a sequence, including one of said function keys followed by one of said function keys without interruption by any of said numeric keys, for automatically performing a mathematical operation employing selected numerical data, stored in said storage means and designated as one or more of said financial variables by actuation of one or more of said function keys, to determine the value of a financial variable associated with the last of said function keys in said sequence; and

output means coupled to said processing means for indicating the value of the financial variable associated with the last of said function keys in said sequence.

2. An electronic calculator as in claim 1 wherein:

said plurality of function keys comprises five financial function keys associated with five functionally related financial variables; and

said processing means is responsive to successive actuation of one or more of said numeric keys and one or more of said non-numeric control keys in a sequence, including one of said financial function keys followed by one of said financial function keys without interruption by any of said numeric keys, for automatically performing a mathematical operation employing selected numerical data, stored in said storage means and designated as one or more of said financial variables by actuation of one or more of said financial function keys, to determine the value of a financial variable associated with the last of said financial function keys in said sequence.

3. An electronic calculator as in claim 2 wherein said five financial function keys include:

a first financial function key associated with a financial variable representing a number of periods;

a second financial function key associated with a financial variable representing an interest rate per period;

a third financial function key associated with a financial variable representing a periodic payment amount;

a fourth financial function key associated with a financial variable representing a present value of principal; and

a fifth financial function key associated with a financial variable representing a future value of principal after one or more periods have elapsed.

⑤ To obtain a specific value on the trend line, key in the appropriate time period number — press [n] [TL]

⑥ Repeat step ⑤ as often as desired.

NOTE: The user may also "step-along" the trend line by simply pressing [TL] as many times as desired. Further, the current time period number may be obtained by pressing [x=y]. The [x=y] key must be pressed *again* before resuming.

⑦ To obtain the amount of change of the trend line *per* period (commonly called "slope") — press [R↓] [R↓]

⑧ To resume operation — press [R↓] [R↓]

WHAT WE CLAIM IS:—

1. An electronic calculator comprising:

keyboard input means having a plurality of numeric keys manually operable for entering numerical data into the calculator and having a plurality of non-numeric control keys manually operable for controlling the calculator, said non-numeric control keys including a plurality of function keys associated with a plurality of functionally related financial variables and manually operable for designating selected numerical data as said financial variables and for conditioning the calculator to perform mathematical operations involving said financial variables;

storage means coupled to said keyboard input means for storing numerical data entered into or calculated by the calculator;

processing means coupled to said keyboard input means and to said storage means and responsive to successive actuation of one or more of said numeric keys and one or more of said non-numeric control keys in a sequence, including one of said function keys followed by one of said function keys without interruption by any of said numeric keys, for automatically performing a mathematical operation employing selected numerical data, stored in said storage means and designated as one or more of said financial variables by actuation of one or more of said function keys, to determine the value of a financial variable associated with the last of said function keys in said sequence; and

output means coupled to said processing means for indicating the value of the financial variable associated with the last of said function keys in said sequence.

2. An electronic calculator as in claim 1 wherein:

said plurality of function keys comprises five financial function keys associated with five functionally related financial variables; and

said processing means is responsive to successive actuation of one or more of said numeric keys and one or more of said non-numeric control keys in a sequence, including one of said financial function keys followed by one of said financial function keys without interruption by any of said numeric keys, for automatically performing a mathematical operation employing selected numerical data, stored in said storage means and designated as one or more of said financial variables by actuation of one or more of said financial function keys, to determine the value of a financial variable associated with the last of said financial function keys in said sequence.

3. An electronic calculator as in claim 2 wherein said five financial function keys include:

a first financial function key associated with a financial variable representing a number of periods;

a second financial function key associated with a financial variable representing an interest rate per period;

a third financial function key associated with a financial variable representing a periodic payment amount;

a fourth financial function key associated with a financial variable representing a present value of principal; and

a fifth financial function key associated with a financial variable representing a future value of principal after one or more periods have elapsed.

4. An electronic calculator as in claims 2 or 3 wherein:

said non-numeric control keys include a command key for associating one of said five financial function keys with an alternative financial variable representing a yield to maturity of a bond, for associating another of said five financial function keys with an alternative financial variable representing an accrued interest amount, and for associating still another of said five financial function keys with an alternative financial variable representing a bond price; and

each of three last-mentioned financial function keys is manually operable, when actuated successively following actuation of said command key, for designating selected numerical data as the corresponding one of said alternative financial variables and for conditioning the calculator to perform a mathematical operation involving that alternative financial variable.

5. An electronic calculator as in claim 3 wherein said first, second, third, fourth, and fifth financial function keys are positioned on said keyboard input means in a lineal sequence and in the order mentioned.

6. An electronic calculator as in claim 4 wherein:

said first, second, third, fourth, and fifth financial function keys are positioned on said keyboard input means in a lineal sequence and in the order mentioned; and

said three financial function keys associable with said alternative financial variables are positioned on said keyboard input means in a lineal sequence and in the order mentioned.

7. An electronic calculator as in claim 4 wherein:

each of said five financial function keys is provided with an indicium indicating the financial variable with which it is associated; and

said keyboard input means is further provided with indicia indicating the alternative financial variables with which said three financial function keys are associable.

8. An electronic calculator as in claim 7 wherein said command key and said indicia indicating the alternative financial variables are color coded.

9. An electronic calculator as in claim 1 wherein said processing means includes:

first means responsive to actuation of a first one of said non-numeric control keys for generating the arithmetic average of numerical data stored in said storage means, for causing said output means to display said arithmetic average in decimal digit form, and for generating an end-of-operation signal; and

second means coupled to said first means and responsive to said end-of-operation signal for generating the standard deviation of numerical data stored in said storage means, said processing means being responsive to actuation of a second one of said non-numeric keys for causing said output means to indicate said standard deviation in decimal digit form.

10. An electronic calculator as in claim 9 wherein said non-numeric control keys include a command key manually operable with said first and second non-numeric control keys, when said second non-numeric control key, said command key, and said first non-numeric control key are successively actuated in the order mentioned following generation of said arithmetic average and said end-of-operation signal, for causing said first and second means to generate the arithmetic average and the standard deviation for different numerical data entered into said storage means by said numeric keys.

11. An electronic calculator as in claim 1 wherein:

a first one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing equally-spaced and chronologically-sequenced numerical data in said storage means;

said processing means is operable for generating the least-squares linear regression of the numerical data stored in said storage means; and

said non-numeric control keys include a command key manually operable with said first non-numeric control key, when said command key and said first non-numeric control key are successively actuated in the order mentioned, for causing said processing means to generate a first value of the least-squares linear regression of the numerical data stored in said storage means and for causing said output means to indicate said first value in decimal digit form.

12. An electronic calculator as in claim 11 wherein:

said first value is the value at the y-intercept in rectangular coordinate notation; and

said processing means is responsive to further successive actuations of said first non-numeric control key for generating succeeding values of the least-squares

linear regression of the numerica data stored in said storage means.

13. An electronic calculator as in claim 11 wherein:

a second one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing the sequence number of a chronological numerical datum in said storage means; and

said processing means is responsive to actuation of said first non-numeric control key, when successively preceded by actuation of said second non-numeric control key, for generating the value of the least-squares linear regression for the chronological numerical datum designated by the sequence number stored in said storage means by actuation of said second non-numeric control key.

14. An electronic calculator as in claim 1 wherein said processing means is responsive to actuation of one of said non-numeric control keys for determining the percentage difference between two numerical values stored in said storage means and for thereupon causing said output means to display that percentage difference in decimal digit form.

15. An electronic calculator as in claim 1 wherein:

said processing means is operable for generating the percentage difference between two numerical values stored in said storage means; and

said non-numeric control keys include a command key manually operable with another of said non-numeric control keys, when said command key and said other non-numeric control key are successively actuated in the order mentioned, for causing said processing means to generate the percentage difference between two numerical values stored in said storage means and for thereupon causing said output means to display that percentage difference in decimal digit form.

16. An electronic calculator as in claim 1 wherein:

said numeric and non-numeric control keys are manually operable for storing numerical data representing any two calendar dates in said storage means in a predetermined decimal digit format; and

said processing means includes first means responsive to actuation of one of said non-numeric control keys for determining the number of days between any two calendar dates, included within a predetermined range of calendar dates and represented by numerical data stored in said storage means in said predetermined decimal digit format, and for causing said output means to display the determined number of days in said prdetermined decimal digit format.

17. An electronic calculator as in claim 1 wherein:

said numeric and non-numeric control keys are manually operable for storing numerical data representing an initial calendar date in said storage means in a predetermined decimal digit format and for storing numerical data representing a number of days from said initial calendar date; and

said processing means includes first means responsive to actuation of one of said non-numeric control keys for generating the calendar date of the day corresponding to said number of days from said initial calendar date, when said initial and generated calendar dates are included within a predetermined range of calendar dates, and for causing said output means to display the generated calendar date in said predetermined decimal digit format.

18. An electronic calculator as in claims 16 or 17 wherein said processing means includes:

second means responsive to actuation of said one non-numeric control key for causing said output means to indicate when numerical data stored in said storage means represents an erroneous calendar date, represents a calendar data outside said predetermined range of calendar dates, or is incompatible with said predetermined decimal digit format; and

third means for compensating for the extra day in leap-years occurring within said predetermined range of calendar dates.

19. An electronic calculator as in claim 17 wherein said non-numeric control keys include a command key manually operable with said one non-numeric control key, when said command key and said one non-numeric control key are successively actuated in the order mentioned, for causing said first means to generate the calendar date of the day corresponding to said number of days from said initial calendar date and to cause said output means to display the generated calendar date in said predetermined decimal digit format.

20. An electronic calculator as in claim 17 wherein said one non-numeric control key for generating the calendar date of the day corresponding to said number of days forward from said initial calendar date, when the numerical data representing said number of days from said initial calendar date is positive, and for

* C L M S *

generating the calendar date of the day corresponding to said number of days backward from said initial calendar date, when the numerical data representing said number of days from said intitial calendar date is negative.

21. An electronic calculator as in claim 1 wherein:

a first one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a first numerical datum designating a particular period within the depreciable life of an asset in said storage means and is manually operable with one or more of said numeric keys for storing a second numerical datum representing the total number of such periods in the depreciable life of the asset in said storage means;

a second one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a third numerical datum representing an initial value of the asset in said storage means;

said processing means is operable for generating the value of the sum-of-the-digits depreciation and the depreciated value of the initial value of the asset represented by said third numerical datum for the period designated by said first numerical datum; and

said non-numeric control keys include a command key manually operable with a third one of said non-numeric control keys, when said command key and said third non-numeric control key are successively actuated in the order mentioned, for causing said processing means to generate said value of the sum-of-the-digits depreciation and said depreciated value and for causing said output means to display said generated value of the sum-of-the-digits depreciation in decimal digit form.

22. An electronic calculator as in claim 21 wherein said processing means is responsive to further successive actuations of said third non-numeric control key for generating the value of the sum-of-the-digits depreciation of the initial value of the asset represented by said third numerical datum for each period included within the total number of periods represented by said second numerical datum subsequent to the period designated by said first numerical datum and for causing said output means to display each generated value of the sum-of-the-digits depreciation in decimal digit form.

23. An electronic calculator as in claim 21 wherein a fourth one of said non-numeric control keys is manually operable for thereafter causing said output means to display said generated depreciated value in decimal digit form.

24. An electronic calculator as in claim 1 wherein:

a first one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a first numerical datum representing the number of successive payments;

a second one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a second numerical datum representing the interest rate per payment;

a third one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a third numerical datum representing the amount of each payment; and

said processing means is responsive to actuation of a fourth one of said non-numeric control keys for generating the present value of the number of successive payments represented by said first numerical datum in the amount per payment represented by said third numerical datum and at the interest rate per payment represented by said second numerical datum and for causing said output means to display the generated present value in decimal digit form.

25. An electronic calculator as in claim 24 wherein each of said first, second, third, and fourth non-numeric control keys comprises a different one of said function keys.

26. An electronic calculator as in claim 1 wherein:

a first one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a first numerical datum representing the number of days within an interest accruing period in said storage means;

a second one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a second numerical datum representing an annual interest rate in said storage means;

a third one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a third numerical datum representing a principal amount in said storage means;

said processing means is responsive to actuation of a fourth one of said non-

* C L M S *

numeric control keys for generating the values of the amount of interest on a 360-day basis and on a 365-day basis of the principal amount represented by said third numerical datum and at the annual interest rate represented by said second numerical datum and for causing said output means to display the value of the amount of interest generated on one of said bases in decimal digit form.

27. An electronic calculator as in claim 26 wherein said non-numeric control keys include a command key manually operable with said fourth non-numeric control key, when said command key and said fourth non-numeric control key are successively actuated in the order mentioned, for causing said processing means to generate said values of the amount of interest and to cause said output means to display the value of the amount of interest generated on said one of said bases in decimal digit form.

28. An electronic calculator as in claim 26 or 27 wherein said processing means is responsive to actuation of a fifth one of said non-numeric control keys for causing said output means to display the value of the amount of interest generated on the other of said bases in decimal digit form.

29. An electronic calculator as in claim 1 wherein:

a first one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a first numerical datum representing the number of payments within an interest accruing period in said storage means;

a second one of said non-numeric control keys is manually operable with one or more of said numeric keys for storing a second numerical datum representing the annual add-on interest rate in said storage means; and

said processing means is responsive to reactuation of said second non-numeric control key, following storage of said second numerical datum in said storage means, for generating the value of an annual percentage interest rate and the value of a monthly payment factor for the number of payments represented by said first numerical datum at the annual add-on interest rate represented by said second numerical datum and for causing said output means to display the generated value of the annual percentage interest rate in decimal digit form.

30. An electronic calculator as in claim 29 wherein each of said first and second non-numeric control keys comprises a different one of said function keys.

31. An electronic calculator as in claim 29 or 30 wherein said processing means is responsive to actuation of a third one of said non-numeric control keys for causing said output means to display the generated value of the monthly payment factor in decimal digit form.

32. An electronic calculator as in claim 31 wherein said processing means is further responsive to actuation of one or more of said numeric keys for storing a third numerical datum representing the principal amount in said storage means and is thereupon responsive to actuation of a fourth one of said non-numeric control keys for generating the value of the monthly payment and for causing said output means to display the generated value of the monthly payment in decimal digit form.

33. An electronic calculator substantially as hereinbefore described with reference to the accompanying drawings.

ERIC POTTER & CLARKSON,
Chartered Patent Agents,
Kingsway House,
Kingsway,
London WC2B 6QX.

Printed for Her Majesty's Stationery Office by the Courier Press, Leamington Spa, 1976.
Published by the Patent Office, 25 Southampton Buildings, London, WC2A 1AY, from which copies may be obtained.

