

Description

The invention relates to a telephone set supplied by line direct voltage through two wires of a subscriber line, the set comprising an active line voltage stabilizer circuit connected between the aforesaid wires of the subscriber line, the circuit comprising two output terminals with there being between them a direct voltage which is independent of the line direct current, a first terminal of which being connected to a first of the aforesaid wires via a resistor substantially conducting the whole line direct current, with there being connected between this first terminal and the second wire a series arrangement composed of a capacitor and a further resistor, the capacitor connections of which constituting a direct voltage supply output.

The invention likewise relates to a line voltage stabilizer circuit suitable for use in such a telephone set.

Such a telephone set is known from the public application report "Application of the transmission circuit TEA 1060 and the supply circuit TEA 1080", report number ETT 8506, N.V. Philips' Gloeilampenfabrieken, The Netherlands, more specifically page R23, figure AP1.

The stabilizer circuit shown in the above publication comprises an operational amplifier connected to the base of an output transistor. The emitter of this output transistor, forming the first output terminal, is connected to a first wire via an emitter resistor substantially conducting the whole line direct current. The collector of the output transistor is connected to the remaining wire. A resistor (referred to as R55 in the above-mentioned figure) is connected to an input of the operational amplifier. The other side of this resistor, forming the second terminal of the stabilizer circuit, is connected in the aforesaid publication to the second wire. The latter connection achieves the direct voltage on the subscriber line to be set to the desired value by the stabilizer circuit. It should be observed that details about achieving the desired line direct voltage are described in the Dutch patent application No. 8400508, laid open to public inspection.

In modern electronic telephone sets it is desirable to have a direct voltage supply connection from where additional equipment (such as for example DTMF dial circuits or memories) can be supplied by power derived from the subscriber line. Such a supply connection should preferably meet the following three requirements:

1. within the working area of the telephone set the supply voltage must not depend on the magnitude of the DC line current;
2. the AC impedance of the telephone set, as seen from the subscriber line, must not be affected by the presence of the supply circuit;
3. when deriving direct current from the supply connection its direct voltage is only allowed to show a slight decrease, so its output impedance has to be low.

The stabilizer circuit shown in the aforesaid application report comprises a direct voltage supply connection for supplying additional equipment. Thereto a series circuit of a capacitor and a resistor is inserted between the first output terminal of this stabilizer circuit (thus the emitter of the output transistor) and one of the wires; the capacitor connections will then form the supply connection. The object of the series resistor is to avoid the series arrangement forming too low an impedance for the audio signal to be transmitted by the telephone set. This implies that the series resistor must not have a much smaller value than the line terminating impedance. A customary value for the line terminating impedance is 600Ω. As the output impedance of the supply connection is mainly formed by the aforesaid series resistor, this circuit does not meet the third requirement of having a low output impedance.

The object of the invention is to provide a telephone set comprising an active line voltage stabilizer circuit, its direct voltage supply point having a low direct current output impedance, indeed meeting the first two requirements.

To that end the telephone set according to the invention is characterized in that the second output terminal is connected to the series arrangement such that there is a resistor between this second terminal and the second wire.

As the constant voltage present between the two said terminals does not vary when supply current is derived, the output impedance of the supply connection will be equal to a possibly present resistance between the second output terminal and the relevant supply terminal, which resistance can be chosen to be low.

For certain configurations and values of the components comprised in the active stabilizer circuit, inserting a pure capacitance between the aforesaid output terminals may cause oscillations of this circuit. To avoid these oscillations the telephone set in accordance with the invention is characterized in that there is a further resistance between the second terminal and the capacitor. This resistance whose value can be selected to be low relative to the internal resistance from the aforesaid application report, now functions as a damping resistance for the undesired oscillations.

The invention and its advantages will now further be described with reference to the figure. The figure shows a telephone set comprising an active line voltage stabilizer circuit having a direct voltage supply connection in accordance with the invention.

The figure only shows the components of the telephone set which are relevant to the invention. The subscriber line to which the telephone set is connected when in operation and through which the set is power supplied, is connected to line terminals 2-1 and 2-2. Active line voltage stabilizer circuit 4 is connected to the wires 6 and 8 of this subscriber line. This circuit 4 comprises two output terminals 10-1 and 10-2, a stabilized direct voltage being present between them. Output terminal 10-1 is connected to wire 8 via resistor 12. In addition, this output terminal is connected to wire 6 via a series arrangement of a capacitor 14 and resistor 16 and a resistor 18. The terminals of capacitor 14 form the direct voltage supply output 20.

The two wires 6 and 8 are interconnected via a series arrangement of a line terminating resistance 22 and capacitor 24. The junction point of the latter two components forms a supply point for supplying the stabilizer circuit 4.

Stabilizer circuit 4 comprises an operational amplifier 26, to the output of which the base of a final transistor 28 is connected. The emitter of this final transistor is connected to output terminal 10-1, its collector being connected to wire 6. The inverting input of amplifier 26 is connected to the emitter of transistor 28 via a voltage reference 30; this voltage reference can for example be designed in the form of a single or a plurality of forward biased diodes. The non-inverting input of amplifier 26 is connected via a resistor 32 to the emitter of transistor 28, via capacitor 34 to wire 8 and via resistor 36 to output terminal 10-2.

The difference in voltage between the output terminals 10-1 and 10-2 does not depend on the line current and neither does it depend on the current derived from this output formed by the terminal pair 10-1 and 10-2, which can be appreciated from the following:

the difference in voltage between terminals 10-1 and 10-2 equals the sum of the voltages across resistor 32 and across resistor 36. The voltage across resistor 32 equals the reference voltage V_j of reference source 30, because amplifier 26 controls such that both inputs show substantially equal voltages. The voltage across resistor 36 is as many times as much as the resistance ratio of resistor 36 to resistor 32 (all direct current through resistor 36 also passes through resistor 32) so that the following holds for the direct voltage V_{10} between the terminals 10-1 and 10-2:

$$V_{10} = \left(1 + \frac{R_{36}}{R_{32}} \right) V_j \quad (1)$$

with R_{36} and R_{32} representing the value of resistor 36 and resistor 32 respectively. From formula (1) it turns out that the voltage between the output terminals 10-1 and 10-2 does not depend on the line current, neither does it depend on the current which is possibly derived from the output 20. It also turns out that the internal resistance (output impedance) shown by supply output 20, equals resistance 16; this can be chosen to be adequately small.

The alternating voltage impedance, as observed from the subscriber line (thus between wires 6 and 8) is adequately high not to affect the value of the total line terminating impedance, which can be explained as follows:

Let it be assumed that the impedance of capacitor 34 in the audio range is negligibly small with respect to resistance 36. Let it likewise be assumed that resistance 36 is large with respect to the parallel value of resistor 18 on the one hand and the series arrangement of resistor 16, capacitor 14 and resistor 12 on the other. If the ratio of components of resistance 36 and the three latter components is k , this means that on terminal 10-2 there is present k times the line signal voltage. The voltage on the noninverting input of amplifier 26 then equals the product of k times the line signal voltage and the impedance of capacitor 34 divided by resistance 36. Through the combination of stabilized circuit 4 and the supply circuit connected thereto there flow three signal currents i_1 , i_2 and i_3 . i_1 flowing through transistor 28, i_2 through resistor 36 and i_3 through resistor 16. Let it be assumed that i_2 can be neglected with respect to the other currents. The sum current is of i_1 and i_3 flows through resistor 12 causing the voltage of the inverting input of the amplifier to become equal to the product of the sum current and resistance 12. Equalization of the voltages on the two amplifier inputs will yield the following for the impedance Z of the whole circuit:

$$Z_1 = \frac{R_{12} R_{36} \omega C_{34}}{k}$$

with R_{12} being the value of resistor 12, R_{36} being the value of resistor 36 and C_{34} being the capacitance of capacitor 34.

This impedance Z_1 is equally frequency-dependent as a self-inductance and in the audio frequency range can be made sufficiently large relative to line terminating impedance.

Resistor 16, determining the internal resistance of supply point 20 is an attenuation resistance for attenuating any oscillations which can be caused by the insertion of capacitor 14 at the output of stabilizer circuit 4.

Capacitor 14 has to prevent the audio signal voltage between wires 6 and 8 from leaking to output 20. Thus the value of this capacitor has to be chosen such that for practical purposes it forms a short-circuit over the entire audio range. Likewise capacitor 14 has to short-circuit any voltage variations coming from a variable load so that they will not disturb the audio signal on the line.

The above has shown that the described stabilizer circuit with supply point meets the aforesaid requirements. A practical implementation of this circuit possesses for example the component values according to the following table:

<u>Reference numeral</u>	<u>Type of component</u>	<u>Values</u>
12	resistor	20 Ω
14	capacitor	100 μF
16	resistor	50 Ω
18	resistor	500 Ω
22	resistor	620 Ω
24	capacitor	100 μF
32	resistor	20 k Ω
34	capacitor	1 μF
36	resistor	17 k Ω

Claims

1. A telephone set supplied by line direct voltage through two wires (6,8) of a subscriber line, the set comprising an active line voltage stabilizer circuit (4) connected between the aforesaid wires of the subscriber line, the circuit comprising two output terminals (10-1,10-2) with there being between them a direct voltage which is independent of the line direct current, a first terminal (10-1) of which being connected to a first (8) of the aforesaid wires via a resistor (12) substantially conducting the whole line direct current, with there being connected between this first terminal (10-1) and the second wire (6) a series arrangement composed of a capacitor (14) and a further resistor (18), the capacitor connections of which constituting a direct voltage supply output (20), characterized in that the second output terminal (10-2) is connected to the series arrangement such that the further resistor (18) is between the second terminal (10-2) and the second wire (6).
2. A telephone set as claimed in Claim 1, characterized in that there is present between the second terminal (10-2) and the capacitor (14) a still further resistor (16).



$$Z_1 = \frac{R_{12} R_{36} \omega C_{34}}{k}$$

5

with R_{12} being the value of resistor 12, R_{36} being the value of resistor 36 and C_{34} being the capacitance of capacitor 34.

This impedance Z_1 is equally frequency-dependent as a self-inductance and in the audio frequency range can be made sufficiently large relative to line terminating impedance.

Resistor 16, determining the internal resistance of supply point 20 is an attenuation resistance for attenuating any oscillations which can be caused by the insertion of capacitor 14 at the output of stabilizer circuit 4.

Capacitor 14 has to prevent the audio signal voltage between wires 6 and 8 from leaking to output 20. Thus the value of this capacitor has to be chosen such that for practical purposes it forms a short-circuit over the entire audio range. Likewise capacitor 14 has to short-circuit any voltage variations coming from a variable load so that they will not disturb the audio signal on the line.

The above has shown that the described stabilizer circuit with supply point meets the aforesaid requirements. A practical implementation of this circuit possesses for example the component values according to the following table:

	<u>Reference numeral</u>	<u>Type of component</u>	<u>Values</u>
25	12	resistor	20 Ω
	14	capacitor	100 μF
	16	resistor	50 Ω
30	18	resistor	500 Ω
	22	resistor	620 Ω
	24	capacitor	100 μF
	32	resistor	20 k Ω
35	34	capacitor	1 μF
	36	resistor	17 k Ω

40

Claims

1. A telephone set supplied by line direct voltage through two wires (6,8) of a subscriber line, the set comprising an active line voltage stabilizer circuit (4) connected between the aforesaid wires of the subscriber line, the circuit comprising two output terminals (10-1,10-2) with there being between them a direct voltage which is independent of the line direct current, a first terminal (10-1) of which being connected to a first (8) of the aforesaid wires via a resistor (12) substantially conducting the whole line direct current, with there being connected between this first terminal (10-1) and the second wire (6) a series arrangement composed of a capacitor (14) and a further resistor (18), the capacitor connections of which constituting a direct voltage supply output (20), characterized in that the second output terminal (10-2) is connected to the series arrangement such that the further resistor (18) is between the second terminal (10-2) and the second wire (6).

55

2. A telephone set as claimed in Claim 1, characterized in that there is present between the second terminal (10-2) and the capacitor (14) a still further resistor (16).



3. A line voltage stabilizer circuit, suitable for use in a telephone set as claimed in Claim 1 or 2.

Revendications

5

1. Appareil téléphonique alimenté par une tension continue de ligne par l'intermédiaire de deux fils (6, 8) d'une ligne d'abonné, cet appareil comprenant un circuit stabilisateur de tension de ligne active (4) connecté entre les fils précités de la ligne d'abonné, ce circuit comprenant deux bornes de sortie (10-1, 10-2) entre lesquelles est présente une tension continue qui est indépendante du courant continu de ligne, une première (10-1) de ces bornes étant connectée à un premier (8) des fils précités par l'intermédiaire d'une résistance (12) conduisant en substance la totalité du courant continu de ligne, un montage en série d'un condensateur (14) et d'une autre résistance (18) étant connecté entre cette première borne (10-1) et le second fil (6), les connexions du condensateur constituant une sortie d'alimentation de tension continue (20), caractérisé en ce que la seconde borne de sortie (10-2) est connectée au montage en série, étant entendu que l'autre résistance (18) est située entre la seconde borne (10-2) et le second fil (6).
2. Appareil téléphonique suivant la revendication 1, caractérisé en ce qu'encore une autre résistance (16) est présente entre la seconde borne (10-2) et le condensateur (14).
3. Circuit stabilisateur de tension de ligne propre à être utilisé dans un appareil téléphonique suivant la revendication 1 ou 2.

20

Ansprüche

25

1. Fernsprengerät, das über zwei Adern (6,8) einer Teilnehmerleitung mit Leitungsgleichspannung gespeist wird, mit einem zwischen den genannten Adern der Teilnehmerleitung vorgesehenen aktiven Leitungsspannungsstabilisierungskreis (4), der mit zwei Ausgangsklemmen (10-1; 10-2) versehen ist, zwischen denen es eine von dem Leitungsgleichstrom unabhängige Gleichspannung gibt, wobei eine erste Anschlußklemme (10-1) über einen nahezu den ganzen Leitungsgleichstrom leitenden Widerstand (12) mit einer ersten (8) der genannten Adern verbunden ist, wobei zwischen dieser ersten Klemme (10-1) und der zweiten Ader (6) eine Reihenschaltung aus einem Kondensator (14) und einem weiteren Widerstand (18) vorgesehen ist, wobei die Kondensatoranschlüsse einen Gleichspannungsspeiseausgang (20) bilden, dadurch gekennzeichnet, daß die zweite Ausgangsklemme (10-2) derart mit der Reihenschaltung verbunden ist, daß zwischen der zweiten Klemme (10-2) und der zweiten Ader (6) ein weiterer Widerstand (18) liegt.
2. Fernsprengerät nach Anspruch 1, dadurch gekennzeichnet, daß zwischen der zweiten Klemme (10-2) und dem Kondensator (14) ein weiterer Widerstand (16) vorgesehen ist.
3. Leitungsspannungsstabilisierungskreis zum Gebrauch in einem Fernsprengerät nach Anspruch 1 oder 2.

45

50

55