

METHOD AND APPARATUS FOR PROGRAMABLY TREATING WATER IN A WATER COOLER

CROSS-REFERENCE TO RELATED APPLICATIONS

Priority of U.S. Provisional patent application No. 60/564,178, filing date 21 Apr. 2004, is hereby claimed.

U.S. Provisional patent application No. 60/564,178, filing date 21 Apr. 2004, is incorporated herein by reference.

Patent Cooperation Treaty Application PCT/US02/19158, international filing date 17 Jun. 2002, is incorporated herein by reference.

STATEMENT REGARDING FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT

Not applicable

REFERENCE TO A "MICROFICHE APPENDIX"

Not applicable

BACKGROUND

The present invention relates to a method and apparatus for programably treating water (preferably refrigerated) in a water cooler and more particularly to an improved method and apparatus for sanitizing water that is to be dispensed from a water cooler of the type having a cabinet with one or more spigots from a reservoir water supply that is hidden inside the cabinet.

There are several types of cabinet type water dispensers in use today. One of the most common types of such water dispensers is a floor standing cabinet having an open top that receives a large inverted bottle. The bottle is typically of a plastic or glass material having a constricted neck. The bottle is turned upside down and placed on the top of the cabinet with the neck of the bottle extending into a water filled reservoir so that the water seeks its own level in the reservoir during use. As a user draws water from a spigot dispenser, the liquid level in the reservoir drops until it falls below the neck of the bottle at which time water flows from the bottle and bubbles enter the bottle until pressure has equalized. Inverted bottle type water dispensers are sold by a number of companies in the United States and elsewhere. Many are refrigerated.

Other types of water dispensers have an outer cabinet that contains a reservoir or water supply. These other types of water dispensers having a cabinet include one type that stores a large bottle (such as three or five gallon) at the bottom of the cabinet. A pump transfers water from the large bottle to the reservoir. At the reservoir, the water is typically refrigerated.

Another type of water dispenser simply connects a water supply (e.g., city water, well water) directly to a reservoir that is hidden inside the cabinet. A float valve or other water level controller can be provided to insure that the reservoir is always filled with water but does not overflow. Water that is transferred from city water, well water or another source can be filtered or otherwise treated before being transmitted to the reservoir.

All of these types of water dispensers that employ cabinets typically have one or more water dispensing spigots on the outside of the cabinet. These spigots are typically manually operated, but can be automatically operated. For

example, water vending machines dispense after a consumer pays for water. The water is automatically dispensed when coins are fed to the machine.

One of the problems with cabinet style water dispensers is that of cleansing the reservoir from time to time. Because the reservoir is not air tight, it breathes allowing bacteria to enter the reservoir over a period of time. The reservoirs are typically contained within the confines of the cabinet and are not easily accessed and cleaned by consumers or end users.

For inverted bottle type dispensers, in addition to the problem of an open top, the five gallon bottles are themselves a source of bacteria and germs. Most of these bottles are transported on trucks where the bottles are exposed to outside air. They are handled by operators that typically grab the bottle at the neck, the very part of the bottle that communicates with the open reservoir during use. Unfortunately, it is difficult to convince every person that handles these bottles to wash their hands frequently enough. In order to properly sanitize such a water dispenser or cooler, the user must carefully clean the neck of the bottle prior to combining the bottle with the cabinet. Further, the user should drain and sanitize the reservoir from time to time. The cleansing of the reservoir in such a water dispenser is a time consuming project that is typically not performed at regular intervals.

The dispensing spigots that are provided on common cabinet type water dispensers can also be a source of contamination. These spigots are typically manually operated and are therefore a source of contamination from the users that operate them. Individuals have also been known to drink directly from the spigot. Therefore, sanitation of the spigots as well as the reservoir should be a part of routine maintenance.

Process ozone diffusion by bubble reactor method in small static volumes of water with abbreviated water columns to diffused ozone levels satisfactory to disinfect microorganisms in brief time periods can be difficult to achieve. An ozone generator can be used as the source of ozone. The ozone generator can include an air pump as a source of oxygen for generating ozone. The air pump preferably includes a microbial filter to filter contaminants. A diffuser can be used to diffuse the generated ozone into the water reservoir.

Various factors impact the effectiveness of bacterial removal from the water such as the microbial load, pH, temperature, conductivity, and cooler characteristics (e.g., whether an ice ring has formed which can act as a shield for microbes trapped in the ice ring). Furthermore, the variability of power supply (e.g., European power supplies versus US power supplies) can cause a generator's application to be geographically limited unless modified. Additionally, time constraints for operation of the ozone generator and diffuser can impact operation.

Additionally, in certain refrigerated reservoirs an ice ring can form inside the reservoir adjacent to the cooling coils for the reservoir. Such an ice ring can serve as a form of protection for microbes contained in the ice ring when ozone is being diffused in the reservoir. After an ozone cycle, when the ice melts wholly or partially, the trapped microbes can enter the water and thus contaminate the reservoir.

Additionally, certain waters contain loadings of bromates which can cause problems.

The above indicate a need for developing a generator and diffuser containing flexibility regarding the timing, amount, and duration of ozone generated; along with the timing, amount, and duration of air supplied. Additionally, there is a need for killing microbes which may be trapped in ice

rings. Furthermore, there is a need for addressing water containing bromates. Additionally, there is a need for addressing different types of electrical supplies for various geographical areas.

In a preferred embodiment the method and apparatus is directed to an economical means of overcoming each of the factors that limit process ozone's potential disinfecting capacity. It is concerned with the optimization of each point in small automated ozonation systems both upstream and downstream from the ozonator. The object of this effort is to devise a single, economical, high longevity system capable of sanitizing many of the shapes and sizes of water dispensers in use today.

The present invention thus provides an improved self sanitizing water dispenser apparatus as well as a method for generating ozone for cleaning the reservoir and the water contained within it.

While certain novel features of this invention shown and described below are pointed out in the annexed claims, the invention is not intended to be limited to the details specified, since a person of ordinary skill in the relevant art will understand that various omissions, modifications, substitutions and changes in the forms and details of the device illustrated and in its operation may be made without departing in any way from the spirit of the present invention. No feature of the invention is critical or essential unless it is expressly stated as being "critical" or "essential."

BRIEF SUMMARY

The drawings constitute a part of this specification and include exemplary embodiments to the invention, which may be embodied in various forms.

In a preferred embodiment the generator is programmable regarding the timing, amount, and/or duration of ozone generated and/or air supplied. In a preferred embodiment the generator is programmable regarding microbes which may be trapped in ice rings and/or water containing bromates. Furthermore in a preferred embodiment the generator can automatically adjust for different types of electrical supplies for various geographical areas.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWINGS

For a further understanding of the nature, objects, and advantages of the present invention, reference should be had to the following detailed description, read in conjunction with the following drawings, wherein like reference numerals denote like elements and wherein:

FIG. 1 is diagram of a water cooler incorporating one embodiment of a programmable controller;

FIG. 2 is diagram of a programmable controller;

FIG. 3 is a perspective view of a programmable controller;

FIG. 4 is an end view of the controller of FIG. 3;

FIG. 5 is a top view of the controller of FIG. 3 with a remote display;

FIG. 6 is a perspective view of the controller of FIG. 3 with the casing opened;

FIG. 7 is a perspective view of a pump for an ozone generator;

FIG. 8 is a perspective view of the pump in FIG. 7 with the input filter removed;

FIG. 9 is another perspective view of the controller of FIG. 3 with the casing opened;

FIG. 10 is a close up view of an ozone generation component in the controller of FIG. 3;

FIGS. 11A, 11B, 11C are parts of a circuit diagram for one embodiment of a programmable controller wherein lines A—A of FIGS. 11A and 11B are match lines and wherein lines B—B of FIGS. 11B and 11C are match lines

FIGS. 12A, 12B are parts of a diagram of a circuit board for a programmable controller of FIG. 11 and wherein lines A—A of FIGS. 12A and 12B are match lines

FIG. 13 is a diagram of the rear of the circuit board in FIG. 11;

FIGS. 14A—14B are circuit diagrams for an alternate embodiment of programmable controller wherein lines A—A of FIG. 14A and 14B are match lines;

FIG. 15 is a diagram of a circuit board for the programmable controller of FIG. 14;

FIG. 16 is a diagram of the rear of the circuit board in FIG. 15;

FIGS. 17A, 17B, 17C, 18–19, 20A, 20B, 20C, 20D, 21A, 21B, 22A, 22B, 23A, 23B, 23C, 23D, 23E, 23F, 24A, 24B, 24C, 24D, 24E, 24F, 25A, 25B, 25C, 25D, 25E, 25F, 25G, 26–30, 31A, 31B, 31C, 31D, 32A, 32B, 32C, 32D, 32E, 32F, 33A, 33B, 33C, 33D, 33E, 33F, 34A, 34B, 34C, 34D, 34E, 34F, 34G are figures from operating manuals of programmable controller

DETAILED DESCRIPTION

Detailed descriptions of one or more preferred embodiments are provided herein. It is to be understood, however, that the present invention may be embodied in various forms. Therefore, specific details disclosed herein are not to be interpreted as limiting, but rather as a basis for the claims and as a representative basis for teaching one skilled in the art to employ the present invention in any appropriate system, structure or manner.

FIG. 1 is diagram of a water cooler 10 incorporating one embodiment of a programmable controller 200. Water dispenser 10 provides an improved apparatus that sanitizes the open reservoir from time to time with ozone. The apparatus 10 includes a cabinet 20 having a lower end portion 30 and an upper end portion 40. The upper end portion 40 carries a cover 50 having an opening 60.

Opening 60 provides an annular flange 70 and a gasket 80 that define an interface between cabinet 20 and bottle 100. Bottle 100 can be any commercially available bottle, typically of a several gallon volume (e.g. five gallons). Bottle 100 can provide a constricted bottled neck 110 that is placed inside an open reservoir 15 during use. Bottle neck 110 has an opening for communicating with a reservoir 15 at the interior of cabinet 20 that holds the water product to be dispensed and consumed. When the water level 19 in reservoir 15 is lowered during use, air bubbles enter bottle 100 and water replenishes reservoir 15 until pressure equalizes.

Reservoir 15 has an interior 16 surrounded by reservoir sidewall 17 and reservoir bottom wall 18. Reservoir 15 can be, for example, generally cylindrically shaped and of a stainless steel or plastic material. Reservoir 15 can provide an open top for communicating with neck 110 of bottle 100.

During use, reservoir 15 has water level 19 that fluctuates slightly as water is dispensed and then replenished by bottle 100. One or more spigots 90, 92 can be provided for withdrawing water contained in reservoir 15. For example, a left hand spigot 90 can have a flow line that extends up to and near water level 19, thus removing ambient temperature water from reservoir 15 that is not in close proximity to the

cooling coils 34 of cooling system which includes a compressor 32. Spigot 92 can provide a port for communicating with water contained in reservoir 15. Because the refrigeration coils 34 are positioned at the lower end of reservoir 15, spigot 92 withdraws cool water. As a practical matter, a water dispenser apparatus 10 could provide either ambient temperature water, cold water or heated water if, for example, a flow line 96 were to be provided with a heating element.

For cooling the water at the lower end portion of the reservoir 15, a cooling system that includes a compressor 32 can be provided. The refrigeration system includes flow lines 35,36 in combination with compressor 32 to transmit cooling fluid to coils 34 and then to heat exchanger 37 as part of a system for cooling water in reservoir 15. Power can be provided by electrical lines, including an electrical line 22 provided with plug 24.

Water in reservoir 15 can be disinfected by ozone supplied by controller 200 operably connected to ozone generator 600.

FIG. 2 is diagram of a programmable ozone generator controller 200. FIG. 3 is a perspective view of programmable controller 200. FIG. 4 is an end view of controller 200. FIG. 5 is a top view of controller 200 with a remote display 250. FIG. 6 is a perspective view of controller 200 with casing 210 opened. FIG. 7 is a perspective view of a pump 400 for ozone generator 600. FIG. 8 is a perspective view of pump 400 with input filter 420 removed. FIG. 9 is another perspective view of controller 200 with casing 210 opened. FIG. 10 is a close up view of ozone generation component 600 which can be located in controller 200.

Generally, programmable controller 200 can comprise casing 210, display 240, programmable input 220, ozone generator 600, pump 600, and power input 280. Controller 200 can incorporate a digital computer. In one embodiment ozone generated from generator 600 can be controlled by controller 200. Ozone can be injected into reservoir 15 through a diffuser 530. Alternatively, programmable controller can include clock 280. To assist in programming ozonation, air, and compressor cycles, controller display 240 can include ozone indicator 242, gas or air flow indicator 244, and power or compressor indicator 246.

In one embodiment, a low permeability filter 510 is placed between ozone generator 600 and diffuser 530. Filter 510 is preferably of a permeability which will allow gas to flow through but resist flow of liquid (e.g., liquid water) up to a head of 10 feet of water. Alternatively, between 3 to 10 feet of water. Filter 510 can prevent liquid from forming inside of ozone generator 600 and causing a failure of generator 600. Check valves were preferred in prior embodiments, however, check valves had a tendency to stick or remain in an open position allowing liquid to pass through and accumulate in ozone generator 600. Filter 510 is preferably made from an expanded PTFE manufactured by W.L. Gore material having an average pore size of one micron. More preferably, the permeability includes a range of average pore sizes between about 0.2 microns to about 3 microns. Most preferably, the permeability includes a range of average pore sizes between about 0.5 microns to about 1.5 microns. Other materials can work where they have permeabilities preventing the formation of liquid in ozone generator 600. That is the materials generally restrict liquid flow, but allow gaseous flow. Moisture in gas (e.g., humidity) flowing through ozone generator 600 will not cause failure of ozone generator 600.

In a preferred embodiment programmable controller 200 can control the timing and/or duration and/or amount of ozone generated. In a preferred embodiment the amount of

ozone generated can be set at levels of 25%, 50%, 75%, and 100%. It is anticipated that for higher microbial loads higher percentages of ozone generation will be set. Additionally, it is anticipated that the level of ozone generated during any one time period can also be changes—for example, from higher to lower or from lower to higher or sinusoidal. In one embodiment the time ozone is generated can be programmed to occur only on certain days of the week or at certain time periods (e.g., on Wednesday and Fridays at 1300 hours) during any calendar period.

In a preferred embodiment programmable controller 200 can control the timing and/or duration and/or amount of gas (e.g., ambient air) pumped through controller 200 (e.g., for ozone generator 600 or merely for air flow to diffuser 530). For example air can be pumped through diffuser 530 before any ozone is generated. Such activity can help to remove potentially deleterious items in the water, such as bromates. Additionally, compressor 32 on the water dispenser 10 can be cut off by the controller 200 while air is being pumped. Such an event would assist in melting an ice ring in reservoir 15 (e.g., being roughly analogous to a defrost cycle in a freezer). After the ice ring was melted, controller 200 could then send ozone through diffuser 530 killing a substantial portion of the microbes in the water. Following ozone being sent through diffuser 530 programmable controller 200 could then send air through diffuser 530 removing ozone which was previously diffused through diffuser 530. Each of these events could be controlled by the programmable controller 200 and individually programmed by a user.

In a preferred embodiment programmable controller 200 can also control power to compressor 32. Some water coolers 10 make ice inside their reservoirs 15 to make sure that customers get a very cold drink of water. Before ozonation takes place, controller 200 can shut off compressor 32 to insure that all of the ice melts either before or during the ozonation cycle. Even though frozen water can be unfriendly to bacteriological growth, this option addresses the risk that an ice ring would shield certain microbes from the ozonation process. For example, compressor 32 can be shut off one or two hours before the ozonation process begins. Alternatively, compressor 32 can be shut off only during the ozonation process. Alternatively, compressor 32 is not shut off.

In an alternative embodiment programmable controller 200 can automatically adjust for different types of electrical supplies (e.g., input voltages) for various geographical areas. For example, different voltages are used in the United States and Europe. Controller 200 can include a voltage control circuit 620 which senses the supply voltage and adjusts same to power controller 200 and the items operably connected to controller 200, such as ozone generator 600, pump 400, and compressor 32.

In an alternative embodiment programmable controller 200 can be programmable on a calender. For example, programmable controller 200 can be programmed on a 999 hour repeatable calender. That is, a user can program ozonation, air pumping, and/or compressor operation individually and separately for specific start and ending periods during the 999 hour repeat cycle. Alternatively, programmable controller 200 can use a 24 hour repeat cycle and a user can program ozonation, air pumping, and/or compressor operation individually and separately for specific start and ending periods during the 24 hour cycle. Alternatively, programming ozone generation can automatically require that air be pumped during the time of ozonation regardless of whether air pumping was individually programmed to overlap with the ozonation cycle. Alternatively, more than

one cycle can be programmed for ozonation, air, refrigeration in any one programming period.

In an alternative embodiment pump 400 can be separated from programmable controller 200. Pump 400 can be fluidly connected to inlet 330 of controller 200 through tube 440. Air pumped from outlet 430 will tend to be at an elevated temperature from ambient air because of the pumping action of pump 400. Ozone generator 600 will tend to generate less ozone when the incoming air is at higher temperatures. Preferably, tube 440 is long enough to allow the air to cool down before entering ozone generator 600. It has been found that seventeen or eighteen inches (43 or 46 centimeters) for tube 440 allows the air to cool sufficiently before entering ozone generator 600. Preferably, pump 400 can pump about 2 liters per minute of air.

In one embodiment, programmable controller 200 can issue a warning signal where pump 400 has not been programmed to operate at least during the entire time that ozone generator 600 has been programmed to operate. This can increase the life of ozone generator 600, as ozone generator 600 may overheat where it is operated without air flow.

FIG. 4 is an end view of controller 200. Casing 200 can include power output 290 and power input 280. Standard receptacles for output 290 and input 280 are shown. To accommodate individual receptacle types (e.g., United States versus European) different lines can be used having the appropriate plugs or receptacles. Also shown is fuse 300 which can be a standard fuse and is designed to address excessively high current or high voltage situations. Power for pump receptacle 310 is shown as being specially formatted to restrict the ability to use a pump 400 that is not properly configured with controller 200. Output 260 is shown for remote display 250.

FIG. 5 is a top view of ozone generator controller 200 with a remote display 250. Remote display 250 can include an ozone indicator 252, power indicator 254, and error indicator 256. Remote display 250 preferably can be placed at a position where a user of water dispenser 10 can readily view the display 250. In many situations this will be spaced apart from controller 200. For example, remote display can be positioned on the front or side of water dispenser 10 where controller 200 is positioned at the rear or inside of water dispenser 10. Ozone indicator 252 will preferably light up when ozone is being generated by ozone generator 600. This can serve as a warning signal for a user to not dispense water while ozone indicator is lighted. Alternatively, ozone indicator 252 can light up not only when ozone is being generated, but for a set period of time after ozone has been generated, such as 5, 10, 15, 20, 25, or 30 minutes, or longer, which will allow time for ozone to be removed from water dispenser 10. Ozone indicator 252 can be a red light to indicate a warning or to stop. Power indicator 254 can be lighted when power is being received by controller 200. Power indicator 254 can be green to indicate a good power situation. Error indicator 256 can be lighted when a failure or error situation has occurred with controller 200. Error indicator 256 can be a yellow light to indicate caution. For example, where there has been a power interruption or where the ozone generator did not come on during a cycle, error indicator 256 can be lighted.

Alternatively, ozone indicator 252 can remain lighted where a successful ozonation cycle has occurred within a set period of time, such as within the last 24 hour period. In this case ozone indicator 252 can be a green light.

In an alternative embodiment a test button can be provided to test the ozonation cycle. Where test button is

activated, the ozonation cycle will be run for a set period of time, for example, thirty seconds. Alternatively, during the test ozone indicator 252 can be lighted where the ozonation cycle is being operated.

In an alternative embodiment a remote programming input unit 230 for programmable controller 200 can be provided. A remote programming input 230 could allow controller 200 to be located in the rear of water dispenser 10 while programming input 230 located on the front or one of the sides of dispenser 10.

FIG. 6 is a perspective view of controller 200 with casing 210 opened. FIG. 9 is another perspective view of ozone generator controller 200 with casing 210 opened. FIG. 10 is a close up view of ozone generation component 600 in ozone generator controller 200. Controller 200 can include a digital computer which includes control circuit 640 for ozone generation, control circuit 650 for air generation, and control circuit 650 for compressor 32 power. Controller 200 can also include control circuit 620 for voltage converter. The individual circuits are shown in the diagrams attached to this disclosure.

FIG. 7 is a perspective view of a pump 400 for ozone generator controller 200. FIG. 8 is a perspective view of pump 400 with input filter 420 removed. Pump 400 can include input 410, filter 420, filter cap 422, and output 430. Pump 400 can be spaced apart from or included in casing 210 for controller 200.

FIG. 11 is a circuit diagram 202 for one embodiment of programmable controller 200. FIG. 12 is a diagram of a circuit board 204 and various components for programmable controller 200. FIG. 13 is a diagram of the rear of the circuit board 204.

FIG. 14 is a circuit diagram 202' for an alternative embodiment of programmable controller 200'. FIG. 15 is a diagram of a circuit board 204' and various components for programmable controller 200'. FIG. 16 is a diagram of the rear of circuit board 204'.

Table 1 lists possible items which can be used in programmable controller 200. SIP 1000 is an operation and programming manual for programmable controller 200. Each of these items is part of the disclosure of this application and all are incorporated herein by reference.

Table 2 lists possible items which can be used in an alternative programmable controller 200. SIP 2000 is an operation and programming manual for alternative programmable controller 200. Each of these items is part of the disclosure of this application and all are incorporated herein by reference.

SIP 1000

Operation and Programming Manual

Below (FIG. 17A), please find an illustration that will show you the major functions and components of the SIP 1000.

Before the "Programming" is explained, on the next page you will find a more detailed explanation of the options on the display.

The Display

Except during programming, the SIP 1000 display shows you the current time (after it has been set properly). This is known at the "Clock State". During programming, it will show you exactly which function you are changing in the program by flashing that number. If you do not enter a

number within 30 seconds (during programming), the module will revert to the Clock State.

Below (FIG. 17B), please find an illustration of the display with an explanation of the various components.

Please note that many the above are visible only when you are using or programming that function. For example, the "PGM" on the display only shows when you are actually in Program Mode.

Function Button Overview:

You will also notice that there are four buttons on the front panel. The Four Programming Buttons are shown in FIG. 17C.

Here's a brief explanation of what the buttons do. This manual will take you step by step through the programming sequence—so it's important to get a general sense of what these buttons do now.

The "SET+" button 220A enters the number and moves you forward through FUNCTIONS

The "SET-" button 220B moves you backwards through FUNCTIONS

The "+" button 220C moves you forward through NUMBERS when you are in Programming mode. In the Clock State, it also will turn the module on, turn the module off and/or put the module in Program Mode.

The "-" button 220D moves you backwards through NUMBERS when in Programming mode. In the Clock State, it also will allow you to adjust the ozone output (25%, 50%, 75% or 100%)

All clock and timer functions are performed with these keys. If you make an incorrect entry during programming you can always go back and enter a correct number by hitting the "SET-" button.

CLOCK STATE KEY FUNCTIONS: The "+" and the "-" buttons 220C, 220D do something other than change the number when the SIP 1000 is in its Clock state (not during programming).

The "+" Button

The "+" button 220C controls the operation of the SIP module. Pressing the "+" button 220C—when not programming—will turn on the ALL ON, the PGM or the ALL OFF (FIG. 18)(explained below). Only one of these three options will be on at a time.

When the module is in ALL ON, you are overriding the program and turning the module on. If installed properly, the module will immediately begin producing ozone.

When you are in ALL OFF mode, the module is NOT running the program that was entered. The SIP 1000 is "off" and only displays the time.

When you are in PGM mode, the SIP 1000 is operating according to the setting that were last entered during the Programming (the time the module comes on, how long it is activated, etc.).

Each press of "+" button 220C switches from ALL ON to PROGRAM to ALL OFF—and then back to ALL ON. (FIG. 19). Again, this is when the module is not in programming mode.

The "-" Button

Each press of the "-" button 220D adjusts the ozone output. There are 4 bars that represent the ozone output setting.

The SIP 1000 on the Highest Setting (FIG. 20A).

Each bar represents 25%—so all four visible indicates 100%—the highest setting. Three visible is 75%. Two visible is 50% and so on.

SIP 1000 Displaying Lowest Ozone Output Setting (25%) (FIG. 20B).

SIP 1000 Displaying the Medium Setting (50%) (FIG. 20C)

SIP 1000 Displaying the Medium-High Setting (75%) (FIG. 20D)

Programming

Programming the SIP 1000 is easy once you get used to it.

A few important things to remember when programming:

When you are programming, the number you are changing will be flashing.

The “+” and the “-” buttons will move you to higher or lower numbers

The “SET+” button ENTERS the number AND moves you to the next function (see QUICK PROGRAMMING SEQUENCE OVERVIEW below).

During programming, if you fail to push a button within 30 seconds, the module will stop programming mode. However, the SIP 1000 remembers the numbers that you did program in. So, to get back to the part of the programming sequence where you left off, you only have to continually push the “SET+” button.

Here is a short overview of the programming functions. More detail is provided on the following pages.

Quick Programming Sequence Overview

STEP	BUTTON	ACTION	DETAIL
	SET+	CLOCK	Day of week
	SET+	“ ”	Hours
	SET+	“ ”	Minutes
	SET+	“ ”	Seconds
1A	SET+	OZONE TIME	Hours—How Long SIP
			Ozonates
1B	SET+	“ ”	Minutes—How Long SIP
			Ozonates
1C	SET+	“ ”	Hours—How Long SIP
			Ozonates OFF
1D	SET+	“ ”	Minutes—How Long SIP
			Ozonates OFF
1E	SET+	“ ”	Hours—What Time Ozonation
			Starts
1F	SET+	“ ”	Minutes—What Time
			Ozonation Starts
2A	SET+	AIR PUMP TIME	Hours—How Long Air Pump
			On
2B	SET+	“ ”	Minutes—How Long Air Pump
			On
2C	SET+	“ ”	Hours—How Long Air Pump
			Off
2D	SET+	“ ”	Minutes—How Long Air Pump
			Off
2E	SET+	“ ”	Hours—Time Air Pump Goes
			On
2F	SET+	“ ”	Minutes—Time Air Pump Goes
			On
3A	SET+	COMPRESSOR	Hours—How Long Compressor
			OFF
3B	SET+	“ ”	Minutes—How Long It Is OFF
3C	SET+	“ ”	Hours—How Long Compressor
			Active
3D	SET+	“ ”	Minutes—How Long
			Compressor Active
3E	SET+	“ ”	Hours—Time Compressor OFF
3F	SET+	“ ”	Minutes—Time Compressor
			OFF

The first thing you will do is set the clock to your time zone. The clock in the SIP Module is a 24-hour clock—therefore, 2:00 PM=14:00.

To begin programming, press the “Set+” button **220A**. Note the day of the week flashes. (FIG. 21A). Again, the “SET+” button **220A** ENTERS the number AND moves you to the next function

Press the “+” button **220C** or the “-” button **220D** until the correct day of the week is displayed (flashing). Please note that the words are listed as the first three letters of the English language days of the week.

Press the “SET+” **220A** button when you have the correct day and note that the day of the week stops flashing. Now the hour flashes. You have moved from setting the day of the week to setting the hour. Press the “+” button **220C** or the “-” button **220D** until the correct hour is displayed. (Remember, this is a 24-hour clock—so 4:00 PM is 16:00.)

The Hour Flashing During Programming (FIG. 21B).

Press the “SET+” button **220A** again once you have the correct hour for the time. Now, note that the minutes are flashing. Press the “+” button **220C** or the “-” button **220D** until the correct minutes are displayed.

Press “SET+” **220A** again and note that the seconds are flashing. Pressing the “+” button **220C** or the “-” button **220D** will reset the seconds to zero.

You have now set the clock to your time zone.

You are now ready to begin the programming of the SIP 1000. After you set the clock, you will set the time for three different options of programming. The first programming option is for the ozone control (when it comes on, how long it's on for, etc.). The second programming option controls the airpump. The third option controls the cooler's compressor (optional).

The SIP 1000 shows triangles along the right side of the display to show which of the three programming options you are setting (see illustration below—FIG. 22A). During programming, only one of these triangle is visible at a time.

Before you begin, determine how long you wish to circulate ozone into the cooler's reservoir, what time you'd like this cycle to turn on, and if you'd like a dissipation cycle.

EXAMPLE: This manual will use an example where the SIP 1000 will ozonate the cooler's reservoir every night at 2:00 AM for 5 minutes. Then, it will dissipate the ozone in the reservoir for an additional 5 minutes. It will also turn the compressor off one hour before the ozonation cycle and keep it off until the dissipation cycle is over.

Function Sequence of SIP 1000 (FIG. 22B).

Programming Step 1: Programing the 03

If the SIP 1000 is in the Clock state, you'll need to press “SET+” **220A** five times until you notice triangle #1 (ozone production) in the upper right of the display. You'll also see that ON become visible at the bottom of the display while the hours flash.

The Display when Programming Ozone Functions (Triangle #1) (FIG. 23A).

Step 1A:

Just like the clock, press the “+” or “-” button **220C**, **220D** to set the AMOUNT OF TIME (HOURS) that ozone will be produced. (This would rarely be used except for severe ozonation as most cycles take only minutes.

Step 1B:

Press "SET+" 220A again and notice the minutes flashing (see below). Press + or - 220C,220D to set the length of time the ozonator is to run.

Programming Ozone Run Time—0:05 Minutes (FIG. 23B).

EXAMPLE: In our example, we want the SIP 1000 to sanitize the reservoir for 5 minutes. So you'd push the "+" or "-" buttons 220C,220D until 0 was programmed in for the hours and 05 was programmed in for the minutes.

STEP 1C:

Press "SET+" 220A again and notice that the hours start flashing and "OFF" becomes visible at the bottom of the display. (FIG. 23C).

STEP 1D:

Press the "+" or "-" buttons 220C,220D to set the AMOUNT OF TIME THAT THE OZONE WILL BE OFF (how long before the next run time). First enter the hours. Press the "SET+" 220A button and then program in the minutes (again using the "+" or "-" buttons).

The Ozone is on for 0:05 Minutes—Therefore, it's Off for 23:55 (FIG. 23D).

(We created this step in the programming to allow someone to ozonate every few days.)

EXAMPLE So, in our example, we wanted a daily cycle of 5 minutes. We set the ON time for 00:05 minutes and the OFF time for 23:55 (24:00 hours minus 0:05 minutes).

STEP 1E:

Press "SET+" 220A again and notice START appears in the lower part of the display. You told the SIP 1000 how long you want it to ozonate, how long you want it to wait between ozonation cycles—now you are going to program what time it comes on.

Programming in the Hours for the Ozonation Start Time (FIG. 23E).

Press the "+" or "-" buttons 220C,220D for the hours.

STEP 1F:

Enter "SET+" 220A. Then, use the "+" or "-" buttons 220C,220D for the minutes until the clock time for desired start is shown.

EXAMPLE: In our example, we would set the time to 2:00 (see below—FIG. 23F).

The SIP 1000 Set to Turn on the Ozone at 2:00 AM (FIG. 23F).

Programming Step #2: Programming the Air Pump

Programming the Air Pump is separate from programming the Ozone production. Step 1 only programmed the SIP 1000 to make Ozone—not circulate it into the reservoir. Step 2 controls the air pump—which has two functions:

Forcing air through the SIP 1000—which converts oxygen in the air (O₂) to activated oxygen (O₃)

Forcing air into the reservoir (after the ozonation function turns off) to dissipate any ozone residual.

So, to calculate the amount of time that your air pump is on, you have to add the amount of time you will ozonate the reservoir to the amount of time you will dissipate (if at all).

Programming Step 2 and Step 3 are exactly the same sequence as Step 1—it's just that they control different things.

STEP 2A:

Press "SET+" 220A again and notice that triangle #2 (air pump) appears in the right of the display and ON becomes visible at the bottom of the display while the hours flash.

Programming the Air Pump (Triangle #2) (FIG. 24A).

Press the "+" or "-" buttons 220C,220D to set the amount of time—in hours—that the air pump would be ON. (Again you would rarely ozonate for more than a few minutes—but it's been built into the SIP 1000 just in case).

STEP 2B:

Press "SET+" 220A again and notice the minutes flashing. Press "+" or "-" 220C,220D to set the length of time (minutes) that the air pump is to run.

You'll need to set the air pump to run for AT LEAST the same amount of time as your ozonation cycle (from Step 1).

To get total Air Pump Time—you will need to ADD the (number of minutes that you'd like to ozonate) to (the number of minutes that you'd like to dissipate the water into the reservoir).

Air Pump (Triangle #2) Set to Run (On) for 10 Minutes (FIG. 24B).

EXAMPLE: Our example called for a 5-minute ozonation and then a 5-minute dissipation cycle. Since the air pump is used for both of these functions, you'll need to set the ON TIME to 10 minutes.

STEP 2C:

Press "SET+" 220A again and notice "OFF" becomes visible at the bottom of the display. You now need to program in how long you want the air pump to be off Press the "+" or "-" buttons 220C,220D to set how long (in hours) before the next run time. (FIG. 24C).

STEP 2D:

Press "SET+" 220A again and then use the "+" or "-" buttons 220C,220D to set how long (in minutes) before the next run time.

EXAMPLE: Since the example calls for the air pump to run for 10 minutes, the OFF TIME will be set for 23:50.

Air Pump Set To Stay Off For 23:50 (FIG. 24D).

STEP 2E:

Press "SET+" 220A again and notice START appears in the lower display. Press the "+" or "-" buttons 220C,220D to program the TIME (hours) that you want the AIR PUMP to START.

You have to make certain that the OZONE and AIR PUMP have the same start time.

EXAMPLE: In our example, we would set the time to 2:00 (just like Step 1E & 1F)(FIG. 24E).

STEP 2F:

Press "SET+" 220A again and press the "+" or "-" buttons 220C,220D to program in the TIME (minutes) that you want the AIR PUMP to START. (FIG. 24F).

EXAMPLE: In our example, we would set the time to 2:00 (just like Step 1 F).

Programming Step #3: Programming Compressor Control:

Some water coolers make ice inside the reservoir to make sure that the customers get a very cold drink of water. You have the option of having the SIP 1000 control the water cooler's compressor—to shut it off in advance of the ozonation cycle. This would insure that all of the ice melted before the ozonation cycle. Even though frozen water is

unfriendly to bacteriological growth, you could make sure that every drop of water in the reservoir went through the sanitation process.

Step 3A:

Press "SET+" 220A again and notice that triangle #3 (water cooler compressor control) appears in the right of the display and ON becomes visible at the bottom of the display while the hours flash.

Programming the Compressor Control (FIG. 25A).

Press the "+" or "-" buttons 220C,220D to set the amount of TIME (hours) that you want the SIP 1000 to take control of your cooler's compressor.

The time that you set here will determine HOW LONG YOUR COMPRESSOR WILL BE OFF.

STEP 3B:

Press "SET+" 220A again and notice the minutes flashing. Press "+" or "-" 220C,220D to program in the TIME (minutes) that you want the water cooler compressor is shut down.

EXAMPLE: Since the example calls for the compressor to shut off one hour in advance of the ozonation cycle—and stay off during both the ozonation and dissipation cycle—the TIME will be set to 01:10 (one hour before plus 5-minute ozonation cycle plus 5-minute dissipation cycle). (FIG. 25C).

Step 3C:

Press "SET+" 220A again and notice "OFF" becomes visible at the bottom of the display. As with steps 1C and 2C, you will now program in how long (in HOURS) the COMPRESSOR CONTROL is OFF.

Press the "+" or "-" buttons 220C,220D to set how long (in hours) before the next run time.

EXAMPLE: In our example, we would set the "wait time" to 22:50—since the SIP 1000 takes control of the compressor for 1 hour and 10 minutes. (FIG. 25C).

Step 3D:

Press "SET+" 220A again—and then use the "+" or "-" buttons 220C,220D to set how long (in minutes) before the next time that the SIP 1000 would take control of your compressor. (FIG. 25D).

Step 3E:

Press "SET+" 220A again and notice START appears in the lower display.

Press the "+" or "-" buttons 220C,220D to program in the TIME (hours) that you want the SIP 1000 to start to take control of the water cooler's compressor (by turning the compressor off). (FIG. 25E).

EXAMPLE: In our example, we would set the time at 1:00 since we wanted the SIP 1000 to take control of (turn off) the compressor at 1:00 AM.

STEP 3F:

Press "SET+" 220A again and press the "+" or "-" buttons 220C,220D to program in the TIME (minutes) that you want the COMPRESSOR to START.

Programming the Minutes Of the Compressor Control (FIG. 25F).

When programming is all done, nothing will be flashing and the time will be displayed (Clock State).

Please make sure that the SIP 1000 is set to PGM (press the "+" button 220C when in the Clock State). (FIG. 25G).

SIP 2000

Operation and Programming Manual

I. Parts of SIP 2000 (see FIG. 26)

II. Description of Function Signs of the SIP2000 Display Screen (see FIG. 27)

The SIP2000 display screen adopts LCD backlight display with data legible and clear.

The main functions include the function of displaying standard time and displaying the status of each function when setting the functions of O_3 , bump and water dispenser, when makes it convenient and easy to operate. In addition, the working status of SIP 2000 will be displayed by the external indicator light equipped by our factory. For more information, refer to item 4 Description of External Indicator Lights.

III. Description of function plug jack of SIP2000 (see FIG. 28)

The function plug jacks of this machine are reasonably distributed and convenient for operation. For operation, insert power cord A (with red mark) into the IEC Plug A (with the corresponding red mark), with the other end of the cord connected to electric supply. Insert power cord B (with green mark) into the IEC socket B (with the corresponding green mark), with the other end of the cord connected with the load (the water dispenser). Note that the plug jacks of indicator light and bump should be plugged with the right direction. FUSE is near the socket, making it more elegant and beautiful in appearance as well as more convenient to change.

IV. Description of External Indicator Lights of SIP2000 (see FIG. 29)

Note that this external indicator lights, different from the LCD display screen, are only used to display the working status of all functions when the SIP2000 machine is in normal operation. The green light is the O_3 indicator light which turns on when O_3 is in operation. The red light is the power indicator light which will turn on when it is connected to the power supply. It will go out only when there is a power cut. The yellow light is the warning indicator light which will turn on when there is a power cut or something wrong with the O_3 inside the SIP machine. The external indicator light are connected to the SIP plug jack with the external connector line with a length of 1 meter. The lights can be placed in front of the water dispenser, at its side or somewhere else the clients prefer.

V. Outline of Function Keys

There are 4 keys (see FIG. 30) 220A, 220C, 220D, 220E below the front display window to set the standard time, the function setting of O_3 , pump and water dispenser and serve as the reset key when the yellow indicator light turns on at the time when a power cut takes place.

Reset key 220E for power cut and the yellow indicator light turning on; start-up and unlocking key for O_3 , pump and water dispenser setting.

Function key 220A for time and function settings.

Press + or - 220C, 220D to set time or data.

V. Operation of Function Setting

Example of setting of adjusting time from the originally set 00:00 to 22:10.

A. Time Adjustment

1. Press the PGM key 220A, the time blinks and shows the original time setting. (FIG. 31A).

2. Press + or – key 220C,220D to set the hour section (the hour section stops blinking while the minute section blinks). Set the desired standard hour time, i.e. 0–24 hours. (FIG. 31B).

3. Press the PGM key 220A to confirm the above setting and shift to the minute section setting (the hour section blinks and the minute section stops blinking). (FIG. 31C). Press + or – key 220C,220D to set the desired standard time, the is 0–60 minutes.

4. Press the PGM key 220A to confirm the minute section setting and it will show the time, indicating that the setting is completed. (FIG. 31D). The time section does not blink and shows the current setting time. If there is a fault setting or it needs to be reset, press PGM key again to reset the time.

B. Example of Setting Operation

Adjust the following factor setting data:

- (1) O₃ 03:00 a.m. on, 03:10 a.m. off
 - (2) pump 00 a.m. on, 03:30 a.m. off
 - (3) water dispenser 01:00 a.m. off, 03:30 a.m. on
- to the required data of the example:
- (1) O₃ 02:10 a.m. on, 02:20 a.m. off
 - (2) pump 10 a.m. on, 02:40 a.m. off
 - (3) water dispenser 00:00 a.m. off, 02:40 a.m. on

The adjusting process is as follows:

1. Press ON/OFF 220E and PGM 220A key simultaneously for 3s, the time section will display the factory setting of O₃ start-up and operation time data and it blinks and displays the PGM, ON and O₃ signs. (FIG. 32A). First set the 03 start-up and operation time.

2. Press + or – key 220C,220D to set the hour section of the O₃ start-up and operation time, i.e., 0–24 hours, the time section does not blink while the minute section blinks. (FIG. 32B).

3. Press the PGM key 220A to confirm the above setting and shift to minute section setting. Press + or – key 220C, 220D to set the minute section of O₃ start-up and operation time, that is 0–60 minutes. The hour section starts blinking and the minute section stops blinking. (FIG. 32C).

4. Press PGM key 220A to confirm the above setting and shift to the setting of O₃ shutdown time. The screen will display the factory setting of O₃ shutdown time and the PGM, OFF and O₃ signs. (FIG. 32D).

5. Press + or – key 220C,220D to set the hours section (0–24 hours) of O₃ shutdown time. The hour section does not blink and the minute section blinks. (FIG. 32E).

6. Press PGM key 220A to confirm the setting of step 5 and shift to the setting of minute section of O₃ (OFF). Press + or – key 220C,220D to set the minute section (0–60 minutes) of O₃ shutdown time. The hour section blinks and the minutes section stops blinking. (FIG. 32F).

7. After the above settings are confirmed, press PGM key 220A to shift to the setting of the pump operation time. It will display the original factory setting of the pump and the signs of PGM, ON and P. (FIG. 33A).

8. Press + or – key 220C,220D to set the hour section (0–24 hours) of the pump start-up and operation time. The hour section doesn't blink while the minute section starts blinking. (FIG. 33B).

9. Press the PGM key 220A again to confirm the setting of step 8 and shift to the setting of the minute section. Press + or – key 220C,220D to set the minute section (0–60 minutes) of the pump start-up and operation time. The hour section blinks and the minute section doesn't blink. (FIG. 33C).

10. Press PGM key 220A to confirm the setting of step 9 and shift to the setting of the pump shutdown time. It will display the signs of PGM, OFF, P and the original factory setting and blinks. (FIG. 33D).

11. Press + or – key 220C,220D to set the hour section (0–24 hours) of the pump shutdown time. The hour section doesn't blink while the minute section blinks. (FIG. 33E).

12. Press PGM key 220A to confirm the setting for step 11 and shift to the minute section setting of the pump shutdown time. (FIG. 33F). Press + or – key 220C,220D to set the minute section (0–60 minutes).

13. Press PGM key 220A to confirm the above setting (pump setting) and shift to the setting of the water dispenser operation time. It will display the setting of the water dispenser shutdown time originally set by the factor as well as the PGM, OFF and COMPRESSOR signs. (FIG. 34A).

14. Press + or – key 220C,220D to set the hour section of the water dispenser shutdown time. The hour section does not blink while the minute section blinks. (FIG. 34B).

15. Press PGM key 220A to confirm the setting of step 14 and shift to the minute section setting of the water dispenser shutdown time. Press + or – key 220C,220D to set the minute (0–60 minutes). The hour section blinks while the minute section does not. (FIG. 34C).

16. Press PGM key 220A to confirm the above setting and shift to the setting of water dispenser operation time. It will display the original factory setting of start-up and operation time. (FIG. 34D).

17. Press + or – key 220C,220D to set the hour section (0–24 hours) of the water dispenser start-up and operation time. The hour section will not blink and the minute section blinks. (FIG. 34E).

18. Press PCM key 220A to confirm the setting of step 17 and shift to the minute section setting of the water dispenser start-up operation time. Press + or – key 220C,220D to set the minute section (0–60 minutes). The hour section blinks and the minute section does not. (FIG. 34F).

19. Press PGM key 220A to complete the setting, and the standard time display will work. (FIG. 34G).

VII. Display of Working Status of SIP 2000

If connected to power, the red external indicator light will turn on when SIP2000 is in operation, showing that the machine is electrified. The green indicator light will shine when O₃ is in operation. When there is a power cut, the yellow indicator light will turn on. Press ON/OFF reset key to turn off the yellow indicator light. When there is malfunction with the O₃ inside the SIP2000, the yellow indicator light will shine showing that something is wrong inside the SIP2000 machine. Call the maintenance personnel to deal with it.

It is preferred that components approved by United Laboratories (UL approved) be used for as many components as possible.

The following is a list of reference numerals:

LIST FOR REFERENCE NUMERALS

(Part No.)	(Description)
10	water dispenser
15	reservoir
16	interior
17	reservoir sidewall
18	reservoir bottom wall
19	water level
20	cabinet
22	electrical line
24	plug
30	lower end portion
32	compressor
34	cooling coils
35	flow line
36	flow line
40	upper end portion

-continued

LIST FOR REFERENCE NUMERALS

(Part No.)	(Description)
50	cover
60	opening
70	annular flange
80	gasket
90	spigot
92	spigot
96	flow line
100	bottle
102	water level in bottle
110	bottleneck
200	controller
202	circuit diagram
204	circuit board
210	casing
212	mounting bracket
220	programmable input
230	remote programmable input
240	display
242	ozone indicator
244	gas flow indicator
246	compressor indicator
248	clock
250	remote display
252	ozone indicator
254	power indicator
256	error indicator
260	output for remote display
270	support connectors
280	power input
282	plug
290	power output
300	electrical fuse
310	power for pump
330	gas input
340	gas output
400	pump
410	input for pump
420	filter
422	cap
430	output for pump
440	tubing
500	first output tubing
510	low permeability filter
520	second output tubing
530	diffuser
600	ozone generator
610	heat sink for ozone generator
620	control circuit for universal voltage converter
630	backup battery
640	control circuit for ozone generation
650	control circuit for air generation
660	control circuit for compressor power

All measurements disclosed herein are at standard temperature and pressure, at sea level on Earth, unless indicated otherwise. All materials used or intended to be used in a human being are biocompatible, unless indicated otherwise.

It will be understood that each of the elements described above, or two or more together may also find a useful application in other types of methods differing from the type described above. Without further analysis, the foregoing will so fully reveal the gist of the present invention that others can, by applying current knowledge, readily adapt it for various applications without omitting features that, from the standpoint of prior art, fairly constitute essential characteristics of the generic or specific aspects of this invention set forth in the appended claims. The foregoing embodiments are presented by way of example only; the scope of the present invention is to be limited only by the following claims.

TABLE 1

附件一：产品零部件清单

申请公司 Tianjin Vitashower International Trading Co.
 APPLICANT
 产品名称 Ozone Generator
 PRODUCT
 产品型号 OG-01
 MODEL
 申报日期 2004-03-18
 DATE

零件名称 COMPONENT	数量 AMOUNT	零件编号 COMPONENT NO.	额定值 RATINGS	零件型号 MODEL	供应商 MANUFACTUREER	UL 档案号 UL FILE No.
1 外壳 Enclosure	1		UL94V-0	ABS-I 94V-0	宁波信高股份有限公司 NINGBO XINGAO PLASTIC & CHEMICAL INDUSTRY CO LTD	E169305
2 电源线 Power Line	1		10 A/ 220 VAC	SVT	昆山阿波罗电线电缆有限公司 Kuen San Apollo Wire & Cable Co., LTD	E55351
3 热缩管 Heat Shrinkable acridine	2		VW-1	Φ 3 Φ 4	深圳市沃尔高温材料有限公司 Shenzhen Woer Heat-Shrinkable Material Co Ltd	E203950
4 地线端子 cable bug	3		10 A	RF250F	苏州源利金属企业有限公司 SUZHOU YUAN LI METAL ENTERPRISE CO LTD	E185793 E186611
5 保险丝座 Fuse holder	1		10 A 250 V	H3-12	黄国民电器有限公司 GUOMIN HUANG ELECTRIC APPLIANCE CO LTD	E223587
6 保险丝 Fuse	1		2 A/250 V	Φ 5x20	深圳市美隆电子有限公司 SHENZHEN LANSON ELECTRONICS CO., LTD	E221465
7 继电器 RELAY	1	K1	240 VAC/ 10 A	WJ108-1C	东莞万佳继电器有限公司 DONGGUAN WANJIA RELAY CO LTD	E196453
8 印制电路板 Printed circuit board	1		110 x 133		河北航凌印制电路板有限公司 HEBEI HANGLING CIRCUIT BOARD CO LTD	E235546
9 定时控制器 Timer Controller	1				深圳市时代纵横科技发展有限公司 SHENZHEN SHIDAIZONGHENG-TECH EXPLOITURE CO., LTD	
10 集成电源开关 Integrated Off-line Switcher	1	U1		TOP245Y	Power Integrations	
11 晶体管 Transistor	4	Q1 Q7 Q8 Q9		9014	Fairchild Semiconductor	
12 功率晶体管 Power Transistor	1	Q10		TIP31C	Fairchild Semiconductor	
13 功率场效应晶体管 Power MOSFET	3	Q4 Q5 Q6	100 V	IRF540	International Rectifier	
14 功率场效应晶体管 Power MOSFET	2	Q2 Q3	-100 V	IRF9540N	International Rectifier	
15 定时器 Timer	2	U3 U4		NE555	National Semiconductor	
16 光耦 Optical isolators	1	U2		H11A817	Fairchild Semiconductor	
17 整流二极管 Rectifier	4	D1 D2 D3 D4	1.0 A / 1000 V	1N4007	上海右翔股份有限公司 SHANGHAI RIGHTKING INC.	
18 整流二极管 Rectifier	1	D13	1.0 A/ 400 V	1N4004	上海右翔股份有限公司 SHANGHAI RIGHTKING INC.	
19 快速开关二极管 Fast Switching Diodes	7	D6 D7 D8 D9 D10 D11 D12		1N4148	Fairchild Semiconductor	
20 整流二极管 Rectifier	1	D5		UF4005	上海右翔股份有限公司 SHANGHAI RIGHTKING INC.	
21 瞬态电压抑制器 Transient voltage surge suppressors	1	ZD1	200 V	P6KE200	Fairchild Semiconductor	
22 稳压二极管 Zener diode	1	ZD2	10 V/ 5 mA	1N5240	Thomson Corporation (ST)	
23 稳压二极管 Zener diode	1	ZD3	3.9 V/ 5 mA	1N5228	Thomson Corporation (ST)	
24 肖特基整流二极管 Schottky Rectifier	1	SD1	10 A/ 100 V	STP20S100	Thomson Corporation (ST)	
25 瓷质电容 Ceramic capacitor	1	C9	470 pF/ 50 V DC	0805N471J	广东肇庆市星洲电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
26 电解电容 (MKT) capacitor	1	C18	0.1 uF/ 250 V DC	1206Y104M	广东肇庆市星洲电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	

TABLE 1-continued

附件一: 产品零部件清单						
申请人	Tianjin Vitashower International Trading Co.					
产品名称	Ozone Generator					
产品型号	OG-01					
填表日期	2004-03-18					
零件名称 COMPONENT	数量 AMOUNT	零件编号 COMPONENT NO.	额定值 RATINGS	零件型号 MODEL	供应商 MANUFACTURER	UL 档案号 UL FILE No.
27 独石电容 Ceramic capacitor	6	C4 C10 C11 C14 C15 C17	0.1 uF/ 50 V DC	0805Y104M	广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
28 独石电容 Ceramic capacitor	1	C5	1 uF/ 50 V DC	0805Y105M	广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
29 电容 capacitor	1	C8	2.2 nF/ 1 KV DC	CT81-1KV- 222M	常州市佳冠电子厂 CHANGZHOU JIAGUAN ELECTRONICS FACTORY	
30 电容器 capacitor	1	C1	0.1 uF/ 250 V AC	X2-0, 1M-300V AC P = 10	锐谷电子有限公司 CHIEFCON ELECTRONICS CO LTD	E209251
31 电解电容 capacitor	1	C3	47 uF/ 35 V DC	CD263	南通江海电容器厂 NANTONG JIANGHAI CAPACITOR FACTORY	
32 电解电容 capacitor	1	C2	100 uF/ 400 V DC	CD294	南通江海电容器厂 NANTONG JIANGHAI CAPACITOR FACTORY	E227010
33 电解电容 capacitor	4	C6 C7 C13 C16	470 uF/ 35 V DC	CD263	南通江海电容器厂 NANTONG JIANGHAI CAPACITOR FACTORY	
34 电解电容 capacitor	1	C12	100 uF/ 50 V DC	CD263	南通江海电容器厂 NANTONG JIANGHAI CAPACITOR FACTORY	
35 电感 inductance	1	T1	22 mH/ 1 A	VTCLB- 12-22	天津万泰克电子有限公司 TIANJIN VENTECH ELECTRONIC CO., LTD	E184446 (C) E187200 (C)
36 变压器 transformer	1	T2		VTCEE25- 19	天津万泰克电子有限公司 TIANJIN VENTECH ELECTRONIC CO., LTD	E184446 (C) E187200 (C)
37 高压包 transformer	1	T3		VTC BT-2	天津万泰克电子有限公司 TIANJIN VENTECH ELECTRONIC CO., LTD	E184446 (C) E187200 (C)
38 电阻 Resistor	1	R3	2 M/ 0.5 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
39 电阻 Resistor	1	R1	4.7 M/ 0.5 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
40 电阻 Resistor	2	R2	9.1 K/ 0.25 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
41 电阻 Resistor	2	R4 R5	150 Ω / 0.25 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
42 电阻 Resistor	1	R6	33 Ω / 0.25 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
43 电阻 Resistor	3	R16 R18 R19	10 K/ 0.25 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
44 电阻 Resistor	2	R11 R13	20 K/ 0.25 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
45 电阻 Resistor	1	R12	3 K/ 0.25 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
46 电阻 Resistor	2	R14 R21	100 K/ 0.25 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
47 电阻 Resistor	1	R22	200 Ω / 0.25 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
48 电阻 Resistor	3	R8 R9 R23	1 K/ 0.25 W		广东省肇庆市至电电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	

TABLE 1-continued

附件一：产成零部件清单						
申请公司	Tianjin Vitashower International Trading Co.					
APPLICANT						
产品名称	Ozone Generator					
PRODUCT						
产品型号	OG-01					
MODEL						
填表日期	2004-03-18					
DATE						
零件名称 COMPONENT	数量 AMOUNT	零件编号 COMPONENT NO.	额定值 RATINGS	零件型号 MODEL	供应商 MANUFACTUREER	UL 编号 UL FILE No.
49 电阻 Resistor	1	R7	400 Ω / 0.25 W		广东省肇庆市益卓电子有限公司 GUANGDONG ZHAOQING ZHIZHUO ELECTRONIC CO LTD	
50 可调电阻 Variable resistor	1	R15	200 K	EVND8AA- 200K	松下半导体公司 PANASONIC SEMICONDUCTOR COMPANY	
51 锂电池 Lithium Battery	1	BT1	3.6 V/950 mAH	ER14250	武汉未来电源有限公司 WUHAN FUTE TECHNOLOGY CO LTD	MH20923
52 排线 Ribbon Wire	1		17/0.16	1.27-10P	中国长城电子有限公司 CHINA LONSID ELECTRIC CO LTD	E205056
53 插头 10 PIN	2		10 P	UL2651 VW-1	深圳博士技术有限公司 NS-TECH CO LTD SHENZHEN	E225927
54 插座 10 PIN Socket	2		10 $\uparrow$	302S-10P	深圳博士技术有限公司 NS-TECH CO LTD SHENZHEN	E225927
55 直流插座 DC Socket	1	D14 LED	DC12 V	DS-313	深圳市芯达电子有限公司 SHENZHEN RISEDONE ELECTRONIC CO LTD	
56 气泵插座 Pump Socket	1		AC12 V		深圳兴日实业有限公司 SHENZHEN XINGRISHENG INDUSTRY CO LTD	E154283 E203950
57 散热器 Heat Sink	3		30 x 25 x 30 15 x 10 x 25	44-DAR 213-DHE	浙江亚奥散热器有限公司 ZHENJIANG YAOU HEAT SINK FACTORY	
58 玻璃管 Glass Tube	1			Φ 5x1	北京玻璃仪器厂 BEIJING GLASS INSTRUMENT FACTORY	
59 夹子 Clip	2	J26 J27		Φ 5x30	越一电子有限公司 YUEYI ELECTRONIC CO LTD	
60 胶管 Silicone Rubber Tube	2			Φ 4x6	江苏天马电子器材厂 JIANGSU TIANMA ELECTRONIC EQUIPMENT FACTORY	

TABLE 2

A Detailed List of Components and Parts
Model: SIP

No.	Component	Models	Quan- tity	No.	Component	Models	Quan- tity
1	Diodes	4007	6	29	Electrolytic Capacitors	4.7 μ F/50 V	1
2		4148	8	30		0.01 μ F/250 V	1
3		P6KE200A	1	31	Power MOSFET	IRF530N	3
4	Voltage Regulator Tubes	3.9 V	1	32		IRF9530N	2
5		10 V	1	33	Power Supply IC	TOP245Y	1
6	Metallic Resistors	2 K	5	34	Power Tubes	TIP41C	1
7		10 K	6	35	Power Tubes	STP20S	1
8		1 K	6	36	Flat Back Transformers	VTCBT-2	1
9		100 K	4	37	Impulse Transformers	VTCEE25-19	1
10		100 Ω	1	38	Wave Filtering Coils	VTCCB12-22	1
11		200 Ω	1	39	NE	555	3
12		33 K	1	40	PC	817	1
13		3.3 M	2	41	Relays	240 VAC/10 A	1
14		4.7 M	1	42	Battery	3.6 V/950 mAH	1
15		2.2 M	1	43	Ribbon wire	101W-10P	1
16		20 K	5	44	Plugs	10 pins 101W-10P	2
17		150 Ω	2	45	Sockets	10 pins 302S-10P	2

TABLE 2-continued

18		9.1 K	1	46	A.C Sockets (Air pump)	DS-313	1
19	Variable Resistors	200 K	1	47	Cooling Plates	44-DAR	3
20	Ceramic Chip Capacitors	222/1 KV	1	48	Printed Circuit Boards	12X13	1
21		105/1 KV	1	49		50X84	1
22		104/1 KV	9	50	Fuse Clamps		2
23		472/1 KV	1	51	Ozonizer Radiators		1
24	Audions	9014	14	52	LCDs		1
25		9012	1	53	Chips		1
26	Electrolytic Capacitors	100 μ f/400 V	1	54	6X6X10 Switches		4
27		1000 μ f/35 V	1	55	Capacitors	104P	4
28		47 μ f/50 V	1	56		18P	2

Haifeng Electrical Appliances Co., Ltd, Cixi City
A Detailed List of Components and Parts List
Model: SIP

No.	Component	Models	Quan- tity	No.	Component	Models	Quan- tity
1	Resistors	100 Ω	2	29			
2	Crystal Oscillators		1	30			
3	Backlight Supplies		1	31			
4	6 wire Sockets		1	32			
5	Wire Jump(ers)		13	33			
6				34			
7				35			
8				36			
9				37			
10				38			
11				39			
12				40			
13				41			
14				42			
15				43			
16				44			
17				45			
18				46			
19				47			
20				48			
21				49			
22				50			

The invention claimed is:

1. A water dispenser, comprising:

- a) a cabinet having upper and lower end portions and an interior;
- b) reservoir contained within the cabinet, the reservoir being capable of holding water;
- d) at least one spigot in fluid communication with the reservoir for dispensing water;
- e) a refrigeration system for cooling water within the reservoir;
- f) a diffuser contained within the reservoir for emitting bubbles into the reservoir;
- g) an ozone generator being operably connected to the diffuser;
- h) a digital computer operably connected to the ozone generator; and
- i) timing and duration of ozone generated by the ozone generator and sent to the diffuser is controlled by the computer; and
- j) wherein the dispenser includes a pump, the pump being operably connected to the diffuser and timing and duration of air is sent to the diffuser from the pump via the computer.

2. The water dispenser of claim 1, wherein the pump is spaced apart from the ozone generator.

3. The water dispenser of claim 2, wherein the pump is spaced sufficiently to allow air pumped by the pump to cool down closed to ambient temperature before reaching the ozone generator.

4. The water dispenser of claim 1, wherein the digital computer is programmed to have air pumped through the diffuser for a set period of time before ozone is generated.

5. The water dispenser of claim 1, wherein the digital computer is programmed to have air pumped through the diffuser for a set period of time before ozone is sent through the diffuser and a set period of time after ozone is generated.

6. The water dispenser of claim 1, wherein the digital computer is programmed to have air pumped through the diffuser for a set period of time after ozone is generated.

7. A water dispenser, comprising:

- a) a cabinet having upper and lower end portions and an interior;
- b) reservoir contained within the cabinet, the reservoir being capable of holding water;
- d) at least one spigot in fluid communication with the reservoir for dispensing water;
- e) a refrigeration system for cooling water within the reservoir;
- f) a diffuser contained within the reservoir for emitting bubbles into the reservoir;

- g) an ozone generator being operably connected to the diffuser;
- h) a digital computer operably connected to the ozone generator; and
- i) timing and duration of ozone generated by the ozone generator and sent to the diffuser is controlled by the computer; and
- j) wherein an amount of ozone generated, is chosen from 25 percent, 50 percent, 75 percent, and 100 percent ozone generation via the digital computer.

8. A water dispenser, comprising:

- a) a cabinet having upper and lower end portions and an interior;
- b) reservoir contained within the cabinet, the reservoir being capable of holding water;
- d) at least one spigot in fluid communication with the reservoir for dispensing water;
- e) a refrigeration system for cooling water within the reservoir;
- f) a diffuser contained within the reservoir for emitting bubbles into the reservoir;
- g) an ozone generator being operably connected to the diffuser;
- h) a digital computer operably connected to the ozone generator;
- i) timing and duration of ozone generated by the ozone generator and sent to the diffuser is controlled by the computer; and
- j) wherein the digital computer is operably connected to the refrigeration system and timing and duration of operation of the refrigeration system is controlled by the computer.

9. The water dispenser of claim 8, wherein the digital computer is programmed to shut off the refrigeration system a set period of time before ozone is generated.

10. The water dispenser of claim 9, wherein the refrigeration is shut off one hour before ozone is generated.

11. A water dispenser, comprising:

- a) a cabinet having upper and lower end portions and an interior;
- b) reservoir contained within the cabinet, the reservoir being capable of holding water;
- d) at least one spigot in fluid communication with the reservoir for dispensing water;
- e) a refrigeration system for cooling water within the reservoir;
- f) a diffuser contained within the reservoir for emitting bubbles into the reservoir;

- g) an ozone generator being operably connected to the diffuser;
- h) a digital computer operably connected to the ozone generator;
- i) timing and duration of ozone generated by the ozone generator and sent to the diffuser is controlled by the computer; and
- j) wherein the dispenser includes a voltage supply regulator circuit, the voltage supply regulator circuit automatically adjusting input voltage to the digital computer based on different electrical supply voltages.

12. The water dispenser of claim 11, wherein the voltage supply regulator, ozone generator, and digital computer are encased in a single case.

13. A water dispenser, comprising:

- a) a cabinet having upper and lower end portions and an interior;
- b) reservoir contained within the cabinet, the reservoir being capable of holding water;
- d) at least one spigot in fluid communication with the reservoir for dispensing water;
- e) a refrigeration system for cooling water within the reservoir;
- f) a diffuser contained within the reservoir for emitting bubbles into the reservoir;
- g) an ozone generator being operably connected to the diffuser;
- h) a digital computer operably connected to the ozone generator;
- i) timing and duration of ozone generated by the ozone generator and sent to the diffuser is controlled by the computer; and
- j) a remote display operably connected to the digital computer but spaced apart from the digital computer, the remote display having at least one indicator regarding operation of the digital computer.

14. The water dispenser of claim 13, wherein the indicator is for ozone operation.

15. The water dispenser of claim 13, wherein the remote display includes three indicators, one for ozone, a second for power, and a third for a warning signal.

16. The water dispenser of claim 15, wherein the ozone indicator is red, power indicator is green, and warning signal is yellow.