

Method for Manufacturing Single-crystal Silicon

Technical Field

5 The present invention relates to a method for manufacturing single-crystal silicon, and particularly to a method for manufacturing single-crystal silicon manufactured by a Czochralski method.

10 Background Art

The Czochralski method has been widely used in the manufacture of single-crystal silicon. In the Czochralski method, a polycrystalline material is melted in a quartz crucible, and a
15 seed crystal is brought into contact with a material melt and is pulled up, thereby growing the single-crystal silicon.

Dislocation of the single-crystal silicon occurs in some cases during growth of the single-crystal silicon. It is pointed out
20 that one of the reasons for dislocation of the single-crystal silicon is that cristobalite precipitated on an inner surface of the crucible made of quartz glass is released into the silicon melt and the cristobalite is taken into a silicon ingot when the silicon is pulled up.

25 Japanese Patent Laying-Open No. 9-110590 describes a method for promoting crystallization of quartz and preventing release of cristobalite by adhering a devitrification promoter containing an alkaline-earth metal such as barium to an inner surface of a
30 quartz crucible.

Japanese Patent Laying-Open No. 2003-160393 describes a method for reducing occurrence of dislocation during growth of single-crystal silicon by decreasing the concentration of a
35 devitrification promoter, which is adhered to an inner surface

of a quartz crucible, at a portion where the temperature during pulling-up of the single-crystal silicon is high, and increasing the concentration of the devitrification promoter at a portion where the temperature is low.

5

Problems to be Solved by the Invention

In recent years, single-crystal silicon has been manufactured using a multi-pulling method for pulling up a plurality of
10 pieces of single-crystal silicon from a material melt in an identical crucible. According to this method, a single crystal is pulled up from the material melt, and then, a polycrystalline material is additionally charged into and melted in the remaining material melt without turning off a
15 heater, and then, a next single crystal is pulled up. By repeating these steps of additionally charging the polycrystalline material into the material melt and melting the polycrystalline material in the material melt, and then, pulling up a next single crystal, the plurality of pieces of
20 single-crystal silicon is pulled up using the identical crucible.

When the plurality of silicon single crystals are pulled up in the identical crucible using the above-mentioned multi-pulling
25 method, the operation takes a long time, and thus, the crucible is also exposed to high temperature for a long time. Even if a crucible having a devitrification promoter containing barium adhered thereto is used in the manufacture of the single-crystal silicon by the multi-pulling method, dislocation occurs
30 in some cases when the single-crystal silicon is separated from the material melt.

The present invention has been made in view of the above-mentioned problems, and an object of the present invention is
35 to provide a method for manufacturing single-crystal silicon that makes it possible to reduce occurrence of dislocation of

the single-crystal silicon when the single-crystal silicon is grown using the multi-pulling method for pulling up a plurality of pieces of single-crystal silicon from a material melt in an identical crucible.

5

Means for Solving the Problems

As a result of earnest study, the inventors of the present invention have found that occurrence of dislocation of single-crystal silicon is affected by an amount (dose amount) of added barium on an inner wall surface of a crucible. When the amount (dose amount) of added barium is large, a rate of occurrence of dislocation of the single-crystal silicon is high. On the other hand, when the amount (dose amount) of added barium is small, the rate of occurrence of dislocation of the single-crystal silicon is low. When the amount (dose amount) of added barium becomes smaller than a certain amount (dose amount), the rate of occurrence of dislocation of the single-crystal silicon becomes high.

20

The reason why the rate of occurrence of dislocation of the single-crystal silicon is high when the amount (dose amount) of added barium is large is considered as follows. First, barium is melted into a silicon melt from a devitrification promoter and the like adhered to the surface of the crucible. When single-crystal silicon is pulled up to a certain length from the silicon melt having the barium melted therein, and then, the single-crystal silicon is separated, silicon solidifies before cristobalite released into the silicon melt flows down from a tail part to the silicon melt, and the cristobalite is taken into the silicon as an impurity. As a result, dislocation occurs in the single-crystal silicon and the silicon is dislocated.

35 On the other hand, when the amount (dose amount) of added barium is extremely small, the rate of occurrence of

dislocation of the single-crystal silicon is high. One of the reasons for this is considered as follows. When the amount (dose amount) of added barium is small, uniform crystallization of quartz on the inner wall of the crucible is not achieved, and thus, the cristobalite is released into the silicon melt and taken into the single-crystal silicon.

When the crucible has a large size, the temperature of the crucible during growth of the single-crystal silicon is high.

High temperature of the crucible promotes crystallization.

Therefore, the amount of barium melted into the silicon melt varies depending on the size of the crucible. Furthermore, even in the crucibles of the same size, the temperature of the crucible during growth of the single-crystal silicon is higher when the single-crystal silicon is pulled up with a magnetic field applied to the crucible than when a magnetic field is not applied to the crucible. Application of the magnetic field to the silicon melt allows suppression of convection of the silicon melt. Therefore, in order to maintain the condition similar to that when the magnetic field is not applied to the silicon melt, the temperature of the crucible must be raised.

The present invention has been made based on the above-

mentioned findings. A method for manufacturing single-crystal

silicon according to the present invention is directed to a

method for manufacturing single-crystal silicon using a multi-pulling method for pulling up a plurality of pieces of single-

crystal silicon from a material melt in an identical crucible within a chamber by a Czochralski method, the method having the

following steps. The material melt is prepared in the crucible

having a diameter of 24 inches. Single-crystal silicon is

pulled up from the material melt. A polycrystalline material

is additionally charged into and dissolved / melted in the remaining material melt while continuing heating of the material melt.

Next single-crystal silicon is pulled up from the material melt having the polycrystalline material additionally charged and

dissolved / melted therein. The step of additionally charging and dissolving / melting the polycrystalline material and the step of pulling up next single-crystal silicon are repeated one or more times. In at least one of the step of pulling up single-crystal silicon and the step of pulling up next single-crystal silicon, which is repeated one or more times, the single-crystal silicon is grown in a magnetic field. A layer containing barium is formed on an inner wall of the crucible, and an amount of the barium added to the surface of the inner wall is 2.2×10^{14} atoms $\cdot$ cm $^{-2}$ or more and 1.1×10^{15} atoms $\cdot$ cm $^{-2}$ or less.

The amount of added barium herein refers to an amount of added barium on the inner surface of the crucible per unit area. The layer containing barium may be a layer of barium alone or a layer of a barium compound such as barium carbonate or barium hydroxide. Furthermore, the layer containing barium may be a barium-rich layer obtained by injecting barium onto the surface of the crucible.

A method for manufacturing single-crystal silicon according to the present invention is directed to a method for manufacturing single-crystal silicon using a multi-pulling method for pulling up a plurality of pieces of single-crystal silicon from a material melt in an identical crucible within a chamber by a Czochralski method, the method having the following steps. The material melt is prepared in the crucible having a diameter of 32 inches. Single-crystal silicon is pulled up from the material melt. A polycrystalline material is additionally charged into and dissolved / melted in the remaining material melt while continuing heating of the material melt. Next single-crystal silicon is pulled up from the material melt having the polycrystalline material additionally charged and dissolved / melted therein. The step of additionally charging and dissolving / melting the polycrystalline material and the step of pulling up next single-crystal silicon are repeated one or more times. In at least one of the step of pulling up single-crystal silicon and

the step of pulling up next single-crystal silicon, which is repeated one or more times, the single-crystal silicon is grown in a magnetic field. A layer containing barium is formed on an inner wall of the crucible, and an amount of the barium added to the surface of the inner wall is 5.4×10^{13} atoms $\cdot$ cm $^{-2}$ or more and 2.2×10^{14} atoms $\cdot$ cm $^{-2}$ or less.

A method for manufacturing single-crystal silicon according to the present invention is directed to a method for manufacturing single-crystal silicon using a multi-pulling method for pulling up a plurality of pieces of single-crystal silicon from a material melt in an identical crucible within a chamber by a Czochralski method, the method having the following steps. The material melt is prepared in the crucible having a diameter of 40 inches. Single-crystal silicon is pulled up from the material melt. A polycrystalline material is additionally charged into and dissolved / melted in the remaining material melt while continuing heating of the material melt. Next single-crystal silicon is pulled up from the material melt having the polycrystalline material additionally charged and dissolved / melted therein. The step of additionally charging and dissolving / melting the polycrystalline material and the step of pulling up next single-crystal silicon are repeated one or more times. In at least one of the step of pulling up single-crystal silicon and the step of pulling up next single-crystal silicon, which is repeated one or more times, the single-crystal silicon is grown in a magnetic field. A layer containing barium is formed on an inner wall of the crucible, and an amount of the barium added to the surface of the inner wall is 1.1×10^{13} atoms $\cdot$ cm $^{-2}$ or more and 5.4×10^{13} atoms $\cdot$ cm $^{-2}$ or less.

Preferably, in the above-mentioned methods for manufacturing single-crystal silicon, at least one of the step of pulling up single-crystal silicon and the step of pulling up next single-crystal silicon, which is repeated one or more times, includes a step of omitting at least a part of formation of a tail part of the single-crystal silicon and separating the single-crystal

silicon from the material melt.

Effects of the Invention

5 In the method for manufacturing single-crystal silicon according to the present invention, there can be reduced occurrence of dislocation of the single-crystal silicon when the single-crystal silicon is grown using the multi-pulling method for pulling up a plurality of pieces of single-crystal
10 silicon from a material melt in an identical crucible.

Brief Description of the Drawings

Fig. 1 is a schematic view showing a single-crystal silicon
15 manufacturing device according to the present embodiment.

Fig. 2 is a schematic view showing one example of an operating state of the single-crystal silicon manufacturing device according to the present embodiment.
20

Fig. 3 is a flowchart showing a method for manufacturing single-crystal silicon according to the present embodiment.

Figs. 4(a) to (d) are explanatory views showing a process of
25 change in shape of a growth face of the single-crystal silicon.

Fig. 5 shows a relationship between a free span success rate and a dose amount of barium.

30 Fig. 6 shows a relationship between the number of remelting and the number of pulled-up silicon ingots.

Fig. 7 shows a relationship between a temperature of a crucible and a size of the crucible as well as a relationship between a
35 dose amount of barium and a size of the crucible.

Fig. 8 shows a relationship between a temperature of the crucible and presence or absence of a magnetic field as well as a relationship between a dose amount of barium and presence or absence of the magnetic field.

Best Modes for Carrying Out the Invention

An embodiment of the present invention will be described hereinafter with reference to the drawings, in which the same or corresponding portions are denoted by the same reference characters and description thereof will not be repeated.

First, a manufacturing device for manufacturing single-crystal silicon according to the present embodiment will be described with reference to Fig. 1.

As shown in Fig. 1, a single-crystal silicon manufacturing device 10 mainly has a chamber 2, a heater 6, a crucible 8, a crucible supporting shaft 13, a pulling-up wire 14, and a magnetic field generating coil 18. An inner wall of chamber 2 is provided with a heat insulating material 3. An inlet 4 through which an inert gas such as argon (Ar) is introduced is provided in the upper portion of chamber 2, and an outlet 5 through which the gas in chamber 2 is discharged is provided at the bottom of chamber 2. Crucible 8 is filled with solid silicon material to form a silicon melt 7. Heater 6 is provided around crucible 8 to melt the solid silicon material, and thereby the silicon melt 7 can be fabricated. Crucible supporting shaft 13 extends from a lower end of crucible 8 toward the bottom of the chamber and is rotatably supported by a crucible supporting shaft drive device 12. Crucible 8 can be moved up and down by crucible supporting shaft drive device 12. Pulling-up wire 14 is for pulling up single-crystal silicon 1, and can be moved up and down by a pulling-up wire drive device 15. Crucible supporting shaft drive device 12 and pulling-up

wire drive device 15 are controlled by a control device 19. By passing a current through magnetic field generating coil 18, a magnetic field can be applied to the silicon melt. A layer containing barium is formed on the inner wall of the crucible 8.

5 The layer containing barium may be a layer of barium alone or a layer of a barium compound such as barium carbonate or barium hydroxide.

Next, a method for manufacturing single-crystal silicon according to the present embodiment will be described with reference to Figs. 1 to 3.

10

As shown in Fig. 3, the method for manufacturing single-crystal silicon according to the present embodiment is directed to a method for manufacturing single-crystal silicon using the multi-pulling method for pulling up a plurality of pieces of single-crystal silicon from a material melt in an identical crucible within a chamber by the Czochralski method, and mainly has a silicon melt preparation step S1, a single-crystal silicon growth step S2, a single-crystal silicon separation step S3, a polycrystalline material charge step S4, and a single-crystal silicon growth step S5.

15

20

In silicon melt preparation step S1, crucible 8 is filled with the solid silicon material, which is heated by heater 6 in order to melt the solid silicon material. Crucible 8 has a diameter of, for example, 18 inches, 24 inches, 32 inches, 40 inches and the like. The layer containing barium is formed on the inner wall of crucible 8. An amount (dose amount) of added barium varies depending on the size of crucible 8.

25

30

The amount of added barium when the crucible has a diameter of 18 inches and the magnetic field is not applied during growth of the single-crystal silicon is 1.4×10^{16} atoms $\cdot$ cm $^{-2}$ or more and 5.4×10^{16} atoms $\cdot$ cm $^{-2}$ or less. The amount of added barium when the

35

crucible has a diameter of 24 inches and the magnetic field is not applied during growth of the single-crystal silicon is 5.4×10^{15} atoms $\cdot$ cm⁻² or more and 2.7×10^{16} atoms $\cdot$ cm⁻² or less. The amount of added barium when the crucible has a diameter of 32 inches and the magnetic field is not applied during growth of the single-crystal silicon is 1.4×10^{15} atoms $\cdot$ cm⁻² or more and 5.4×10^{15} atoms $\cdot$ cm⁻² or less.

As described below, the amount of added barium when the crucible has a diameter of 24 inches and the magnetic field is applied is 2.2×10^{14} atoms $\cdot$ cm⁻² or more and 1.1×10^{15} atoms $\cdot$ cm⁻² or less. The amount of added barium when the crucible has a diameter of 32 inches and the magnetic field is applied is 5.4×10^{13} atoms $\cdot$ cm⁻² or more and 2.2×10^{14} atoms $\cdot$ cm⁻² or less. The amount of added barium when the crucible has a diameter of 40 inches and the magnetic field is applied is 1.1×10^{13} atoms $\cdot$ cm⁻² or more and 5.4×10^{13} atoms $\cdot$ cm⁻² or less.

In single-crystal silicon growth step S2, a seed crystal attached to a seed chuck is first moved down to the surface of silicon melt 7 and immersed in silicon melt 7. Thereafter, pulling-up wire 14 is wound up by pulling-up wire drive device 15 to pull up single-crystal silicon 1. After single-crystal silicon 1 attains a target diameter through growth of a cone part (extended part), a straight part 11 is grown to have a predetermined length.

In single-crystal silicon separation step S3, straight part 11 is first grown to have the predetermined length, and then, winding-up of pulling-up wire 14 is stopped. Thereafter, crucible 8 is moved down to separate single-crystal silicon 1 from silicon melt 7. Although there are various methods as a method for separating the single-crystal silicon, it is preferable to separate the single-crystal silicon such that a

tail part thereof is as short as possible, from the viewpoint of enhancing the yield. There is a method called "free span method (tail-coneless method)" as a method for separating the single-crystal silicon to achieve the short tail part.

5 According to the free span method, when the length of the straight part reaches the predetermined length in pulling-up of single-crystal silicon 1, the crucible supporting shaft drive device starts moving up crucible 8. As shown in Fig. 2, the speed of moving up crucible 8 is set to be the same as the
10 speed of moving up single-crystal silicon 1, and single-crystal silicon 1 and crucible 8 are moved up. When crucible 8 reaches a predetermined height, moving-up of crucible 8 by crucible supporting shaft drive device 12 and winding-up of pulling-up wire 14 are stopped. Thereafter, crucible supporting shaft
15 drive device 12 causes crucible 8 to move down to separate single-crystal silicon 1 from silicon melt 7. With the above-mentioned method, single-crystal silicon 1 can be separated while minimizing formation of the tail part. It is to be noted that separation of the tail part may be implemented by a method
20 other than the free span method.

Next, polycrystalline material charge step S4 is performed. In the polycrystalline material charge step, after single-crystal silicon 1 is separated from silicon melt 7, a polycrystalline
25 material is additionally charged through a not-shown supply port into silicon melt 7 remaining in crucible 8, and the polycrystalline material is melted. When the polycrystalline material is additionally charged, heater 6 heating crucible 8 is not turned off. As a result, the polycrystalline material
30 is charged into crucible 8 while continuing heating of crucible 8.

Next, single-crystal silicon growth step S5 is performed. In this step, next single-crystal silicon 1 is pulled up from the
35 material melt (silicon melt 7) having the polycrystalline material additionally charged and melted therein. When

straight part 11 reaches the predetermined length, single-crystal silicon 1 is separated from silicon melt 7.

The single-crystal silicon separation step, the step of
5 additionally charging and melting the polycrystalline material, and the step of pulling up the next single-crystal silicon are repeated one or more times. As a result, a plurality of pieces of single-crystal silicon 1 can be pulled up. In at least one
10 of the steps of pulling up the plurality of pieces of single-crystal silicon 1, the single-crystal silicon is grown in the magnetic field. Preferably, all of the steps of pulling up the plurality of pieces of single-crystal silicon 1 are performed in the magnetic field. At least one of the steps of pulling up the plurality of pieces of single-crystal silicon 1 may include
15 a step of omitting at least a part of formation of the tail part of single-crystal silicon 1 and separating single-crystal silicon 1 from the material melt (silicon melt 7). Omission of at least a part of formation of the tail part also includes the case of separating the single-crystal silicon by the free span
20 method after partially forming the tail part.

With reference to Fig. 4, description will be given to a process of change in shape of a growth face (interface with the material melt) of single-crystal silicon 1 when single-crystal
25 silicon 1 is separated by the free span method. As shown in Fig. 4(a), the growth face of single-crystal silicon 1 during growth of straight part 11 has an upwardly convex shape. When crucible 8 starts moving up at the same speed as the pulling rate of single-crystal silicon 1, pulling-up of single-crystal
30 silicon 1 stops substantially (the relative movement of crucible 8 and single-crystal silicon 1 in the vertical direction stops). Therefore, the upwardly convex shape of the growth face of single-crystal silicon 1 is gradually relieved as shown in Fig. 4(b). After this substantially stopped state
35 is maintained for a predetermined time period, the shape of the growth face of single-crystal silicon 1 changes into a

downwardly convex shape as shown in Fig. 4(c). By separating single-crystal silicon 1 from silicon melt 7 with the growth face of single-crystal silicon 1 having the downwardly convex shape, separation is achieved while minimizing bubbling of silicon melt 7 (Fig. 4(d)). As a result, single-crystal silicon 1 can be separated from silicon melt 7 while maintaining single-crystal silicon 1 in the dislocation-free state and minimizing the length of the tail.

10 In the free span method, crucible 8 containing silicon melt 7 is moved up at the same speed as the pulling rate of single-crystal silicon 1 during growth. As a result, pulling-up of single-crystal silicon 1 is substantially stopped without considerable change in heat history of single-crystal silicon 1, and in this state, single-crystal silicon 1 is separated from silicon melt 7. Consequently, a lower end face (i.e., interface with silicon melt 7) of single-crystal silicon 1 can have the downwardly convex shape, and the single-crystal silicon can be separated from silicon melt 7 with the single-crystal silicon maintained in the dislocation-free state.

With reference to Fig. 5, description will be given to a relationship between a free span success rate when single-crystal silicon 1 is pulled up and an amount (dose amount) of addition of barium formed on the inner wall of 18-inch crucible 8. Data shown in Fig. 5 is obtained as a result of measurement without application of the magnetic field. The vertical axis indicates the free span success rate and the horizontal axis indicates the concentration of barium coating. The free span success rate refers to a ratio between the number of pulling-up of single-crystal silicon 1 and the number of pulling-up of single-crystal silicon 1 without dislocation by the free span method. In order to obtain the data, pulling-up of five single-crystal silicon 1 by the multi-pulling method is carried out ten times. The barium is added by spraying a barium hydroxide aqueous solution on the inner wall of crucible 8. As

shown in Fig. 5, when the amount (dose amount) of added barium is 1.4×10^{17} atoms $\cdot$ cm $^{-2}$ or more, the free span success rate is 40% or less. On the other hand, when the amount (dose amount) of added barium is 5.4×10^{16} atoms $\cdot$ cm $^{-2}$ or less, the free span
5 success rate is approximately 90% or more. One of the reasons why the free span success rate is low when the amount (dose amount) of added barium is large is considered as follows. The barium is dissolved in silicon melt 7 and taken into the silicon when single-crystal silicon 1 is pulled up, thereby
10 dislocating the silicon.

With reference to Fig. 6, description will be given to a relationship between the number of remelting and the number of pulled-up silicon ingots. Data shown in Fig. 6 is obtained as
15 a result of measurement without application of the magnetic field. The vertical axis indicates the number of remelting and the horizontal axis indicates the number of pulled-up ingots. Data indicated by a white circle is data when the concentration (dose amount) of barium coating is 2.7×10^{17} atoms/cm 2 . Data
20 indicated by a white triangle is data when the concentration (dose amount) of barium coating is 1.4×10^{17} atoms/cm 2 . Data indicated by a white square is data when the concentration (dose amount) of barium coating is 5.4×10^{16} atoms/cm 2 . Data indicated by a black circle is data when the concentration
25 (dose amount) of barium coating is 1.4×10^{16} atoms/cm 2 . Data indicated by a black square is data when the concentration (dose amount) of barium coating is 5.4×10^{15} atoms/cm 2 . If single-crystal silicon 1 is dislocated during pulling-up of single-crystal silicon 1, dislocated single-crystal silicon 1
30 is moved down and again melted into silicon melt 7. Thereafter, pulling-up of single-crystal silicon 1 is restarted. The number of remelting refers to the average number of remelting single-crystal silicon 1 into silicon melt 7 when single-crystal silicon 1 is dislocated. The number of pulled-up

ingots refers to the number of pulled-up ingots when a plurality of pieces of single-crystal silicon 1 is pulled up using the multi-pulling method.

5 Referring to Fig. 6, when the amount (dose amount) of added barium is 1.4×10^{16} atoms $\cdot$ cm $^{-2}$ or more, the number of remelting remain nearly unchanged even when the number of pulled-up ingots is five. However, when the amount (dose amount) of added barium is 5.4×10^{15} atoms $\cdot$ cm $^{-2}$ or less, the number of
10 remelting increases as the number of pulled-up ingots increases. As the number of remelting increases, the operation time becomes longer, which leads to an extreme decrease in productivity. In addition, heat load is applied to crucible 8 for a long time, and thus, crucible 8 may break. Therefore, in
15 view of productivity and heat load to crucible 8, the amount of added barium is desirably 1.4×10^{16} atoms $\cdot$ cm $^{-2}$ or more.

With reference to Fig. 7, description will be given to a relationship between the temperature of crucible 8 and the size
20 of crucible 8 as well as a relationship between the dose amount of barium and the size of crucible 8. Data shown in Fig. 7 is obtained as a result of measurement without application of the magnetic field. The vertical axis on the left indicates the temperature of crucible 8 and the vertical axis on the right
25 indicates the dose amount of barium. The horizontal axis indicates the diameter of crucible 8. When large-size crucible 8 is used, the temperature of crucible 8 must be raised in order to maintain the state of silicon melt 7 in crucible 8 under the condition similar to that when small-size crucible 8
30 is used. High temperature of crucible 8 promotes crystallization of the barium adhered to the inner wall of crucible 8. As crystallization of the barium is promoted, the amount of the barium melted into silicon melt 7 decreases. Therefore, an optimum amount (dose amount) of added barium
35 varies depending on the size of crucible 8. Generally, an

amount of change in temperature of crucible 8 is in inverse proportion to a rate of change in optimum amount (dose amount) of added barium. For example, when the temperature of crucible 8 rises by 20°C, the amount (dose amount) of added barium must be decreased by a factor of 10. When the temperature of crucible 8 rises by 50°C, the amount (dose amount) of added barium must be decreased by a factor of 25.

As shown in Fig. 7, when the diameter of crucible 8 is changed from 18 inches to 32 inches, the temperature of crucible 8 in pulling-up of single-crystal silicon 1 must be changed from 1430°C (18 inches) to 1450°C (32 inches). When the temperature of crucible 8 rises by 20°C, the amount (dose amount) of added barium must be decreased by a factor of 10. The optimum amount of added barium when crucible 8 has a diameter of 18 inches is 1.4×10^{16} atoms•cm⁻² or more and 5.4×10^{16} atoms•cm⁻² or less. Therefore, the optimum amount of added barium when crucible 8 has a diameter of 32 inches is 1.4×10^{15} atoms•cm⁻² or more and 5.4×10^{15} atoms•cm⁻² or less. Similarly, the optimum amount of added barium when crucible 8 has a diameter of 24 inches is 5.4×10^{15} atoms•cm⁻² or more and 2.7×10^{16} atoms•cm⁻² or less.

With reference to Fig. 8, description will be given to a relationship between the temperature of crucible 8 and presence or absence of the magnetic field as well as a relationship between the dose amount of barium and presence or absence of the magnetic field. Crucible 8 has a size of 32 inches. The vertical axis on the left indicates the temperature of crucible 8 and the vertical axis on the right indicates the dose amount of barium. The horizontal axis indicates presence or absence of the magnetic field. As shown in Fig. 8, even in crucibles 8 of the same size, the temperature of crucible 8 during growth of single-crystal silicon 1 must be higher when the single-crystal silicon is pulled up with the magnetic field applied to

crucible 8 than when the magnetic field is not applied to crucible 8. Application of the magnetic field to silicon melt 7 allows suppression of convection of silicon melt 7.

Therefore, in order to maintain the condition similar to that when the magnetic field is not applied to silicon melt 7, the temperature of crucible 8 must be raised. As shown in Fig. 8, the temperature of the crucible without the magnetic field is 1450°C, while the temperature of crucible 8 with the magnetic field must be 1500°C.

As described with reference to Fig. 7, when the temperature of crucible 8 becomes higher, the optimum amount (dose amount) of added barium must be decreased. Since the temperature of crucible 8 rises by 50°C when the magnetic field is applied, the amount (dose amount) of added barium must be decreased by a factor of 25. Therefore, the optimum amount of added barium when crucible 8 has a diameter of 24 inches and the magnetic field is applied is 2.2×10^{14} atoms•cm⁻² or more and 1.1×10^{15} atoms•cm⁻² or less. The optimum amount of added barium when crucible 8 has a diameter of 32 inches and the magnetic field is applied is 5.4×10^{-3} atoms•cm⁻² or more and 2.2×10^{14} atoms•cm⁻² or less. The optimum amount of added barium when crucible 8 has a diameter of 40 inches and the magnetic field is applied is 1.1×10^{13} atoms•cm⁻² or more and 5.4×10^{13} atoms•cm⁻² or less.

The dose amount of added barium refers to an amount of barium adhered to or contained on the inner surface of crucible 8 per square centimeter surface area, which is expressed in the number of atoms.

Next, description will be given to a method for forming the layer containing barium on the inner surface of crucible 8.

First, a barium hydroxide aqueous solution, for example, is

prepared as the layer containing barium (devitrification promoter). Next, the barium hydroxide aqueous solution is sprayed on quartz crucible 8 heated to 200 to 300°C. The barium hydroxide aqueous solution is applied using a spraying method while rotating crucible 8. An amount of adhering of the layer containing barium can be controlled in accordance with the spraying time and the like.

The layer containing barium may be formed on the inner surface of crucible 8 at a uniform amount of addition, or may be formed at different amounts of addition depending on positions on the inner surface of crucible 8. For example, a large amount of barium may be added at the bottom of crucible 8, and a small amount of barium may be added at a sidewall part and the bottom of crucible 8.

It should be understood that the embodiment disclosed herein is illustrative and not limitative in any respect. The scope of the present invention is defined by the terms of the claims, rather than the embodiment above, and is intended to include any modifications within the scope and meaning equivalent to the terms of the claims.

Claims

1. A method for manufacturing single-crystal silicon using a multi-pulling method for pulling up a plurality of pieces
5 of single-crystal silicon from a material melt in an identical crucible within a chamber by a Czochralski method, the method comprising the steps of:

preparing said material melt in said crucible having a diameter of 24 inches;

10 pulling up single-crystal silicon from said material melt;

additionally charging a polycrystalline material into remaining said material melt and dissolving the polycrystalline material in said material melt while
15 continuing heating of said material melt; and

pulling up next single-crystal silicon from said material melt having said polycrystalline material additionally charged and dissolved therein, wherein

said step of additionally charging and dissolving the polycrystalline material and said step of pulling up next
20 single-crystal silicon are repeated one or more times,

in at least one of said step of pulling up single-crystal silicon and said step of pulling up next single-crystal silicon, which is repeated one or more times, said
25 single-crystal silicon is grown in a magnetic field,

barium is added to a surface of an inner wall of said crucible, and an amount of said barium added to the surface of the inner wall is 2.2×10^{14} atoms $\cdot$ cm $^{-2}$ or more and 1.1×10^{15} atoms $\cdot$ cm $^{-2}$ or less, and

30 at least one of said step of pulling up single-crystal silicon and said step of pulling up next single-crystal silicon, which is repeated one or more times, includes a step of omitting at least a part of formation of a tail part of the single-crystal silicon and separating the single-crystal
35 silicon from said material melt.

2. A method for manufacturing single-crystal silicon using a multi-pulling method for pulling up a plurality of pieces of single-crystal silicon from a material melt in an identical crucible within a chamber by a Czochralski method, the method comprising the steps of:

preparing said material melt in said crucible having a diameter of 32 inches;

pulling up single-crystal silicon from said material melt;

additionally charging a polycrystalline material into remaining said material melt and dissolving the polycrystalline material in said material melt while continuing heating of said material melt; and

pulling up next single-crystal silicon from said material melt having said polycrystalline material additionally charged and dissolved therein, wherein

said step of additionally charging and dissolving the polycrystalline material and said step of pulling up next single-crystal silicon are repeated one or more times,

in at least one of said step of pulling up single-crystal silicon and said step of pulling up next single-crystal silicon, which is repeated one or more times, said single-crystal silicon is grown in a magnetic field,

barium is added to a surface of an inner wall of said crucible, and an amount of said barium added to the surface of the inner wall is 5.4×10^{13} atoms $\cdot$ cm $^{-2}$ or more and 2.2×10^{14} atoms $\cdot$ cm $^{-2}$ or less, and

at least one of said step of pulling up single-crystal silicon and said step of pulling up next single-crystal silicon, which is repeated one or more times, includes a step of omitting at least a part of formation of a tail part of the single-crystal silicon and separating the single-crystal silicon from said material melt.

3. A method for manufacturing single-crystal silicon using a multi-pulling method for pulling up a plurality of pieces of single-crystal silicon from a material melt in an identical crucible within a chamber by a Czochralski method, the method comprising the steps of:

preparing said material melt in said crucible having a diameter of 40 inches;

pulling up single-crystal silicon from said material melt;

10 additionally charging a polycrystalline material into remaining said material melt and dissolving the polycrystalline material in said material melt while continuing heating of said material melt; and

pulling up next single-crystal silicon from said material melt having said polycrystalline material additionally charged and dissolved therein, wherein

said step of additionally charging and dissolving the polycrystalline material and said step of pulling up next single-crystal silicon are repeated one or more times,

20 in at least one of said step of pulling up single-crystal silicon and said step of pulling up next single-crystal silicon, which is repeated one or more times, said single-crystal silicon is grown in a magnetic field,

barium is added to a surface of an inner wall of said crucible, and an amount of said barium added to the surface of the inner wall is 1.1×10^{13} atoms $\cdot$ cm $^{-2}$ or more and 5.4×10^{13} atoms $\cdot$ cm $^{-2}$ or less, and

at least one of said step of pulling up single-crystal silicon and said step of pulling up next single-crystal silicon, which is repeated one or more times, includes a step of omitting at least a part of formation of a tail part of the single-crystal silicon and separating the single-crystal silicon from said material melt.